

JANTZEN AUDIO

C- Coils - Toroidal Core

Sorted by inductance (mH)

Sizing: OD (outer diameter) x H (height)

Index:	Description:	Weight (kg):
000-6000	C-Coil 0,41mH +/-5% 0,03Ω +/-10% 1500W / 8Ω wire 1,8mm=13AWG core-30 OD85 H26	0,530
000-6002	C-Coil 0,68mH +/-5% 0,05Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD58 H25	0,280
000-6003	C-Coil 0,75mH +/-5% 0,04Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD82 H26	0,490
000-6005	C-Coil 0,82mH +/-5% 0,03Ω +/-10% 1500W / 8Ω wire 1,8mm=13AWG core-30 OD85 H26	0,520
000-6010	C-Coil 0,92mH +/-5% 0,03Ω +/-10% 1500W / 8Ω wire 1,8mm=13AWG core-30 OD85 H26	0,530
000-6017	C-Coil 0,82mH +/-5% 0,04Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD82 H26	0,490
000-6019	C-Coil 1,0mH +/-5% 0,04Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD82 H26	0,490
000-6020	C-Coil 1,0mH +/-5% 0,03Ω +/-10% 1500W / 8Ω wire 1,8mm=13AWG core-30 OD85 H28	0,550
000-6022	C-Coil 1,1mH +/-5% 0,03Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,750
000-6025	C-Coil 1,2mH +/-5% 0,06Ω +/-10% 500W / 8Ω wire 1,4mm=15AWG core-10 OD71 H25	0,320
000-6027	C-Coil 1,2mH +/-5% 0,04Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD82 H26	0,495
000-6030	C-Coil 1,3mH +/-5% 0,05Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD82 H26	0,500
000-6032	C-Coil 1,5mH +/-5% 0,08Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD71 H25	0,280
000-6035	C-Coil 1,5mH +/-5% 0,05Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD82 H26	0,530
000-6040	C-Coil 1,5mH +/-5% 0,05Ω +/-10% 1500W / 8Ω wire 1,8mm=13AWG core-30 OD85 H28	0,570
000-6045	C-Coil 1,5mH +/-5% 0,03Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,800
000-6048	C-Coil 1,7mH +/-5% 0,06Ω +/-10% 500W / 8Ω wire 1,4mm=15AWG core-10 OD71 H25	0,330
000-604818	C-Coil 1,8mH +/-5% 0,08Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD71 H25	0,330
000-6049	C-Coil 1,8mH +/-5% 0,06Ω +/-10% 500W / 8Ω wire 1,4mm=15AWG core-10 OD71 H25	0,330
000-6050	C-Coil 1,8mH +/-5% 0,06Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD84 H26	0,540
000-6055	C-Coil 1,8mH +/-5% 0,03Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,800
000-6058	C-Coil 2,0mH +/-5% 0,09Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD69 H25	0,310
000-6060	C-Coil 2,0mH +/-5% 0,06Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD84 H26	0,540
000-6065	C-Coil 2,0mH +/-5% 0,06Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-40 OD87 H31	0,610
000-6070	C-Coil 2,0mH +/-5% 0,04Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,840
000-6075	C-Coil 2,1mH +/-5% 0,05Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD104 H31	1,093
000-6080	C-Coil 2,1mH +/-5% 0,04Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,850
000-6083	C-Coil 2,2mH +/-5% 0,09Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD69 H25	0,310
000-6085	C-Coil 2,2mH +/-5% 0,06Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD83 H26	0,540
000-6090	C-Coil 2,2mH +/-5% 0,06Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-40 OD87 H31	0,610
000-6095	C-Coil 2,2mH +/-5% 0,04Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,850
000-6097	C-Coil 2,2mH +/-5% 0,04Ω +/-10% 4000W / 8Ω wire 2,0mm=12AWG core-300 OD132 H42	2,334
000-6098	C-Coil 2,5mH +/-5% 0,09Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD71 H25	0,310
000-6100	C-Coil 2,5mH +/-5% 0,07Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD83 H28	0,545
000-6102	C-Coil 2,5mH +/-5% 0,05Ω +/-10% 4000W / 8Ω wire 2,0mm=12AWG core-300 OD133 H42	2,250
000-6103	C-Coil 2,7mH +/-5% 0,09Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD71 H25	0,310
000-6105	C-Coil 2,7mH +/-5% 0,07Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD83 H28	0,545
000-6110	C-Coil 2,7mH +/-5% 0,04Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,870
000-6111	C-Coil 2,7mH +/-5% 0,08Ω +/-10% 4000W / 8Ω wire 2,5mm=10AWG core-200 OD123 H40	1,844
000-611128	C-Coil 2,8mH +/-5% 0,05Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,870
000-6112	C-Coil 3,0mH +/-5% 0,10Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD71 H25	0,310
000-6115	C-Coil 3,0mH +/-5% 0,07Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD82 H28	0,560
000-6120	C-Coil 3,0mH +/-5% 0,07Ω +/-10% 1500W / 8Ω wire 1,8mm=13AWG core-40 OD87 H31	0,720
000-6122	C-Coil 3,0mH +/-5% 0,04Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,880
000-6123	C-Coil 3,0mH +/-5% 0,03Ω +/-10% 5000W / 8Ω wire 2,5mm=10AWG core-300 OD133 H42	2,380
000-6125	C-Coil 3,3mH +/-5% 0,07Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD84 H28	0,550
000-6130	C-Coil 3,3mH +/-5% 0,07Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD92 H30	0,790
000-6135	C-Coil 3,3mH +/-5% 0,04Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,880
000-6140	C-Coil 3,5mH +/-5% 0,09Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD71 H25	0,310
000-6142	C-Coil 3,5mH +/-5% 0,08Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD84 H28	0,570
000-6145	C-Coil 3,6mH +/-5% 0,07Ω +/-10% 1500W / 8Ω wire 1,8mm=13AWG core-40 OD87 H31	0,720
000-6147	C-Coil 3,6mH +/-5% 0,04Ω +/-10% 5000W / 8Ω wire 2,5mm=10AWG core-300 OD133 H42	2,380
000-6150	C-Coil 3,9mH +/-5% 0,10Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD71 H25	0,310
000-6155	C-Coil 3,9mH +/-5% 0,08Ω +/-10% 500W / 8Ω wire 1,4mm=15AWG core-10 OD71 H25	0,372
000-6160	C-Coil 3,9mH +/-5% 0,08Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-30 OD84 H28	0,570
000-6165	C-Coil 3,9mH +/-5% 0,09Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-40 OD87 H31	0,665
000-6170	C-Coil 3,9mH +/-5% 0,07Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD92 H30	0,790
000-6180	C-Coil 3,9mH +/-5% 0,07Ω +/-10% 1500W / 8Ω wire 1,8mm=13AWG core-40 OD87 H31	0,725
000-6190	C-Coil 3,9mH +/-5% 0,05Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,900
000-6196	C-Coil 3,9mH +/-5% 0,08Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-300 OD133 H42	2,220
000-6197	C-Coil 4,0mH +/-5% 0,06Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-50 OD92 H33	0,820
000-6200	C-Coil 4,0mH +/-5% 0,08Ω +/-10% 500W / 8Ω wire 1,4mm=15AWG core-10 OD71 H25	0,380
000-6202	C-Coil 4,0mH +/-5% 0,05Ω +/-10% 2500W / 8Ω wire 2,0mm=12AWG core-100 OD106 H37	1,190
000-6204	C-Coil 4,2mH +/-5% 0,07Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H30	0,810
000-6205	C-Coil 4,2mH +/-5% 0,05Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,885
000-6206	C-Coil 4,3mH +/-5% 0,05Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,885

Index:	Description:	Weight (kg):
000-6207	C-Coil 4,4mH +/-5% 0,05Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,885
000-6208	C-Coil 4,4mH +/-5% 0,10Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD104 H35	1,193
000-6210	C-Coil 4,5mH +/-5% 0,09Ω +/-10% 500W / 8Ω wire 1,4mm=15AWG core-10 OD71 H25	0,380
000-6215	C-Coil 4,5mH +/-5% 0,07Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H30	0,810
000-6220	C-Coil 4,5mH +/-5% 0,10Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD104 H35	1,193
000-6222	C-Coil 4,6mH +/-5% 0,07Ω +/-10% 2500W / 8Ω wire 1,8mm=13AWG core-300 OD132 H42	2,500
000-6223	C-Coil 4,7mH +/-5% 0,13Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD71 H25	0,330
000-6225	C-Coil 4,7mH +/-5% 0,07Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H30	0,810
000-6230	C-Coil 4,7mH +/-5% 0,07Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-50 OD94 H33	0,910
000-6240	C-Coil 4,7mH +/-5% 0,10Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD106 H35	1,150
000-6245	C-Coil 4,7mH +/-5% 0,05Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H32	0,899
000-6255	C-Coil 5,0mH +/-5% 0,13Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD71 H25	0,330
000-6260	C-Coil 5,0mH +/-5% 0,10Ω +/-10% 500W / 8Ω wire 1,4mm=15AWG core-10 OD71 H25	0,400
000-6265	C-Coil 5,0mH +/-5% 0,07Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-50 OD94 H33	0,915
000-626851	C-Coil 5,1mH +/-5% 0,07Ω +/-10% 4000W / 8Ω wire 2,0mm=12AWG core-300 OD132 H42	2,320
000-6270	C-Coil 5,2mH +/-5% 0,08Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H32	0,830
000-6275	C-Coil 5,2mH +/-5% 0,07Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-50 OD94 H33	0,930
000-6277	C-Coil 5,2mH +/-5% 0,05Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H34	0,915
000-6278	C-Coil 5,3mH +/-5% 0,05Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H34	0,915
000-627853	C-Coil 5,3mH +/-5% 0,07Ω +/-10% 4000W / 8Ω wire 2,0mm=12AWG core-300 OD131 H42	2,320
000-627854	C-Coil 5,4mH +/-5% 0,11Ω +/-10% 800W / 8Ω wire 1,4mm=15AWG core-30 OD80 H26	0,550
000-6278542	C-Coil 5,4mH +/-5% 0,05Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H34	0,915
000-6279	C-Coil 5,5mH +/-5% 0,11Ω +/-10% 800W / 8Ω wire 1,4mm=15AWG core-30 OD80 H26	0,550
000-6280	C-Coil 5,6mH +/-5% 0,13Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD71 H25	0,330
000-6285	C-Coil 5,6mH +/-5% 0,11Ω +/-10% 500W / 8Ω wire 1,4mm=15AWG core-10 OD71 H25	0,400
000-6290	C-Coil 5,6mH +/-5% 0,12Ω +/-10% 800W / 8Ω wire 1,4mm=15AWG core-30 OD80 H26	0,560
000-6292	C-Coil 5,6mH +/-5% 0,11Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-40 OD90 H31	0,680
000-6295	C-Coil 5,6mH +/-5% 0,08Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H32	0,830
000-6300	C-Coil 5,6mH +/-5% 0,07Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-50 OD94 H33	0,860
000-6303	C-Coil 5,6mH +/-5% 0,08Ω +/-10% 2500W / 8Ω wire 1,8mm=13AWG core-300 OD132 H42	2,500
000-6305	C-Coil 5,6mH +/-5% 0,05Ω +/-10% 2000W / 8Ω wire 2,0mm=12AWG core-50 OD95 H34	0,915
000-6306	C-Coil 5,6mH +/-5% 0,07Ω +/-10% 4000W / 8Ω wire 2,0mm=12AWG core-300 OD131 H42	2,320
000-6310	C-Coil 5,8mH +/-5% 0,08Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-50 OD94 H33	0,865
000-6315	C-Coil 6,0mH +/-5% 0,11Ω +/-10% 500W / 8Ω wire 1,4mm=15AWG core-10 OD71 H25	0,410
000-6317	C-Coil 6,0mH +/-5% 0,07Ω +/-10% 2500W / 8Ω wire 2,0mm=12AWG core-100 OD106 H37	1,240
000-6320	C-Coil 6,2mH +/-5% 0,09Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H32	0,815
000-6324	C-Coil 6,2mH +/-5% 0,08Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD106 H35	1,200
000-6325	C-Coil 6,3mH +/-5% 0,10Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD106 H35	1,200
000-6330	C-Coil 6,3mH +/-5% 0,07Ω +/-10% 2500W / 8Ω wire 2,0mm=12AWG core-100 OD107 H37	1,270
000-6335	C-Coil 6,4mH +/-5% 0,24Ω +/-10% 400W / 8Ω wire 1,0mm=18AWG core-30 OD81 H26	0,500
000-6340	C-Coil 6,4mH +/-5% 0,10Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H32	0,820
000-6345	C-Coil 6,4mH +/-5% 0,11Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-100 OD108 H32	1,140
000-6350	C-Coil 6,6mH +/-5% 0,10Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H32	0,820
000-6353	C-Coil 6,7mH +/-5% 0,14Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD71 H25	0,360
000-6355	C-Coil 6,8mH +/-5% 0,17Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD71 H25	0,360
000-6360	C-Coil 6,8mH +/-5% 0,12Ω +/-10% 500W / 8Ω wire 1,4mm=15AWG core-10 OD71 H25	0,410
000-6365	C-Coil 6,8mH +/-5% 0,14Ω +/-10% 800W / 8Ω wire 1,4mm=15AWG core-30 OD84 H27	0,570
000-6370	C-Coil 6,8mH +/-5% 0,10Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H32	0,840
000-6371	C-Coil 6,8mH +/-5% 0,12Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-100 OD108 H32	1,160
000-6380	C-Coil 6,8mH +/-5% 0,10Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD105 H35	1,210
000-6390	C-Coil 6,8mH +/-5% 0,07Ω +/-10% 2500W / 8Ω wire 2,0mm=12AWG core-100 OD107 H37	1,280
000-6395	C-Coil 6,8mH +/-5% 0,08Ω +/-10% 3000W / 8Ω wire 2,0mm=12AWG core-200 OD120 H40	1,836
000-6398	C-Coil 7,0mH +/-5% 0,10Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD105 H35	1,240
000-6405	C-Coil 7,5mH +/-5% 0,10Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD105 H35	1,240
000-6408	C-Coil 7,8mH +/-5% 0,15Ω +/-10% 800W / 8Ω wire 1,4mm=15AWG core-30 OD82 H27	0,580
000-6410	C-Coil 8,0mH +/-5% 0,08Ω +/-10% 2500W / 8Ω wire 2,0mm=12AWG core-100 OD107 H37	1,300
000-6415	C-Coil 8,2mH +/-5% 0,19Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD71 H25	0,370
000-6416	C-Coil 8,2mH +/-5% 0,17Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-30 OD81 H26	0,524
000-6428	C-Coil 8,0mH +/-5% 0,11Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H32	0,830
000-6430	C-Coil 8,2mH +/-5% 0,11Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H32	0,855
000-6440	C-Coil 8,2mH +/-5% 0,10Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-50 OD93 H33	0,915
000-6450	C-Coil 8,2mH +/-5% 0,11Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD104 H35	1,250
000-6455	C-Coil 8,2mH +/-5% 0,08Ω +/-10% 2500W / 8Ω wire 2,0mm=12AWG core-100 OD107 H37	1,320
000-6460	C-Coil 8,2mH +/-5% 0,08Ω +/-10% 3000W / 8Ω wire 2,0mm=12AWG core-200 OD120 H40	1,875
000-6461	C-Coil 8,2mH +/-5% 0,08Ω +/-10% 4000W / 8Ω wire 2,0mm=12AWG core-300 OD133 H43	2,400
000-6463	C-Coil 8,5mH +/-5% 0,16Ω +/-10% 800W / 8Ω wire 1,4mm=15AWG core-30 OD82 H27	0,570
000-6465	C-Coil 8,8mH +/-5% 0,16Ω +/-10% 800W / 8Ω wire 1,4mm=15AWG core-30 OD82 H27	0,580
000-6467	C-Coil 9,0mH +/-5% 0,11Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H32	0,855
000-6468	C-Coil 9,0mH +/-5% 0,10Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD105 H35	1,220
000-6469	C-Coil 9,6mH +/-5% 0,11Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H32	0,870
000-6469-8	C-Coil 9,8mH +/-5% 0,11Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H32	0,870
000-6470	C-Coil 10,0mH +/-5% 0,21Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-10 OD69 H26	0,360
000-6480	C-Coil 10,0mH +/-5% 0,18Ω +/-10% 800W / 8Ω wire 1,4mm=15AWG core-30 OD83 H27	0,600
000-6485	C-Coil 10,0mH +/-5% 0,11Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD93 H32	0,870
000-6495	C-Coil 10,0mH +/-5% 0,12Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD105 H35	1,282
000-6500	C-Coil 10,0mH +/-5% 0,09Ω +/-10% 2500W / 8Ω wire 2,0mm=12AWG core-100 OD107 H37	1,350
000-6505	C-Coil 10,0mH +/-5% 0,09Ω +/-10% 3000W / 8Ω wire 2,0mm=12AWG core-200 OD120 H40	1,875
000-6506	C-Coil 10,0mH +/-5% 0,09Ω +/-10% 4000W / 8Ω wire 2,0mm=12AWG core-300 OD133 H42	2,437
000-6508	C-Coil 10,5mH +/-5% 0,12Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD89 H32	0,910

Index:	Description:	Weight (kg):
000-6510	C-Coil 11,0mH +/-5% 0,09Ω +/-10% 3000W / 8Ω wire 2,0mm=12AWG core-200 OD120 H40	1,900
000-6515	C-Coil 12,0mH +/-5% 0,11Ω +/-10% 1500W / 8Ω wire 1,6mm=14AWG core-50 OD94 H32	0,910
000-6525	C-Coil 12,0mH +/-5% 0,15Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-100 OD104 H35	1,240
000-6530	C-Coil 12,0mH +/-5% 0,14Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD106 H36	1,320
000-6535	C-Coil 12,0mH +/-5% 0,10Ω +/-10% 3000W / 8Ω wire 2,0mm=12AWG core-200 OD120 H40	1,930
000-6540	C-Coil 13,0mH +/-5% 0,10Ω +/-10% 3000W / 8Ω wire 2,0mm=12AWG core-200 OD120 H40	1,930
000-6542	C-Coil 13,3mH +/-5% 0,25Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-40 OD87 H28	0,648
000-6545	C-Coil 14,0mH +/-5% 0,10Ω +/-10% 3000W / 8Ω wire 2,0mm=12AWG core-200 OD120 H40	1,950
000-6550	C-Coil 14,0mH +/-5% 0,10Ω +/-10% 4000W / 8Ω wire 2,0mm=12AWG core-300 OD130 H42	2,500
000-6555	C-Coil 15,0mH +/-5% 0,31Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-40 OD87 H31	0,666
000-6565	C-Coil 15,0mH +/-5% 0,16Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-100 OD105 H35	1,270
000-6570	C-Coil 15,0mH +/-5% 0,16Ω +/-10% 2000W / 8Ω wire 1,8mm=13AWG core-100 OD105 H38	1,360
000-6575	C-Coil 15,0mH +/-5% 0,11Ω +/-10% 3000W / 8Ω wire 2,0mm=12AWG core-200 OD121 H43	1,993
000-6577	C-Coil 16,0mH +/-5% 0,16Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-100 OD105 H36	1,280
000-6579	C-Coil 16,8mH +/-5% 0,17Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-100 OD105 H36	1,250
000-6580	C-Coil 17,0mH +/-5% 0,11Ω +/-10% 4000W / 8Ω wire 2,0mm=12AWG core-300 OD130 H42	2,520
000-6588	C-Coil 18,0mH +/-5% 0,30Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-50 OD91 H32	0,774
000-6595	C-Coil 18,0mH +/-5% 0,17Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-100 OD105 H36	1,290
000-6596	C-Coil 18,8mH +/-5% 0,17Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-100 OD105 H36	1,290
000-6597	C-Coil 18,0mH +/-5% 0,18Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-200 OD120 H42	1,790
000-6602	C-Coil 20,0mH +/-5% 0,30Ω +/-10% 500W / 8Ω wire 1,2mm=17AWG core-50 OD91 H32	0,830
000-6603	C-Coil 20,0mH +/-5% 0,2?Ω +/-10% 1000W / 8Ω 1,4mm=15AWG core-100 OD104 H36	1,200
000-6605	C-Coil 20,0mH +/-5% 0,18Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-100 OD104 H36	1,310
000-6606	C-Coil 22,0mH +/-5% 0,20Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-100 OD104 H36	1,310
000-6609	C-Coil 22,0mH +/-5% 0,15Ω +/-10% 2500W / 8Ω wire 1,80mm=13AWG core-200 OD120 H40	1,900
000-6610	C-Coil 22,0mH +/-5% 0,14Ω +/-10% 3000W / 8Ω wire 2,0mm=12AWG core-200 OD122 H40	2,090
000-6615	C-Coil 24,0mH +/-5% 0,16Ω +/-10% 2500W / 8Ω wire 1,8mm=13AWG core-300 OD133 H42	2,500
000-6618	C-Coil 25,0mH +/-5% 0,23Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-200 OD120 h42	1,910
000-6619	C-Coil 25,0mH +/-5% 0,14Ω +/-10% 4000W / 8Ω wire 2,0mm=12AWG core-300 OD133 H42	2,638
000-6620	C-Coil 26,0mH +/-5% 0,23Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-200 OD120 h42	1,900
000-6622	C-Coil 27,0mH +/-5% 0,23Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-200 OD120 H42	1,900
000-6625	C-Coil 34,0mH +/-5% 0,29Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-300 OD132 H44	2,560
000-6630	C-Coil 36,0mH +/-5% 0,30Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-200 OD122 H42	2,000
000-6635	C-Coil 38,0mH +/-5% 0,30Ω +/-10% 1500W / 8Ω 1,6mm=14AWG core-300 OD132 H44	2,600