

## Air Core Wire Coils - Sorted by inductance (mH)

Sizing: OD (outer diameter) x H (height) & ID (Inner hole diameter)



Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-0812	Air Core Coil 0,005mH +/-1% 0,06Ω wire 0,80mm=20AWG OD-9 / 8mm	0,005	0,060	9	0,80	20	0,004
000-1619	Air Core Coil 0,005mH +/-1% 0,013Ω wire 1,60mm=14AWG OD-18 / 25mm	0,005	0,013	8	1,60	14	0,033
000-1581	Air Core Coil 0,007mH +/-1% 0,03Ω wire 1,20mm=17AWG OD-27 / 10mm	0,007	0,030	20	1,20	17	0,015
000-1589	Air Core Coil 0,007mH +/-1% 0,15Ω wire 0,40mm=26AWG OD-11 / 8mm	0,007	0,150	9	0,40	26	0,002
000-0051	Air Core Coil 0,008mH +/-1% 0,016Ω wire 1,60mm=14AWG OD-18 / 25mm	0,008	0,016	8	1,60	14	0,033
000-0045	Air Core Coil 0,010mH +/-1% 0,020Ω wire 1,60mm=14AWG OD-21 / 25mm	0,010	0,020	8	1,60	14	0,037
000-0849	Air Core Coil 0,010mH +/-1% 0,06Ω wire 1,80mm=13AWG OD-23 / 20mm	0,010	0,060	8	1,80	13	0,047
000-1557	Air Core Coil 0,010mH +/-1% 0,070Ω wire 0,80mm=20AWG OD-14 / 25mm	0,010	0,070	8	0,80	20	0,010
000-1633	Air Core Coil 0,010mH +/-1% 0,025Ω wire 1,40mm=15AWG OD-17 / 25mm	0,010	0,025	8	1,40	15	0,032
000-1251	Air Core Coil 0,012mH +/-1% 0,025Ω wire 1,40mm=15AWG OD-17 / 25mm	0,012	0,025	8	1,40	15	0,032
000-1790	Air Core Coil 0,015mH +/-1% 0,080Ω wire 0,80mm=20AWG OD-14 / 25mm	0,015	0,080	8	0,80	20	0,012
000-0176	Air Core Coil 0,020mH +/-1% 0,028Ω wire 1,60mm=14AWG OD-24 / 25mm	0,020	0,028	8	1,60	14	0,057
000-0193	Air Core Coil 0,020mH +/-1% 0,04Ω wire 1,20mm=17AWG OD-34 / 15mm	0,020	0,040	25	1,20	17	0,029
000-0813	Air Core Coil 0,020mH +/-1% 0,10Ω wire 0,80mm=20AWG OD-19 / 8mm	0,020	0,100	9	0,80	20	0,009
000-1233	Air Core Coil 0,020mH +/-1% 0,105Ω wire 0,63mm=22AWG OD-15 / 8mm	0,020	0,105	9	0,63	22	0,006
000-1522	Air Core Coil 0,020mH +/-1% 0,090Ω wire 0,80mm=20AWG OD-14 / 25mm	0,020	0,090	8	0,80	20	0,013
000-0190	Air Core Coil 0,025mH +/-1% 0,040Ω wire 1,40mm=15AWG OD-38 / 15mm	0,025	0,035	25	1,40	15	0,050
000-0192	Air Core Coil 0,025mH +/-1% 0,04Ω wire 1,20mm=17AWG OD-34 / 15mm	0,025	0,040	25	1,20	17	0,032
000-1532	Air Core Coil 0,025mH +/-1% 0,132Ω wire 0,70mm=21AWG OD-13 / 25mm	0,025	0,132	8	0,70	21	0,011
000-1804	Air Core Coil 0,025mH +/-1% 0,060Ω wire 1,00mm=18AWG OD-31 / 15mm	0,025	0,060	25	1,00	18	0,021
000-0834	Air Core Coil 0,028mH +/-1% 0,29Ω wire 0,40mm=26AWG OD-12 / 8mm	0,028	0,290	9	0,40	26	0,003
000-0060	Air Core Coil 0,030mH +/-1% 0,040Ω wire 1,60mm=14AWG OD-30 / 25mm	0,030	0,040	8	1,60	14	0,087
000-0814	Air Core Coil 0,030mH +/-1% 0,12Ω wire 0,80mm=20AWG OD-20 / 8mm	0,030	0,120	9	0,80	20	0,012
000-0949	Air Core Coil 0,030mH +/-1% 0,049Ω wire 1,20mm=17AWG OD-34 / 15mm	0,030	0,049	25	1,20	17	0,034
000-1523	Air Core Coil 0,030mH +/-1% 0,120Ω wire 0,80mm=20AWG OD-15 / 25mm	0,030	0,120	8	0,80	20	0,016
000-1805	Air Core Coil 0,030mH +/-1% 0,290Ω wire 0,40mm=26AWG OD-12 / 8mm	0,030	0,290	9	0,40	26	0,003
000-0171	Air Core Coil 0,033mH +/-1% 0,07Ω wire 1,00mm=18AWG OD-29 / 8mm	0,033	0,070	15	1,00	18	0,023
000-1599	Air Core Coil 0,033mH +/-1% 0,22Ω wire 0,50mm=24AWG OD-15 / 8mm	0,033	0,240	9	0,50	24	0,005
000-1544	Air Core Coil 0,035mH +/-1% 0,150Ω wire 0,63mm=22AWG OD-17 / 8mm	0,035	0,150	9	0,63	22	0,008
000-0920	Air Core Coil 0,037mH +/-1% 0,058Ω wire 1,20mm=17AWG OD-34 / 15mm	0,037	0,058	25	1,20	17	0,036
000-1794	Air Core Coil 0,037mH +/-1% 0,14Ω wire 0,70mm=21AWG OD-20 / 15mm	0,037	0,140	15	0,70	21	0,013
000-1110	Air Core Coil 0,040mH +/-1% 0,13Ω wire 0,80mm=20AWG OD-21 / 8mm	0,040	0,130	9	0,80	20	0,014
000-1806	Air Core Coil 0,040mH +/-1% 0,240Ω wire 0,50mm=24AWG OD-15 / 8mm	0,040	0,240	9	0,50	24	0,005
000-1902	Air Core Coil 0,040mH +/-1% 0,040Ω wire 1,40mm=15AWG OD-38 / 15mm	0,040	0,040	25	1,40	15	0,055
000-0939	Air Core Coil 0,045mH +/-1% 0,090Ω wire 1,00mm=18AWG OD-25 / 15mm	0,045	0,090	15	1,00	18	0,028
000-1318	Air Core Coil 0,047mH +/-1% 0,170Ω wire 0,70mm=21AWG OD-20 / 15mm	0,047	0,170	15	0,70	21	0,013
000-0001	Air Core Coil 0,050mH +/-1% 0,046Ω wire 1,60mm=14AWG OD-30 / 25mm	0,050	0,046	8	1,60	14	0,096
000-0101	Air Core Coil 0,050mH +/-1% 0,038Ω wire 1,80mm=13AWG OD-32 / 25mm	0,050	0,038	8	1,80	13	0,121
000-0191	Air Core Coil 0,050mH +/-1% 0,05Ω wire 1,40mm=15AWG OD-40 / 15mm	0,050	0,050	25	1,40	15	0,060
000-0831	Air Core Coil 0,043mH +/-1% 0,060Ω wire 1,20mm=17AWG OD-34 / 15mm	0,050	0,060	25	1,20	17	0,046
000-0918	Air Core Coil 0,050mH +/-1% 0,124Ω wire 0,80mm=20AWG OD-23 / 8mm	0,050	0,124	9	0,80	20	0,016
000-1024	Air Core Coil 0,050mH +/-1% 0,060Ω wire 1,20mm=17AWG OD-34 / 15mm	0,050	0,060	25	1,20	17	0,046
000-1106	Air Core Coil 0,050mH +/-1% 0,260Ω wire 0,50mm=24AWG OD-15 / 8mm	0,050	0,260	9	0,50	24	0,006
000-1428	Air Core Coil 0,050mH +/-1% 0,178Ω wire 0,63mm=22AWG OD-18 / 8mm	0,050	0,178	9	0,63	22	0,010
000-1603	Air Core Coil 0,050mH +/-1% 0,170Ω wire 0,70mm=21AWG OD-21 / 15mm	0,050	0,170	15	0,70	21	0,014
000-1947	Air Core Coil 0,050mH +/-1% 0,090Ω wire 1,00mm=18AWG OD-33 / 15mm	0,050	0,090	25	1,00	18	0,031
000-1963	Air Core Coil 0,050mH +/-1% 0,090Ω wire 1,00mm=18AWG OD-25 / 15mm	0,050	0,090	15	1,00	18	0,029
000-0150	Air Core Coil 0,055mH +/-1% 0,170Ω wire 0,70mm=21AWG OD-25 / 8mm	0,055	0,170	15	0,70	21	0,013
000-0870	Air Core Coil 0,055mH +/-1% 0,090Ω wire 1,00mm=18AWG OD-25 / 15mm	0,055	0,090	15	1,00	18	0,029
000-0980	Air Core Coil 0,057mH +/-1% 0,77Ω wire 0,30mm=29AWG OD-17 / 8mm	0,057	0,770	15	0,30	29	0,003
000-1053	Air Core Coil 0,060mH +/-1% 0,135Ω wire 0,80mm=20AWG OD-23 / 8mm	0,060	0,135	9	0,80	20	0,018
000-1903	Air Core Coil 0,060mH +/-1% 0,170Ω wire 0,70mm=21AWG OD-25 / 8mm	0,060	0,170	15	0,70	21	0,014
000-0828	Air Core Coil 0,068mH +/-1% 0,10Ω wire 1,00mm=18AWG OD-33 / 8mm	0,068	0,100	15	1,00	18	0,032
000-1693	Air Core Coil 0,070mH +/-1% 0,120Ω wire 1,00mm=18AWG OD-35 / 15mm	0,070	0,120	25	1,00	18	0,038
000-1694	Air Core Coil 0,070mH +/-1% 0,108Ω wire 1,00mm=18AWG OD-33 / 8mm	0,070	0,108	15	1,00	18	0,032
000-1807	Air Core Coil 0,070mH +/-1% 0,330Ω wire 0,50mm=24AWG OD-16 / 8mm	0,070	0,330	9	0,50	24	0,007
000-0997	Air Core Coil 0,074mH +/-1% 0,290Ω wire 0,63mm=22AWG OD-24 / 8mm	0,074	0,290	15	0,63	22	0,012
000-1069	Air Core Coil 0,075mH +/-1% 0,185Ω wire 0,70mm=21AWG OD-25 / 8mm	0,075	0,185	15	0,70	21	0,016
000-1426	Air Core Coil 0,075mH +/-1% 0,157Ω wire 0,80mm=20AWG OD-25 / 8mm	0,075	0,157	9	0,80	20	0,021
000-0839	Air Core Coil 0,080mH +/-1% 0,98Ω wire 0,30mm=29AWG OD-18 / 8mm	0,080	0,980	15	0,30	29	0,003
000-1028	Air Core Coil 0,080mH +/-1% 0,120Ω wire 1,00mm=18AWG OD-35 / 15mm	0,080	0,120	25	1,00	18	0,038
000-1154	Air Core Coil 0,080mH +/-1% 0,157Ω wire 0,80mm=20AWG OD-25 / 8mm	0,080	0,157	9	0,80	20	0,022
000-1517	Air Core Coil 0,080mH +/-1% 0,200Ω wire 0,70mm=21AWG OD-25 / 8mm	0,080	0,200	15	0,70	21	0,016
000-1534	Air Core Coil 0,080mH +/-1% 0,060Ω wire 1,40mm=15AWG OD-39 / 20mm	0,080	0,060	25	1,40	15	0,084
000-1808	Air Core Coil 0,082mH +/-1% 0,370Ω wire 0,50mm=24AWG OD-17 / 8mm	0,082	0,370	9	0,50	24	0,008
000-1032	Air Core Coil 0,085mH +/-1% 0,120Ω wire 1,00mm=18AWG OD-35 / 15mm	0,085	0,122	25	1,00	18	0,038
000-0881	Air Core Coil 0,090mH +/-1% 0,229Ω wire 0,70mm=21AWG OD-22 / 15mm	0,090	0,229	15	0,70	21	0,018
000-0922	Air Core Coil 0,090mH +/-1% 0,378Ω wire 0,50mm=24AWG OD-17 / 8mm	0,090	0,378	9	0,50	24	0,008
000-1141	Air Core Coil 0,090mH +/-1% 0,210Ω wire 0,70mm=21AWG OD-26 / 8mm	0,090	0,210	15	0,70	21	0,017
000-1646	Air Core Coil 0,090mH +/-1% 0,130Ω wire 1,00mm=18AWG OD-29 / 15mm	0,090	0,130	15	1,00	18	0,043
000-0002	Air Core Coil 0,100mH +/-3% 0,067Ω wire 1,60mm=14AWG OD-35 / 25mm	0,100	0,067	8	1,60	14	0,140
000-0102	Air Core Coil 0,100mH +/-3% 0,055Ω wire 1,80mm=13AWG OD-39 / 25mm	0,100	0,055	8	1,80	13	0,177
000-0206	Air Core Coil 0,100mH +/-3% 0,18Ω wire 1,00mm=18AWG OD-21 / 40mm	0,100	0,180	10	1,00	18	0,056
000-0951	Air Core Coil 0,100mH +/-3% 0,10Ω wire 1,20mm=17AWG OD-33 / 15mm	0,100	0,096	15	1,20	17	0,063
000-1002	Air Core Coil 0,100mH +/-3% 0,190Ω wire 0,80mm=20AWG OD-31 / 10mm	0,100	0,190	20	0,80	20	0,026
000-1148	Air Core Coil 0,100mH +/-3% 0,260Ω wire 0,70mm=21AWG OD-24 / 8mm	0,100	0,260	9	0,70	21	0,019
000-1149	Air Core Coil 0,100mH +/-3% 0,190Ω wire 0,80mm=20AWG OD-27 / 8mm	0,100	0,190	9	0,80	20	0,025
000-1234	Air Core Coil 0,100mH +/-3% 0,120Ω wire 1,00mm=18AWG OD-35 / 10mm	0,100	0,120	20	1,00	18	0,042
000-1237	Air Core Coil 0,100mH +/-3% 0,260Ω wire 0,70mm=21AWG OD-30 / 15mm	0,100	0,260	25	0,70	21	0,021
000-1361	Air Core Coil 0,100mH +/-3% 0,330Ω wire 0,70mm=21AWG OD-29 / 30mm	0,100	0,330	25	0,70	21	0,025
000-1449	Air Core Coil 0,100mH +/-3% 0,190Ω wire 0,80mm=20AWG OD-24 / 15mm	0,100	0,190	15	0,80	20	0,026
000-1463	Air Core Coil 0,100mH +/-3% 0,290Ω wire 0,63mm=22AWG OD-25 / 8mm	0,100	0,290	15	0,63	22	0,014
000-1533	Air Core Coil 0,100mH +/-3% 0,117Ω wire 1,20mm=17AWG OD-34 / 30mm	0,100	0,117	25	1,20	17	0,070
000-1535	Air Core Coil 0,100mH +/-3% 0,075Ω wire 1,40mm=15AWG OD-43 / 15mm	0,100	0,075	25	1,40	15	0,089
000-1536	Air Core Coil 0,100mH +/-3% 0,160Ω wire 1,00mm=18AWG OD-31 / 30mm	0,100	0,160	25	1,00	18	0,050
000-1580	Air Core Coil 0,100mH +/-3% 0,08Ω wire 1,40mm=15AWG OD-36 / 30mm	0,100	0,082	25	1,40	15	0,102
000-1751	Air Core Coil 0,100mH +/-3% 0,580Ω wire 0,50mm=24AWG OD-19 / 27mm	0,100	0,580	15	0,50	24	0,012
000-1752	Air Core Coil 0,100mH +/-3% 0,290Ω wire 0,70mm=21AWG OD-20 / 27mm	0,100	0,290	15	0,70	21	0,024

Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-1801	Air Core Coil 0,100mH +/-3% 0,230Ω wire 0,70mm=21AWG OD-26 / 8mm	0,100	0,230	15	0,70	21	0,018
000-1809	Air Core Coil 0,100mH +/-3% 0,440Ω wire 0,50mm=24AWG OD-21 / 8mm	0,100	0,440	15	0,50	24	0,009
000-1810	Air Core Coil 0,100mH +/-3% 0,090Ω wire 1,20mm=17AWG OD-38 / 15mm	0,100	0,090	25	1,20	17	0,065
000-1900	Air Core Coil 0,100mH +/-3% 0,250Ω wire 0,70mm=21AWG OD-22 / 15mm	0,100	0,250	15	0,70	21	0,019
000-1948	Air Core Coil 0,100mH +/-3% 0,130Ω wire 1,00mm=18AWG OD-35 / 15mm	0,100	0,130	25	1,00	18	0,044
000-1964	Air Core Coil 0,100mH +/-3% 0,130Ω wire 1,00mm=18AWG OD-29 / 15mm	0,100	0,130	15	1,00	18	0,042
000-1617	Air Core Coil 0,107mH +/-1% 0,630Ω wire 0,40mm=26AWG OD-15 / 8mm	0,107	0,630	9	0,40	26	0,006
000-1620	Air Core Coil 0,107mH +/-1% 0,100Ω wire 1,20mm=17AWG OD-38 / 15mm	0,107	0,100	25	1,20	17	0,067
000-0177	Air Core Coil 0,110mH +/-3% 0,44Ω wire 0,50mm=24AWG OD-22 / 8mm	0,110	0,440	15	0,50	24	0,010
000-0894	Air Core Coil 0,110mH +/-3% 0,430Ω wire 0,50mm=24AWG OD-18 / 8mm	0,110	0,430	9	0,50	24	0,009
000-0895	Air Core Coil 0,110mH +/-1% 1,14Ω wire 0,30mm=29AWG OD-18 / 8mm	0,110	1,140	15	0,30	29	0,003
000-0917	Air Core Coil 0,110mH +/-3% 0,133Ω wire 1,00mm=18AWG OD-36 / 15mm	0,110	0,133	25	1,00	18	0,045
000-1621	Air Core Coil 0,110mH +/-3% 0,100Ω wire 1,20mm=17AWG OD-38 / 15mm	0,110	0,100	25	1,20	17	0,067
000-1634	Air Core Coil 0,110mH +/-3% 0,200Ω wire 0,80mm=20AWG OD-31 / 10mm	0,110	0,200	20	0,80	20	0,027
000-1692	Air Core Coil 0,110mH +/-3% 0,250Ω wire 0,70mm=21AWG OD-24 / 15mm	0,110	0,250	15	0,70	21	0,021
000-0003	Air Core Coil 0,120mH +/-3% 0,074Ω wire 1,60mm=14AWG OD-35 / 25mm	0,120	0,074	8	1,60	14	0,150
000-0066	Air Core Coil 0,120mH +/-3% 0,06Ω wire 1,80mm=13AWG OD-46 / 30mm	0,120	0,060	25	1,80	13	0,188
000-0103	Air Core Coil 0,120mH +/-3% 0,060Ω wire 1,80mm=13AWG OD-39 / 25mm	0,120	0,060	8	1,80	13	0,195
000-0928	Air Core Coil 0,120mH +/-3% 0,110Ω wire 1,20mm=17AWG OD-38 / 15mm	0,120	0,110	25	1,20	17	0,072
000-1003	Air Core Coil 0,120mH +/-3% 0,320Ω wire 0,63mm=22AWG OD-26 / 8mm	0,120	0,320	15	0,63	22	0,016
000-1080	Air Core Coil 0,120mH +/-3% 0,700Ω wire 0,40mm=26AWG OD-20 / 8mm	0,120	0,700	15	0,40	26	0,006
000-1090	Air Core Coil 0,120mH +/-3% 0,250Ω wire 0,70mm=21AWG OD-24 / 15mm	0,120	0,250	15	0,70	21	0,022
000-1261	Air Core Coil 0,120mH +/-3% 0,26Ω wire 0,70mm=21AWG OD-27 / 8mm	0,120	0,260	15	0,70	21	0,020
000-1325	Air Core Coil 0,120mH +/-3% 0,440Ω wire 0,50mm=24AWG OD-18 / 8mm	0,120	0,440	9	0,50	24	0,009
000-1543	Air Core Coil 0,120mH +/-3% 0,086Ω wire 1,40mm=15AWG OD-43 / 15mm	0,120	0,086	25	1,40	15	0,095
000-1675	Air Core Coil 0,120mH +/-3% 0,147Ω wire 1,00mm=18AWG OD-35 / 15mm	0,120	0,147	25	1,00	18	0,047
000-1680	Air Core Coil 0,120mH +/-3% 0,150Ω wire 1,00mm=18AWG OD-29 / 15mm	0,120	0,150	15	1,00	18	0,046
000-1682	Air Core Coil 0,120mH +/-3% 0,140Ω wire 1,00mm=18AWG OD-37 / 10mm	0,120	0,140	20	1,00	18	0,044
000-1811	Air Core Coil 0,120mH +/-3% 0,470Ω wire 0,50mm=24AWG OD-22 / 8mm	0,120	0,470	15	0,50	24	0,010
000-1812	Air Core Coil 0,120mH +/-3% 0,210Ω wire 0,80mm=20AWG OD-31 / 10mm	0,120	0,210	20	0,80	20	0,028
000-0999	Air Core Coil 0,125mH +/-1% 1,15Ω wire 0,30mm=29AWG OD-18 / 8mm	0,125	1,150	15	0,30	29	0,003
000-0152	Air Core Coil 0,126mH +/-1% 0,15Ω wire 1,00mm=18AWG OD-29 / 15mm	0,126	0,150	15	1,00	18	0,047
000-0208	Air Core Coil 0,130mH +/-3% 0,30Ω wire 0,80mm=20AWG OD-18 / 40mm	0,130	0,300	10	0,80	20	0,040
000-0901	Air Core Coil 0,130mH +/-3% 0,221Ω wire 0,80mm=20AWG OD-32 / 10mm	0,130	0,221	20	0,80	20	0,030
000-0973	Air Core Coil 0,130mH +/-3% 0,31Ω wire 0,63mm=22AWG OD-25 / 8mm	0,130	0,310	15	0,63	22	0,017
000-1531	Air Core Coil 0,130mH +/-3% 0,290Ω wire 0,70mm=21AWG OD-25 / 15mm	0,130	0,290	15	0,70	21	0,022
000-1738	Air Core Coil 0,130mH +/-3% 0,476Ω wire 0,50mm=24AWG OD-22 / 8mm	0,130	0,476	15	0,50	24	0,010
000-1949	Air Core Coil 0,130mH +/-3% 0,160Ω wire 1,00mm=18AWG OD-37 / 15mm	0,130	0,160	25	1,00	18	0,050
000-1965	Air Core Coil 0,130mH +/-3% 0,160Ω wire 1,00mm=18AWG OD-30 / 15mm	0,130	0,160	15	1,00	18	0,048
000-0168	Air Core Coil 0,135mH +/-1% 0,291Ω wire 0,70mm=21AWG OD-25 / 15mm	0,135	0,291	15	0,70	21	0,023
000-0219	Air Core Coil 0,135mH +/-3% 0,085Ω wire 1,40mm=15AWG OD-45 / 15mm	0,135	0,085	25	1,40	15	0,109
000-0702	Air Core Coil 0,135mH +/-3% 0,16Ω wire 1,00mm=18AWG OD-30 / 15mm	0,135	0,160	15	1,00	18	0,050
000-0207	Air Core Coil 0,140mH +/-3% 0,22Ω wire 1,00mm=18AWG OD-22 / 40mm	0,140	0,220	10	1,00	18	0,068
000-0921	Air Core Coil 0,140mH +/-3% 0,163Ω wire 1,00mm=18AWG OD-30 / 15mm	0,140	0,163	15	1,00	18	0,050
000-1112	Air Core Coil 0,140mH +/-3% 0,225Ω wire 0,80mm=20AWG OD-32 / 10mm	0,140	0,225	20	0,80	20	0,030
000-1813	Air Core Coil 0,140mH +/-3% 0,500Ω wire 0,50mm=24AWG OD-22 / 8mm	0,140	0,500	15	0,50	24	0,011
000-0004	Air Core Coil 0,150mH +/-3% 0,084Ω wire 1,60mm=14AWG OD-38 / 25mm	0,150	0,084	8	1,60	14	0,166
000-0104	Air Core Coil 0,150mH +/-3% 0,070Ω wire 1,80mm=13AWG OD-42 / 25mm	0,150	0,070	8	1,80	13	0,221
000-1007	Air Core Coil 0,150mH +/-3% 0,310Ω wire 0,70mm=21AWG OD-25 / 15mm	0,150	0,310	15	0,70	21	0,024
000-1045	Air Core Coil 0,150mH +/-3% 0,240Ω wire 0,80mm=20AWG OD-26 / 15mm	0,150	0,240	15	0,80	20	0,033
000-1051	Air Core Coil 0,150mH +/-3% 0,160Ω wire 1,00mm=18AWG OD-37 / 15mm	0,150	0,160	25	1,00	18	0,054
000-1061	Air Core Coil 0,150mH +/-3% 0,300Ω wire 0,70mm=21AWG OD-30 / 10mm	0,150	0,300	20	0,70	21	0,024
000-1092	Air Core Coil 0,150mH +/-3% 0,120Ω wire 1,20mm=17AWG OD-41 / 15mm	0,150	0,120	25	1,20	17	0,079
000-1129	Air Core Coil 0,150mH +/-3% 0,330Ω wire 0,63mm=22AWG OD-26 / 8mm	0,150	0,330	15	0,63	22	0,018
000-1130	Air Core Coil 0,150mH +/-3% 0,160Ω wire 1,00mm=18AWG OD-31 / 15mm	0,150	0,160	15	1,00	18	0,055
000-1146	Air Core Coil 0,150mH +/-3% 0,290Ω wire 0,70mm=21AWG OD-25 / 8mm	0,150	0,290	9	0,70	21	0,023
000-1206	Air Core Coil 0,150mH +/-3% 0,193Ω wire 1,00mm=18AWG OD-33 / 30mm	0,150	0,193	25	1,00	18	0,062
000-1236	Air Core Coil 0,150mH +/-3% 0,160Ω wire 1,00mm=18AWG OD-39 / 10mm	0,150	0,160	20	1,00	18	0,053
000-1262	Air Core Coil 0,150mH +/-3% 0,283Ω wire 0,70mm=21AWG OD-29 / 8mm	0,150	0,283	15	0,70	21	0,023
000-1324	Air Core Coil 0,150mH +/-3% 0,490Ω wire 0,50mm=24AWG OD-19 / 8mm	0,150	0,490	9	0,50	24	0,010
000-1358	Air Core Coil 0,150mH +/-3% 0,400Ω wire 0,70mm=21AWG OD-29 / 30mm	0,150	0,400	25	0,70	21	0,029
000-1472	Air Core Coil 0,150mH +/-3% 0,850Ω wire 0,40mm=26AWG OD-20 / 8mm	0,150	0,850	15	0,40	26	0,006
000-1485	Air Core Coil 0,150mH +/-3% 0,099Ω wire 1,40mm=15AWG OD-45 / 15mm	0,150	0,099	25	1,40	15	0,110
000-1496	Air Core Coil 0,150mH +/-3% 0,146Ω wire 1,20mm=17AWG OD-34 / 30mm	0,150	0,146	25	1,20	17	0,093
000-1688	Air Core Coil 0,150mH +/-3% 0,105Ω wire 1,40mm=15AWG OD-38 / 30mm	0,150	0,105	25	1,40	15	0,126
000-1814	Air Core Coil 0,150mH +/-3% 1,16Ω wire 0,30mm=29AWG OD-18 / 8mm	0,150	1,160	15	0,30	29	0,003
000-1815	Air Core Coil 0,150mH +/-3% 0,230Ω wire 0,80mm=20AWG OD-32 / 10mm	0,150	0,230	20	0,80	20	0,032
000-1816	Air Core Coil 0,150mH +/-3% 0,510Ω wire 0,50mm=24AWG OD-23 / 8mm	0,150	0,510	15	0,50	24	0,011
000-0064	Air Core Coil 0,160mH +/-3% 0,07Ω wire 1,80mm=13AWG OD-46 / 30mm	0,160	0,070	25	1,80	13	0,208
000-0225	Air Core Coil 0,160mH +/-3% 1,30Ω wire 0,30mm=29AWG OD-19 / 8mm	0,160	1,300	15	0,30	29	0,004
000-0232	Air Core Coil 0,160mH +/-3% 0,15Ω wire 1,20mm=17AWG OD-37 / 30mm	0,160	0,150	25	1,20	17	0,098
000-0952	Air Core Coil 0,160mH +/-3% 0,12Ω wire 1,20mm=17AWG OD-37 / 15mm	0,160	0,123	15	1,20	17	0,082
000-1008	Air Core Coil 0,160mH +/-3% 0,850Ω wire 0,40mm=26AWG OD-20 / 8mm	0,160	0,850	15	0,40	26	0,007
000-1397	Air Core Coil 0,160mH +/-3% 0,410Ω wire 0,70mm=21AWG OD-29 / 30mm	0,160	0,410	25	0,70	21	0,031
000-1627	Air Core Coil 0,160mH +/-3% 0,180Ω wire 1,00mm=18AWG OD-33 / 15mm	0,160	0,180	15	1,00	18	0,056
000-1684	Air Core Coil 0,160mH +/-3% 0,290Ω wire 0,70mm=21AWG OD-29 / 8mm	0,160	0,290	15	0,70	21	0,023
000-1817	Air Core Coil 0,160mH +/-3% 0,240Ω wire 0,80mm=20AWG OD-33 / 10mm	0,160	0,240	20	0,80	20	0,032
000-0978	Air Core Coil 0,169mH +/-1% 1,17Ω wire 0,30mm=29AWG OD-18 / 8mm	0,169	1,170	15	0,30	29	0,005
000-0822	Air Core Coil 0,170mH +/-3% 0,18Ω wire 1,00mm=18AWG OD-28 / 17mm	0,170	0,180	10	1,00	18	0,059
000-0965	Air Core Coil 0,170mH +/-3% 0,14Ω wire 1,20mm=17AWG OD-38 / 15mm	0,170	0,140	15	1,20	17	0,090
000-1049	Air Core Coil 0,170mH +/-3% 0,111Ω wire 1,40mm=15AWG OD-38 / 30mm	0,170	0,111	25	1,40	15	0,131
000-1270	Air Core Coil 0,170mH +/-3% 0,180Ω wire 1,00mm=18AWG OD-33 / 15mm	0,170	0,180	15	1,00	18	0,057
000-0164	Air Core Coil 0,174mH +/-3% 0,099Ω wire 1,40mm=15AWG OD-45 / 15mm	0,174	0,099	25	1,40	15	0,124
000-0005	Air Core Coil 0,180mH +/-3% 0,094Ω wire 1,60mm=14AWG OD-42 / 25mm	0,180	0,094	8	1,60	14	0,192
000-0105	Air Core Coil 0,180mH +/-3% 0,075Ω wire 1,80mm=13AWG OD-49 / 30mm	0,180	0,075	25	1,80	13	0,239
000-1010	Air Core Coil 0,180mH +/-3% 0,180Ω wire 1,00mm=18AWG OD-39 / 15mm	0,180	0,180	25	1,00	18	0,059
000-1066	Air Core Coil 0,180mH +/-3% 0,270Ω wire 0,80mm=20AWG OD-27 / 15mm	0,180	0,270	15	0,80	20	0,037
000-1072	Air Core Coil 0,180mH +/-3% 0,330Ω wire 0,70mm=21AWG OD-25 / 15mm	0,180	0,330	15	0,70	21	0,027
000-1091	Air Core Coil 0,180mH +/-3% 0,420Ω wire 0,63mm=22AWG OD-24 / 15mm	0,180	0,420	15	0,63	22	0,020
000-1207	Air Core Coil 0,180mH +/-3% 0,210Ω wire 1,00mm=18AWG OD-33 / 30mm	0,180	0,210	25	1,00	18	0,067
000-1273	Air Core Coil 0,180mH +/-3% 0,105Ω wire 1,40mm=15AWG OD-56 / 10mm	0,180	0,105	25	1,40	15	0,123
000-1277	Air Core Coil 0,180mH +/-3% 0,180Ω wire 1,00mm=18AWG OD-39 / 10mm	0,180	0,180	20	1,00	18	0,056
000-1289	Air Core Coil 0,180mH +/-3% 0,180Ω wire 1,00mm=18AWG OD-33 / 15mm	0,180	0,180	15	1,00	18	0,060
000-1291	Air Core Coil 0,180mH +/-3% 0,321Ω wire 0,70mm=21AWG OD-30 / 8mm	0,180	0,321	15	0,70	21	0,024
000-1421	Air Core Coil 0,180mH +/-3% 0,430Ω wire 0,70mm=21AWG OD-29 / 30mm	0,180	0,430	25	0,70	21	0,032

Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-1475	Air Core Coil 0,180mH +/-3% 1,20Ω wire 0,30mm=29AWG OD-18 / 8mm	0,180	1,200	15	0,30	29	0,005
000-1488	Air Core Coil 0,180mH +/-3% 0,382Ω wire 0,63mm=22AWG OD-27 / 8mm	0,180	0,382	15	0,63	22	0,020
000-1741	Air Core Coil 0,180mH +/-3% 0,850Ω wire 0,50mm=24AWG OD-28 / 30mm	0,180	0,850	25	0,50	24	0,017
000-1750	Air Core Coil 0,180mH +/-3% 0,810Ω wire 0,50mm=24AWG OD-19 / 27mm	0,180	0,810	15	0,50	24	0,016
000-1818	Air Core Coil 0,180mH +/-3% 0,250Ω wire 0,80mm=20AWG OD-34 / 10mm	0,180	0,250	20	0,80	20	0,035
000-1819	Air Core Coil 0,180mH +/-3% 0,900Ω wire 0,40mm=26AWG OD-20 / 8mm	0,180	0,900	15	0,40	26	0,008
000-1820	Air Core Coil 0,180mH +/-3% 0,550Ω wire 0,50mm=24AWG OD-23 / 8mm	0,180	0,550	15	0,50	24	0,012
000-1937	Air Core Coil 0,180mH +/-3% 0,140Ω wire 1,20mm=17AWG OD-38 / 15mm	0,180	0,140	15	1,20	17	0,091
000-0163	Air Core Coil 0,185mH +/-3% 0,11Ω wire 1,40mm=15AWG OD-50 / 15mm	0,185	0,115	25	1,40	15	0,128
000-0096	Air Core Coil 0,190mH +/-3% 0,08Ω wire 1,80mm=13AWG OD-46 / 25mm	0,190	0,080	8	1,80	13	0,252
000-0941	Air Core Coil 0,190mH +/-3% 0,290Ω wire 0,80mm=20AWG OD-29 / 13mm	0,190	0,290	15	0,80	20	0,037
000-1042	Air Core Coil 0,190mH +/-3% 0,182Ω wire 1,00mm=18AWG OD-41 / 10mm	0,190	0,182	20	1,00	18	0,058
000-1530	Air Core Coil 0,190mH +/-3% 0,920Ω wire 0,40mm=26AWG OD-20 / 8mm	0,190	0,920	15	0,40	26	0,008
000-1576	Air Core Coil 0,190mH +/-3% 0,14Ω wire 1,20mm=17AWG OD-48 / 10mm	0,190	0,140	20	1,20	17	0,093
000-1597	Air Core Coil 0,190mH +/-3% 0,290Ω wire 0,80mm=20AWG OD-28 / 15mm	0,190	0,290	15	0,80	20	0,037
000-1667	Air Core Coil 0,190mH +/-3% 0,345Ω wire 0,70mm=21AWG OD-25 / 15mm	0,190	0,345	15	0,70	21	0,027
000-1763	Air Core Coil 0,190mH +/-3% 0,209Ω wire 1,00mm=18AWG OD-26 / 25mm	0,190	0,209	8	1,00	18	0,067
000-1906	Air Core Coil 0,190mH +/-3% 0,590Ω wire 0,50mm=24AWG OD-23 / 8mm	0,190	0,590	15	0,50	24	0,012
000-0919	Air Core Coil 0,193mH +/-1% 0,145Ω wire 1,20mm=17AWG OD-43 / 15mm	0,193	0,145	25	1,20	17	0,091
000-0057	Air Core Coil 0,200mH +/-3% 0,10Ω wire 1,60mm=14AWG OD-42 / 25mm	0,200	0,100	8	1,60	14	0,205
000-0139	Air Core Coil 0,200mH +/-3% 0,080Ω wire 1,80mm=13AWG OD-46 / 25mm	0,200	0,080	8	1,80	13	0,265
000-0854	Air Core Coil 0,200mH +/-3% 0,45Ω wire 0,63mm=22AWG OD-24 / 15mm	0,200	0,450	15	0,63	22	0,022
000-1011	Air Core Coil 0,200mH +/-3% 0,700Ω wire 0,50mm=24AWG OD-20 / 15mm	0,200	0,700	15	0,50	24	0,014
000-1073	Air Core Coil 0,200mH +/-3% 0,600Ω wire 0,50mm=24AWG OD-24 / 8mm	0,200	0,600	15	0,50	24	0,013
000-1100	Air Core Coil 0,200mH +/-3% 0,350Ω wire 0,70mm=21AWG OD-30 / 10mm	0,200	0,350	20	0,70	21	0,026
000-1101	Air Core Coil 0,200mH +/-3% 0,350Ω wire 0,70mm=21AWG OD-25 / 15mm	0,200	0,350	15	0,70	21	0,028
000-1109	Air Core Coil 0,200mH +/-3% 0,290Ω wire 0,80mm=20AWG OD-29 / 13mm	0,200	0,290	15	0,80	20	0,037
000-1147	Air Core Coil 0,200mH +/-3% 0,350Ω wire 0,70mm=21AWG OD-28 / 8mm	0,200	0,350	9	0,70	21	0,027
000-1276	Air Core Coil 0,200mH +/-3% 0,193Ω wire 1,00mm=18AWG OD-41 / 10mm	0,200	0,193	20	1,00	18	0,062
000-1357	Air Core Coil 0,200mH +/-3% 0,210Ω wire 1,00mm=18AWG OD-35 / 25mm	0,200	0,210	25	1,00	18	0,068
000-1359	Air Core Coil 0,200mH +/-3% 0,450Ω wire 0,70mm=21AWG OD-30 / 30mm	0,200	0,450	25	0,70	21	0,034
000-1462	Air Core Coil 0,200mH +/-3% 0,420Ω wire 0,63mm=22AWG OD-28 / 8mm	0,200	0,420	15	0,63	22	0,021
000-1507	Air Core Coil 0,200mH +/-3% 0,130Ω wire 1,40mm=15AWG OD-41 / 30mm	0,200	0,130	25	1,40	15	0,148
000-1600	Air Core Coil 0,200mH +/-3% 0,150Ω wire 1,20mm=17AWG OD-43 / 15mm	0,200	0,150	25	1,20	17	0,093
000-1606	Air Core Coil 0,200mH +/-3% 0,115Ω wire 1,40mm=15AWG OD-48 / 15mm	0,200	0,115	25	1,40	15	0,135
000-1612	Air Core Coil 0,200mH +/-3% 0,110Ω wire 1,40mm=15AWG OD-56 / 10mm	0,200	0,110	25	1,40	15	0,132
000-1622	Air Core Coil 0,200mH +/-3% 0,295Ω wire 0,80mm=20AWG OD-28 / 15mm	0,200	0,295	15	0,80	20	0,037
000-1822	Air Core Coil 0,200mH +/-3% 0,200Ω wire 1,00mm=18AWG OD-39 / 15mm	0,200	0,200	25	1,00	18	0,063
000-1823	Air Core Coil 0,200mH +/-3% 0,940Ω wire 0,40mm=26AWG OD-21 / 8mm	0,200	0,940	15	0,40	26	0,008
000-1824	Air Core Coil 0,200mH +/-3% 0,290Ω wire 0,80mm=20AWG OD-34 / 10mm	0,200	0,290	20	0,80	20	0,037
000-1875	Air Core Coil 0,200mH +/-3% 1,000Ω wire 0,40mm=26AWG OD-24 / 10mm	0,200	1,000	20	0,40	26	0,009
000-1928	Air Core Coil 0,200mH +/-3% 0,150Ω wire 1,20mm=17AWG OD-40 / 15mm	0,200	0,150	15	1,20	17	0,092
000-1985	Air Core Coil 0,200mH +/-3% 0,220Ω wire 1,00mm=18AWG OD-26 / 25mm	0,200	0,220	8	1,00	18	0,069
000-0100	Air Core Coil 0,210mH +/-3% 0,080Ω wire 1,80mm=13AWG OD-49 / 30mm	0,210	0,080	25	1,80	13	0,263
000-1074	Air Core Coil 0,210mH +/-3% 0,605Ω wire 0,50mm=24AWG OD-24 / 8mm	0,210	0,605	15	0,50	24	0,014
000-1086	Air Core Coil 0,210mH +/-3% 0,295Ω wire 0,80mm=20AWG OD-34 / 10mm	0,210	0,295	20	0,80	20	0,038
000-1420	Air Core Coil 0,210mH +/-3% 0,460Ω wire 0,70mm=21AWG OD-30 / 30mm	0,210	0,460	25	0,70	21	0,036
000-1559	Air Core Coil 0,210mH +/-3% 0,150Ω wire 1,20mm=17AWG OD-44 / 15mm	0,210	0,150	25	1,20	17	0,095
000-1686	Air Core Coil 0,210mH +/-3% 0,370Ω wire 0,70mm=21AWG OD-31 / 8mm	0,210	0,370	15	0,70	21	0,027
000-0006	Air Core Coil 0,220mH +/-3% 0,104Ω wire 1,60mm=14AWG OD-42 / 25mm	0,220	0,104	8	1,60	14	0,219
000-0106	Air Core Coil 0,220mH +/-3% 0,083Ω wire 1,80mm=13AWG OD-49 / 30mm	0,220	0,083	25	1,80	13	0,265
000-1013	Air Core Coil 0,220mH +/-3% 0,440Ω wire 0,63mm=22AWG OD-29 / 8mm	0,220	0,440	15	0,63	22	0,023
000-1015	Air Core Coil 0,220mH +/-3% 0,210Ω wire 1,00mm=18AWG OD-34 / 15mm	0,220	0,210	15	1,00	18	0,067
000-1125	Air Core Coil 0,220mH +/-3% 0,370Ω wire 0,70mm=21AWG OD-26 / 15mm	0,220	0,370	15	0,70	21	0,031
000-1263	Air Core Coil 0,220mH +/-3% 0,349Ω wire 0,70mm=21AWG OD-31 / 8mm	0,220	0,349	15	0,70	21	0,028
000-1268	Air Core Coil 0,220mH +/-3% 0,120Ω wire 1,40mm=15AWG OD-50 / 15mm	0,220	0,120	25	1,40	15	0,139
000-1278	Air Core Coil 0,220mH +/-3% 0,205Ω wire 1,00mm=18AWG OD-41 / 10mm	0,220	0,205	20	1,00	18	0,065
000-1308	Air Core Coil 0,220mH +/-3% 0,300Ω wire 0,80mm=20AWG OD-33 / 8mm	0,220	0,300	9	0,80	20	0,039
000-1323	Air Core Coil 0,220mH +/-3% 0,640Ω wire 0,50mm=24AWG OD-21 / 8mm	0,220	0,640	9	0,50	24	0,014
000-1345	Air Core Coil 0,220mH +/-3% 0,210Ω wire 1,00mm=18AWG OD-39 / 15mm	0,220	0,210	25	1,00	18	0,068
000-1631	Air Core Coil 0,220mH +/-3% 0,140Ω wire 1,40mm=15AWG OD-41 / 30mm	0,220	0,140	25	1,40	15	0,155
000-1650	Air Core Coil 0,220mH +/-3% 0,465Ω wire 0,63mm=22AWG OD-24 / 15mm	0,220	0,465	15	0,63	22	0,023
000-1674	Air Core Coil 0,220mH +/-3% 0,360Ω wire 0,70mm=21AWG OD-29 / 8mm	0,220	0,360	9	0,70	21	0,029
000-1708	Air Core Coil 0,220mH +/-3% 0,310Ω wire 0,80mm=20AWG OD-28 / 15mm	0,220	0,310	15	0,80	20	0,039
000-1742	Air Core Coil 0,220mH +/-3% 0,465Ω wire 0,70mm=21AWG OD-31 / 30mm	0,220	0,465	25	0,70	21	0,036
000-1745	Air Core Coil 0,220mH +/-3% 0,240Ω wire 1,00mm=18AWG OD-35 / 30mm	0,220	0,240	25	1,00	18	0,075
000-1753	Air Core Coil 0,220mH +/-3% 0,455Ω wire 0,70mm=21AWG OD-23 / 27mm	0,220	0,455	15	0,70	21	0,034
000-1756	Air Core Coil 0,220mH +/-3% 0,230Ω wire 1,00mm=18AWG OD-27 / 27mm	0,220	0,230	15	1,00	18	0,073
000-1825	Air Core Coil 0,220mH +/-3% 0,300Ω wire 0,80mm=20AWG OD-34 / 10mm	0,220	0,300	20	0,80	20	0,039
000-1826	Air Core Coil 0,220mH +/-3% 0,610Ω wire 0,50mm=24AWG OD-24 / 8mm	0,220	0,610	15	0,50	24	0,014
000-1827	Air Core Coil 0,220mH +/-3% 1,070Ω wire 0,40mm=26AWG OD-19 / 15mm	0,220	1,070	15	0,40	26	0,009
000-1909	Air Core Coil 0,220mH +/-3% 0,440Ω wire 0,70mm=21AWG OD-20 / 25mm	0,220	0,440	8	0,70	21	0,034
000-1910	Air Core Coil 0,220mH +/-3% 0,353Ω wire 0,70mm=21AWG OD-31 / 10mm	0,220	0,353	20	0,70	21	0,029
000-1912	Air Core Coil 0,220mH +/-3% 0,880Ω wire 0,40mm=26AWG OD-17 / 8mm	0,220	0,880	9	0,40	26	0,008
000-1914	Air Core Coil 0,220mH +/-3% 0,800Ω wire 0,50mm=24AWG OD-15 / 25mm	0,220	0,800	8	0,50	24	0,017
000-1915	Air Core Coil 0,220mH +/-3% 0,500Ω wire 0,63mm=22AWG OD-17 / 25mm	0,220	0,500	8	0,63	22	0,027
000-1921	Air Core Coil 0,220mH +/-3% 0,170Ω wire 1,20mm=17AWG OD-37 / 30mm	0,220	0,170	25	1,20	17	0,113
000-1922	Air Core Coil 0,220mH +/-3% 0,160Ω wire 1,20mm=17AWG OD-45 / 15mm	0,220	0,160	25	1,20	17	0,100
000-1923	Air Core Coil 0,220mH +/-3% 0,160Ω wire 1,20mm=17AWG OD-40 / 15mm	0,220	0,160	15	1,20	17	0,097
000-1998	Air Core Coil 0,220mH +/-3% 0,230Ω wire 1,00mm=18AWG OD-26 / 25mm	0,220	0,230	8	1,00	18	0,073
000-0227	Air Core Coil 0,230mH +/-3% 0,15Ω wire 1,20mm=17AWG OD-40 / 15mm	0,230	0,150	15	1,20	17	0,106
000-1016	Air Core Coil 0,230mH +/-3% 0,210Ω wire 1,00mm=18AWG OD-34 / 15mm	0,230	0,210	15	1,00	18	0,068
000-1165	Air Core Coil 0,230mH +/-3% 0,370Ω wire 0,70mm=21AWG OD-31 / 8mm	0,230	0,370	15	0,70	21	0,029
000-1616	Air Core Coil 0,230mH +/-3% 0,305Ω wire 0,80mm=20AWG OD-35 / 10mm	0,230	0,305	20	0,80	20	0,040
000-1648	Air Core Coil 0,230mH +/-3% 0,44Ω wire 0,63mm=22AWG OD-29 / 8mm	0,230	0,440	15	0,63	22	0,024
000-0905	Air Core Coil 0,240mH +/-3% 0,125Ω wire 1,40mm=15AWG OD-52 / 15mm	0,240	0,125	25	1,40	15	0,146
000-1017	Air Core Coil 0,240mH +/-3% 1,690Ω wire 0,30mm=29AWG OD-19 / 8mm	0,240	1,690	15	0,30	29	0,005
000-1084	Air Core Coil 0,240mH +/-3% 0,310Ω wire 0,80mm=20AWG OD-35 / 10mm	0,240	0,310	20	0,80	20	0,041
000-1102	Air Core Coil 0,240mH +/-3% 0,640Ω wire 0,50mm=24AWG OD-24 / 8mm	0,240	0,640	15	0,50	24	0,015
000-1481	Air Core Coil 0,240mH +/-3% 1,020Ω wire 0,40mm=26AWG OD-22 / 8mm	0,240	1,020	15	0,40	26	0,009
000-1642	Air Core Coil 0,240mH +/-3% 0,165Ω wire 1,20mm=17AWG OD-40 / 15mm	0,240	0,165	15	1,20	17	0,110
000-1683	Air Core Coil 0,240mH +/-3% 0,375Ω wire 0,70mm=21AWG OD-31 / 8mm	0,240	0,375	15	0,70	21	0,030
000-1926	Air Core Coil 0,240mH +/-3% 0,210Ω wire 1,00mm=18AWG OD-39 / 15mm	0,240	0,210	25	1,00	18	0,071
000-0991	Air Core Coil 0,245mH +/-1% 1,45Ω wire 0,30mm=29AWG OD-15 / 8mm	0,245	1,450	9	0,30	29	0,005
000-1076	Air Core Coil 0,250mH +/-3% 0,220Ω wire 1,00mm=18AWG OD-40 / 15mm	0,250	0,220	25	1,00	18	0,071

Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-1093	Air Core Coil 0,250mH +/-3% 0,170Ω wire 1,20mm=17AWG OD-42 / 15mm	0,250	0,170	15	1,20	17	0,113
000-1152	Air Core Coil 0,250mH +/-3% 0,720Ω wire 0,50mm=24AWG OD-21 / 15mm	0,250	0,720	15	0,50	24	0,016
000-1155	Air Core Coil 0,250mH +/-3% 0,140Ω wire 1,40mm=15AWG OD-41 / 30mm	0,250	0,140	25	1,40	15	0,165
000-1269	Air Core Coil 0,250mH +/-3% 0,128Ω wire 1,40mm=15AWG OD-52 / 15mm	0,250	0,128	25	1,40	15	0,150
000-1279	Air Core Coil 0,250mH +/-3% 0,223Ω wire 1,00mm=18AWG OD-34 / 15mm	0,250	0,223	15	1,00	18	0,072
000-1360	Air Core Coil 0,250mH +/-3% 0,490Ω wire 0,70mm=21AWG OD-31 / 30mm	0,250	0,490	25	0,70	21	0,039
000-1464	Air Core Coil 0,250mH +/-3% 0,400Ω wire 0,70mm=21AWG OD-26 / 15mm	0,250	0,400	15	0,70	21	0,031
000-1490	Air Core Coil 0,250mH +/-3% 0,460Ω wire 0,63mm=22AWG OD-29 / 8mm	0,250	0,460	15	0,63	22	0,024
000-1525	Air Core Coil 0,250mH +/-3% 0,660Ω wire 0,50mm=24AWG OD-24 / 8mm	0,250	0,660	15	0,50	24	0,015
000-1528	Air Core Coil 0,250mH +/-3% 0,330Ω wire 0,80mm=20AWG OD-29 / 15mm	0,250	0,330	15	0,80	20	0,043
000-1645	Air Core Coil 0,250mH +/-3% 0,380Ω wire 0,70mm=21AWG OD-32 / 8mm	0,250	0,380	15	0,70	21	0,031
000-1904	Air Core Coil 0,250mH +/-3% 0,250Ω wire 1,00mm=18AWG OD-35 / 30mm	0,250	0,250	25	1,00	18	0,081
000-1905	Air Core Coil 0,250mH +/-3% 0,250Ω wire 1,00mm=18AWG OD-26 / 25mm	0,250	0,250	8	1,00	18	0,078
000-1925	Air Core Coil 0,250mH +/-3% 1,020Ω wire 0,40mm=26AWG OD-22 / 8mm	0,250	1,020	15	0,40	26	0,010
000-0867	Air Core Coil 0,256mH +/-3% 0,23Ω wire 1,00mm=18AWG OD-35 / 15mm	0,256	0,230	15	1,00	18	0,074
000-0879	Air Core Coil 0,260mH +/-3% 0,470Ω wire 0,63mm=22AWG OD-29 / 8mm	0,260	0,470	15	0,63	22	0,024
000-0904	Air Core Coil 0,260mH +/-3% 0,132Ω wire 1,40mm=15AWG OD-52 / 15mm	0,260	0,132	25	1,40	15	0,157
000-0907	Air Core Coil 0,260mH +/-3% 0,091Ω wire 1,80mm=13AWG OD-50 / 25mm	0,260	0,091	8	1,80	13	0,302
000-1113	Air Core Coil 0,260mH +/-3% 0,317Ω wire 0,80mm=20AWG OD-36 / 10mm	0,260	0,317	20	0,80	20	0,042
000-1162	Air Core Coil 0,260mH +/-3% 0,410Ω wire 0,70mm=21AWG OD-26 / 15mm	0,260	0,410	15	0,70	21	0,033
000-1266	Air Core Coil 0,260mH +/-3% 1,830Ω wire 0,30mm=29AWG OD-19 / 8mm	0,260	1,830	15	0,30	29	0,005
000-1372	Air Core Coil 0,260mH +/-3% 0,260Ω wire 1,00mm=18AWG OD-35 / 30mm	0,260	0,260	25	1,00	18	0,083
000-1412	Air Core Coil 0,260mH +/-3% 0,186Ω wire 1,20mm=17AWG OD-39 / 30mm	0,260	0,186	25	1,20	17	0,116
000-1414	Air Core Coil 0,260mH +/-3% 0,140Ω wire 1,40mm=15AWG OD-41 / 30mm	0,260	0,140	25	1,40	15	0,169
000-1419	Air Core Coil 0,260mH +/-3% 0,500Ω wire 0,70mm=21AWG OD-31 / 30mm	0,260	0,500	25	0,70	21	0,039
000-1728	Air Core Coil 0,260mH +/-3% 0,225Ω wire 1,00mm=18AWG OD-40 / 15mm	0,260	0,225	25	1,00	18	0,073
000-1777	Air Core Coil 0,260mH +/-3% 0,710Ω wire 0,50mm=24AWG OD-22 / 8mm	0,260	0,710	9	0,50	24	0,015
000-1000	Air Core Coil 0,267mH +/-1% 1,90Ω wire 0,30mm=29AWG OD-18 / 8mm	0,267	1,900	15	0,30	29	0,005
000-0007	Air Core Coil 0,270mH +/-3% 0,120Ω wire 1,60mm=14AWG OD-44 / 25mm	0,270	0,120	8	1,60	14	0,242
000-0107	Air Core Coil 0,270mH +/-3% 0,095Ω wire 1,80mm=13AWG OD-52 / 30mm	0,270	0,095	25	1,80	13	0,303
000-0882	Air Core Coil 0,270mH +/-3% 0,750Ω wire 0,50mm=24AWG OD-21 / 15mm	0,270	0,750	15	0,50	24	0,015
000-0889	Air Core Coil 0,270mH +/-3% 0,150Ω wire 1,40mm=15AWG OD-40 / 25mm	0,270	0,150	8	1,40	15	0,181
000-1019	Air Core Coil 0,270mH +/-3% 0,410Ω wire 0,70mm=21AWG OD-26 / 15mm	0,270	0,410	15	0,70	21	0,034
000-1168	Air Core Coil 0,270mH +/-3% 0,414Ω wire 0,70mm=21AWG OD-32 / 10mm	0,270	0,414	20	0,70	21	0,031
000-1208	Air Core Coil 0,270mH +/-3% 0,266Ω wire 1,00mm=18AWG OD-35 / 30mm	0,270	0,266	25	1,00	18	0,085
000-1275	Air Core Coil 0,270mH +/-3% 0,134Ω wire 1,40mm=15AWG OD-52 / 15mm	0,270	0,134	25	1,40	15	0,159
000-1322	Air Core Coil 0,270mH +/-3% 0,710Ω wire 0,50mm=24AWG OD-22 / 8mm	0,270	0,710	9	0,50	24	0,016
000-1350	Air Core Coil 0,270mH +/-3% 0,405Ω wire 0,70mm=21AWG OD-33 / 8mm	0,270	0,405	15	0,70	21	0,031
000-1446	Air Core Coil 0,270mH +/-3% 0,230Ω wire 1,00mm=18AWG OD-40 / 15mm	0,270	0,230	25	1,00	18	0,074
000-1579	Air Core Coil 0,270mH +/-3% 0,17Ω wire 1,20mm=17AWG OD-52 / 10mm	0,270	0,170	20	1,20	17	0,115
000-1632	Air Core Coil 0,270mH +/-3% 0,160Ω wire 1,20mm=17AWG OD-46 / 15mm	0,270	0,160	25	1,20	17	0,113
000-1635	Air Core Coil 0,270mH +/-3% 0,23Ω wire 1,00mm=18AWG OD-35 / 15mm	0,270	0,230	15	1,00	18	0,074
000-1640	Air Core Coil 0,270mH +/-3% 0,490Ω wire 0,63mm=22AWG OD-29 / 8mm	0,270	0,490	15	0,63	22	0,025
000-1769	Air Core Coil 0,270mH +/-3% 0,152Ω wire 1,40mm=15AWG OD-41 / 30mm	0,270	0,152	25	1,40	15	0,170
000-1828	Air Core Coil 0,270mH +/-3% 0,330Ω wire 0,80mm=20AWG OD-36 / 10mm	0,270	0,330	20	0,80	20	0,044
000-1829	Air Core Coil 0,270mH +/-3% 0,680Ω wire 0,50mm=24AWG OD-25 / 8mm	0,270	0,680	15	0,50	24	0,016
000-1986	Air Core Coil 0,270mH +/-3% 0,260Ω wire 1,00mm=18AWG OD-28 / 25mm	0,270	0,260	8	1,00	18	0,082
000-1916	Air Core Coil 0,275mH +/-1% 0,170Ω wire 1,20mm=17AWG OD-46 / 15mm	0,275	0,170	25	1,20	17	0,115
000-1917	Air Core Coil 0,275mH +/-1% 0,235Ω wire 1,00mm=18AWG OD-40 / 15mm	0,275	0,235	25	1,00	18	0,075
000-1919	Air Core Coil 0,275mH +/-1% 0,230Ω wire 1,00mm=18AWG OD-35 / 15mm	0,275	0,230	15	1,00	18	0,075
000-0903	Air Core Coil 0,280mH +/-3% 0,140Ω wire 1,40mm=15AWG OD-53 / 15mm	0,280	0,140	25	1,40	15	0,162
000-1020	Air Core Coil 0,280mH +/-3% 0,500Ω wire 0,63mm=22AWG OD-30 / 8mm	0,280	0,500	15	0,63	22	0,025
000-1114	Air Core Coil 0,280mH +/-3% 0,335Ω wire 0,80mm=20AWG OD-36 / 10mm	0,280	0,335	20	0,80	20	0,045
000-1164	Air Core Coil 0,280mH +/-3% 0,790Ω wire 0,50mm=24AWG OD-21 / 15mm	0,280	0,790	15	0,50	24	0,017
000-1340	Air Core Coil 0,280mH +/-3% 0,240Ω wire 1,00mm=18AWG OD-40 / 15mm	0,280	0,240	25	1,00	18	0,076
000-1456	Air Core Coil 0,280mH +/-3% 0,420Ω wire 0,70mm=21AWG OD-26 / 15mm	0,280	0,420	15	0,70	21	0,034
000-1590	Air Core Coil 0,280mH +/-3% 0,710Ω wire 0,50mm=24AWG OD-25 / 8mm	0,280	0,710	15	0,50	24	0,016
000-1759	Air Core Coil 0,280mH +/-3% 0,192Ω wire 1,20mm=17AWG OD-34 / 27mm	0,280	0,192	15	1,20	17	0,126
000-1764	Air Core Coil 0,280mH +/-3% 0,191Ω wire 1,20mm=17AWG OD-39 / 30mm	0,280	0,191	25	1,20	17	0,124
000-1830	Air Core Coil 0,280mH +/-3% 0,420Ω wire 0,70mm=21AWG OD-33 / 10mm	0,280	0,420	20	0,70	21	0,032
000-1831	Air Core Coil 0,280mH +/-3% 0,760Ω wire 0,50mm=24AWG OD-27 / 10mm	0,280	0,760	20	0,50	24	0,016
000-0065	Air Core Coil 0,290mH +/-3% 0,12Ω wire 1,60mm=14AWG OD-46 / 25mm	0,290	0,120	8	1,60	14	0,246
000-0843	Air Core Coil 0,290mH +/-3% 0,750Ω wire 0,50mm=24AWG OD-25 / 8mm	0,290	0,750	15	0,50	24	0,016
000-0868	Air Core Coil 0,290mH +/-3% 0,180Ω wire 1,20mm=17AWG OD-48 / 15mm	0,290	0,180	25	1,20	17	0,117
000-1643	Air Core Coil 0,290mH +/-3% 0,420Ω wire 0,70mm=21AWG OD-33 / 8mm	0,290	0,420	15	0,70	21	0,032
000-1644	Air Core Coil 0,290mH +/-3% 0,23Ω wire 1,00mm=18AWG OD-36 / 15mm	0,290	0,230	15	1,00	18	0,076
000-1651	Air Core Coil 0,290mH +/-3% 0,520Ω wire 0,63mm=22AWG OD-25 / 15mm	0,290	0,520	15	0,63	22	0,028
000-0954	Air Core Coil 0,300mH +/-3% 0,100Ω wire 1,80mm=13AWG OD-52 / 30mm	0,300	0,100	25	1,80	13	0,325
000-0969	Air Core Coil 0,300mH +/-3% 1,35Ω wire 0,40mm=26AWG OD-16 / 20mm	0,300	1,350	10	0,40	26	0,011
000-1027	Air Core Coil 0,300mH +/-3% 0,210Ω wire 1,20mm=17AWG OD-39 / 30mm	0,300	0,210	25	1,20	17	0,134
000-1143	Air Core Coil 0,300mH +/-3% 0,550Ω wire 0,63mm=22AWG OD-33 / 15mm	0,300	0,550	25	0,63	22	0,028
000-1163	Air Core Coil 0,300mH +/-3% 0,157Ω wire 1,40mm=15AWG OD-43 / 30mm	0,300	0,157	25	1,40	15	0,183
000-1170	Air Core Coil 0,300mH +/-3% 0,440Ω wire 0,70mm=21AWG OD-27 / 15mm	0,300	0,440	15	0,70	21	0,035
000-1223	Air Core Coil 0,300mH +/-3% 0,430Ω wire 0,70mm=21AWG OD-34 / 10mm	0,300	0,430	20	0,70	21	0,035
000-1272	Air Core Coil 0,300mH +/-3% 0,144Ω wire 1,40mm=15AWG OD-53 / 15mm	0,300	0,144	25	1,40	15	0,171
000-1313	Air Core Coil 0,300mH +/-3% 0,24Ω wire 1,00mm=18AWG OD-36 / 15mm	0,300	0,240	15	1,00	18	0,080
000-1315	Air Core Coil 0,300mH +/-3% 0,260Ω wire 1,00mm=18AWG OD-45 / 8mm	0,300	0,260	9	1,00	18	0,078
000-1335	Air Core Coil 0,300mH +/-3% 0,180Ω wire 1,20mm=17AWG OD-48 / 15mm	0,300	0,180	25	1,20	17	0,118
000-1362	Air Core Coil 0,300mH +/-3% 0,540Ω wire 0,70mm=21AWG OD-31 / 30mm	0,300	0,540	25	0,70	21	0,042
000-1452	Air Core Coil 0,300mH +/-3% 0,550Ω wire 0,63mm=22AWG OD-25 / 15mm	0,300	0,550	15	0,63	22	0,028
000-1454	Air Core Coil 0,300mH +/-3% 0,500Ω wire 0,63mm=22AWG OD-30 / 8mm	0,300	0,500	15	0,63	22	0,026
000-1483	Air Core Coil 0,300mH +/-3% 0,160Ω wire 1,40mm=15AWG OD-40 / 25mm	0,300	0,160	8	1,40	15	0,193
000-1575	Air Core Coil 0,300mH +/-3% 0,18Ω wire 1,20mm=17AWG OD-54 / 10mm	0,300	0,180	20	1,20	17	0,124
000-1803	Air Core Coil 0,300mH +/-3% 1,140Ω wire 0,40mm=26AWG OD-22 / 8mm	0,300	1,140	15	0,40	26	0,010
000-1832	Air Core Coil 0,300mH +/-3% 0,370Ω wire 0,80mm=20AWG OD-29 / 15mm	0,300	0,362	15	0,80	20	0,047
000-1833	Air Core Coil 0,300mH +/-3% 0,750Ω wire 0,50mm=24AWG OD-25 / 8mm	0,300	0,750	15	0,50	24	0,016
000-1880	Air Core Coil 0,300mH +/-3% 0,430Ω wire 0,70mm=21AWG OD-33 / 8mm	0,300	0,430	15	0,70	21	0,034
000-1883	Air Core Coil 0,300mH +/-3% 0,750Ω wire 0,50mm=24AWG OD-22 / 8mm	0,300	0,750	9	0,50	24	0,016
000-1884	Air Core Coil 0,300mH +/-3% 1,100Ω wire 0,40mm=26AWG OD-18 / 8mm	0,300	1,100	9	0,40	26	0,009
000-1885	Air Core Coil 0,300mH +/-3% 1,950Ω wire 0,30mm=29AWG OD-19 / 8mm	0,300	1,950	15	0,30	29	0,005
000-0145	Air Core Coil 0,310mH +/-3% 0,24Ω wire 1,00mm=18AWG OD-36 / 15mm	0,310	0,240	15	1,00	18	0,081
000-1433	Air Core Coil 0,310mH +/-3% 0,550Ω wire 0,70mm=21AWG OD-31 / 30mm	0,310	0,550	25	0,70	21	0,043
000-1629	Air Core Coil 0,310mH +/-3% 0,160Ω wire 1,40mm=15AWG OD-43 / 30mm	0,310	0,160	25	1,40	15	0,185
000-1685	Air Core Coil 0,310mH +/-3% 0,460Ω wire 0,70mm=21AWG OD-27 / 15mm	0,310	0,460	15	0,70	21	0,035
000-0166	Air Core Coil 0,320mH +/-3% 0,10Ω wire 1,80mm=13AWG OD-52 / 30mm	0,320	0,100	25	1,80	13	0,340

Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-0173	Air Core Coil 0,320mH +/-3% 0,210Ω wire 1,20mm=17AWG OD-39 / 30mm	0,320	0,210	25	1,20	17	0,137
000-0966	Air Core Coil 0,320mH +/-3% 0,88Ω wire 0,50mm=24AWG OD-22 / 15mm	0,320	0,880	15	0,50	24	0,019
000-1059	Air Core Coil 0,320mH +/-3% 1,970Ω wire 0,30mm=29AWG OD-15 / 8mm	0,320	1,970	9	0,30	29	0,005
000-1115	Air Core Coil 0,320mH +/-3% 0,366Ω wire 0,80mm=20AWG OD-30 / 15mm	0,320	0,366	15	0,80	20	0,049
000-1172	Air Core Coil 0,320mH +/-3% 0,164Ω wire 1,40mm=15AWG OD-43 / 30mm	0,320	0,164	25	1,40	15	0,187
000-1529	Air Core Coil 0,320mH +/-3% 0,560Ω wire 0,63mm=22AWG OD-25 / 15mm	0,320	0,560	15	0,63	22	0,029
000-1661	Air Core Coil 0,320mH +/-3% 0,470Ω wire 0,70mm=21AWG OD-27 / 15mm	0,320	0,470	15	0,70	21	0,036
000-0008	Air Core Coil 0,330mH +/-3% 0,129Ω wire 1,60mm=14AWG OD-46 / 25mm	0,330	0,129	8	1,60	14	0,268
000-0108	Air Core Coil 0,330mH +/-3% 0,105Ω wire 1,80mm=13AWG OD-52 / 30mm	0,330	0,105	25	1,80	13	0,342
000-0890	Air Core Coil 0,330mH +/-3% 0,170Ω wire 1,40mm=15AWG OD-40 / 25mm	0,330	0,170	8	1,40	15	0,189
000-1021	Air Core Coil 0,330mH +/-3% 0,480Ω wire 0,70mm=21AWG OD-28 / 15mm	0,330	0,480	15	0,70	21	0,037
000-1022	Air Core Coil 0,330mH +/-3% 0,260Ω wire 1,00mm=18AWG OD-42 / 15mm	0,330	0,260	25	1,00	18	0,084
000-1071	Air Core Coil 0,330mH +/-3% 0,153Ω wire 1,40mm=15AWG OD-53 / 15mm	0,330	0,153	25	1,40	15	0,179
000-1173	Air Core Coil 0,330mH +/-3% 0,220Ω wire 1,20mm=17AWG OD-39 / 30mm	0,330	0,220	25	1,20	17	0,140
000-1214	Air Core Coil 0,330mH +/-3% 1,240Ω wire 0,40mm=26AWG OD-25 / 10mm	0,330	1,240	20	0,40	26	0,011
000-1264	Air Core Coil 0,330mH +/-3% 0,445Ω wire 0,70mm=21AWG OD-34 / 8mm	0,330	0,445	15	0,70	21	0,036
000-1310	Air Core Coil 0,330mH +/-3% 0,160Ω wire 1,40mm=15AWG OD-44 / 30mm	0,330	0,160	25	1,40	15	0,193
000-1321	Air Core Coil 0,330mH +/-3% 0,790Ω wire 0,50mm=24AWG OD-23 / 8mm	0,330	0,790	9	0,50	24	0,017
000-1513	Air Core Coil 0,330mH +/-3% 1,200Ω wire 0,40mm=26AWG OD-22 / 8mm	0,330	1,200	15	0,40	26	0,010
000-1550	Air Core Coil 0,330mH +/-3% 2,000Ω wire 0,30mm=29AWG OD-20 / 8mm	0,330	2,000	15	0,30	29	0,006
000-1551	Air Core Coil 0,330mH +/-3% 1,970Ω wire 0,30mm=29AWG OD-15 / 8mm	0,330	1,970	9	0,30	29	0,005
000-1679	Air Core Coil 0,330mH +/-3% 0,260Ω wire 1,00mm=18AWG OD-36 / 15mm	0,330	0,260	15	1,00	18	0,085
000-1712	Air Core Coil 0,330mH +/-3% 0,194Ω wire 1,20mm=17AWG OD-48 / 15mm	0,330	0,194	25	1,20	17	0,127
000-1743	Air Core Coil 0,330mH +/-3% 0,561Ω wire 0,70mm=21AWG OD-31 / 30mm	0,330	0,561	25	0,70	21	0,044
000-1746	Air Core Coil 0,330mH +/-3% 0,310Ω wire 1,00mm=18AWG OD-35 / 10mm	0,330	0,310	25	1,00	18	0,093
000-1754	Air Core Coil 0,330mH +/-3% 0,561Ω wire 0,70mm=21AWG OD-24 / 27mm	0,330	0,561	15	0,70	21	0,042
000-1757	Air Core Coil 0,330mH +/-3% 0,293Ω wire 1,00mm=18AWG OD-29 / 27mm	0,330	0,293	15	1,00	18	0,091
000-1834	Air Core Coil 0,330mH +/-3% 0,780Ω wire 0,50mm=24AWG OD-26 / 8mm	0,330	0,780	15	0,50	24	0,018
000-1835	Air Core Coil 0,330mH +/-3% 0,390Ω wire 0,80mm=20AWG OD-30 / 15mm	0,330	0,390	15	0,80	20	0,051
000-1890	Air Core Coil 0,330mH +/-3% 0,580Ω wire 0,63mm=22AWG OD-25 / 15mm	0,330	0,580	15	0,63	22	0,030
000-1987	Air Core Coil 0,330mH +/-3% 0,290Ω wire 1,00mm=18AWG OD-28 / 25mm	0,330	0,290	8	1,00	18	0,090
000-0832	Air Core Coil 0,340mH +/-3% 0,27Ω wire 1,00mm=18AWG OD-37 / 15mm	0,340	0,270	15	1,00	18	0,085
000-0859	Air Core Coil 0,340mH +/-3% 0,10Ω wire 1,80mm=13AWG OD-52 / 30mm	0,340	0,100	25	1,80	13	0,343
000-0869	Air Core Coil 0,340mH +/-3% 0,218Ω wire 1,20mm=17AWG OD-34 / 25mm	0,340	0,218	8	1,20	17	0,136
000-0908	Air Core Coil 0,340mH +/-3% 0,580Ω wire 0,63mm=22AWG OD-31 / 8mm	0,340	0,580	15	0,63	22	0,029
000-1911	Air Core Coil 0,340mH +/-3% 0,790Ω wire 0,50mm=24AWG OD-26 / 8mm	0,340	0,790	15	0,50	24	0,018
000-0860	Air Core Coil 0,350mH +/-3% 0,11Ω wire 1,80mm=13AWG OD-55 / 30mm	0,350	0,110	25	1,80	13	0,351
000-1009	Air Core Coil 0,350mH +/-3% 0,275Ω wire 1,00mm=18AWG OD-37 / 15mm	0,350	0,275	15	1,00	18	0,086
000-1204	Air Core Coil 0,350mH +/-3% 0,400Ω wire 0,80mm=20AWG OD-30 / 15mm	0,350	0,400	15	0,80	20	0,053
000-1332	Air Core Coil 0,350mH +/-3% 0,490Ω wire 0,70mm=21AWG OD-28 / 15mm	0,350	0,490	15	0,70	21	0,038
000-1354	Air Core Coil 0,350mH +/-3% 0,475Ω wire 0,70mm=21AWG OD-34 / 8mm	0,350	0,475	15	0,70	21	0,037
000-1363	Air Core Coil 0,350mH +/-3% 0,580Ω wire 0,70mm=21AWG OD-31 / 30mm	0,350	0,580	25	0,70	21	0,045
000-1417	Air Core Coil 0,350mH +/-3% 0,167Ω wire 1,40mm=15AWG OD-44 / 30mm	0,350	0,167	25	1,40	15	0,201
000-1450	Air Core Coil 0,350mH +/-3% 0,800Ω wire 0,50mm=24AWG OD-26 / 8mm	0,350	0,800	15	0,50	24	0,018
000-1453	Air Core Coil 0,350mH +/-3% 0,580Ω wire 0,63mm=22AWG OD-31 / 8mm	0,350	0,580	15	0,63	22	0,029
000-1836	Air Core Coil 0,350mH +/-3% 1,240Ω wire 0,40mm=26AWG OD-23 / 8mm	0,350	1,240	15	0,40	26	0,010
000-1876	Air Core Coil 0,350mH +/-3% 1,300Ω wire 0,40mm=26AWG OD-25 / 10mm	0,350	1,300	20	0,40	26	0,011
000-1979	Air Core Coil 0,350mH +/-3% 0,230Ω wire 1,20mm=17AWG OD-40 / 30mm	0,350	0,230	25	1,20	17	0,143
000-0054	Air Core Coil 0,360mH +/-3% 0,137Ω wire 1,60mm=14AWG OD-49 / 25mm	0,360	0,137	8	1,60	14	0,282
000-0968	Air Core Coil 0,360mH +/-3% 1,25Ω wire 0,40mm=26AWG OD-23 / 8mm	0,360	1,250	15	0,40	26	0,011
000-1082	Air Core Coil 0,360mH +/-3% 0,525Ω wire 0,70mm=21AWG OD-29 / 15mm	0,360	0,525	15	0,70	21	0,038
000-1153	Air Core Coil 0,360mH +/-3% 0,280Ω wire 1,00mm=18AWG OD-37 / 15mm	0,360	0,280	15	1,00	18	0,088
000-1415	Air Core Coil 0,360mH +/-3% 0,170Ω wire 1,40mm=15AWG OD-44 / 30mm	0,360	0,170	25	1,40	15	0,203
000-1432	Air Core Coil 0,360mH +/-3% 0,590Ω wire 0,70mm=21AWG OD-31 / 30mm	0,360	0,590	25	0,70	21	0,047
000-1628	Air Core Coil 0,360mH +/-3% 0,315Ω wire 1,00mm=18AWG OD-36 / 30mm	0,360	0,315	25	1,00	18	0,098
000-1729	Air Core Coil 0,360mH +/-3% 0,235Ω wire 1,20mm=17AWG OD-40 / 30mm	0,360	0,235	25	1,20	17	0,145
000-0140	Air Core Coil 0,370mH +/-3% 0,110Ω wire 1,80mm=13AWG OD-56 / 30mm	0,370	0,110	25	1,80	13	0,360
000-0858	Air Core Coil 0,370mH +/-3% 0,50Ω wire 0,70mm=21AWG OD-35 / 8mm	0,370	0,500	15	0,70	21	0,038
000-1116	Air Core Coil 0,370mH +/-3% 0,170Ω wire 1,40mm=15AWG OD-44 / 30mm	0,370	0,170	25	1,40	15	0,206
000-1117	Air Core Coil 0,370mH +/-3% 0,280Ω wire 1,00mm=18AWG OD-42 / 15mm	0,370	0,280	25	1,00	18	0,090
000-1177	Air Core Coil 0,370mH +/-3% 0,24Ω wire 1,20mm=17AWG OD-41 / 30mm	0,370	0,240	25	1,20	17	0,147
000-1178	Air Core Coil 0,370mH +/-3% 0,320Ω wire 1,00mm=18AWG OD-36 / 30mm	0,370	0,320	25	1,00	18	0,098
000-1179	Air Core Coil 0,370mH +/-3% 0,920Ω wire 0,50mm=24AWG OD-22 / 15mm	0,370	0,920	15	0,50	24	0,019
000-1317	Air Core Coil 0,370mH +/-3% 0,620Ω wire 0,63mm=22AWG OD-25 / 15mm	0,370	0,620	15	0,63	22	0,031
000-1343	Air Core Coil 0,370mH +/-3% 0,580Ω wire 0,63mm=22AWG OD-31 / 8mm	0,370	0,580	15	0,63	22	0,030
000-1344	Air Core Coil 0,370mH +/-3% 0,630Ω wire 0,63mm=22AWG OD-33 / 15mm	0,370	0,630	25	0,63	22	0,032
000-1492	Air Core Coil 0,370mH +/-3% 0,410Ω wire 0,80mm=20AWG OD-31 / 15mm	0,370	0,410	15	0,80	20	0,053
000-0231	Air Core Coil 0,380mH +/-3% 0,24Ω wire 1,20mm=17AWG OD-41 / 30mm	0,380	0,240	25	1,20	17	0,155
000-0862	Air Core Coil 0,380mH +/-3% 0,11Ω wire 1,80mm=13AWG OD-56 / 30mm	0,380	0,110	25	1,80	13	0,367
000-1004	Air Core Coil 0,380mH +/-3% 0,860Ω wire 0,50mm=24AWG OD-26 / 8mm	0,380	0,860	15	0,50	24	0,018
000-1773	Air Core Coil 0,380mH +/-3% 1,300Ω wire 0,40mm=26AWG OD-23 / 8mm	0,380	1,300	15	0,40	26	0,011
000-1837	Air Core Coil 0,380mH +/-3% 0,285Ω wire 1,00mm=18AWG OD-38 / 15mm	0,380	0,285	15	1,00	18	0,089
000-1593	Air Core Coil 0,383mH +/-1% 0,18Ω wire 1,40mm=15AWG OD-43 / 25mm	0,383	0,180	8	1,40	15	0,215
000-0986	Air Core Coil 0,385mH +/-1% 0,11Ω wire 1,80mm=13AWG OD-55 / 30mm	0,385	0,110	25	1,80	13	0,374
000-0009	Air Core Coil 0,390mH +/-3% 0,140Ω wire 1,60mm=14AWG OD-50 / 25mm	0,390	0,140	8	1,60	14	0,295
000-0109	Air Core Coil 0,390mH +/-3% 0,11Ω wire 1,80mm=13AWG OD-55 / 30mm	0,390	0,110	25	1,80	13	0,374
000-1018	Air Core Coil 0,390mH +/-3% 0,527Ω wire 0,70mm=21AWG OD-29 / 15mm	0,390	0,527	15	0,70	21	0,041
000-1104	Air Core Coil 0,390mH +/-3% 0,290Ω wire 1,00mm=18AWG OD-42 / 15mm	0,390	0,290	25	1,00	18	0,092
000-1181	Air Core Coil 0,390mH +/-3% 0,24Ω wire 1,20mm=17AWG OD-41 / 30mm	0,390	0,240	25	1,20	17	0,155
000-1211	Air Core Coil 0,390mH +/-3% 0,322Ω wire 1,00mm=18AWG OD-37 / 30mm	0,390	0,322	25	1,00	18	0,100
000-1274	Air Core Coil 0,390mH +/-3% 0,167Ω wire 1,40mm=15AWG OD-56 / 15mm	0,390	0,167	25	1,40	15	0,199
000-1292	Air Core Coil 0,390mH +/-3% 0,498Ω wire 0,70mm=21AWG OD-35 / 8mm	0,390	0,498	15	0,70	21	0,039
000-1514	Air Core Coil 0,390mH +/-3% 1,300Ω wire 0,40mm=26AWG OD-23 / 8mm	0,390	1,300	15	0,40	26	0,011
000-1578	Air Core Coil 0,390mH +/-3% 0,21Ω wire 1,20mm=17AWG OD-50 / 10mm	0,390	0,210	20	1,20	17	0,145
000-1624	Air Core Coil 0,390mH +/-3% 0,285Ω wire 1,00mm=18AWG OD-42 / 12mm	0,390	0,285	17	1,00	18	0,090
000-1641	Air Core Coil 0,390mH +/-3% 0,205Ω wire 1,20mm=17AWG OD-50 / 15mm	0,390	0,205	25	1,20	17	0,139
000-1677	Air Core Coil 0,390mH +/-3% 0,293Ω wire 1,00mm=18AWG OD-38 / 15mm	0,390	0,293	15	1,00	18	0,090
000-1838	Air Core Coil 0,390mH +/-3% 0,860Ω wire 0,50mm=24AWG OD-26 / 8mm	0,390	0,860	15	0,50	24	0,018
000-1839	Air Core Coil 0,390mH +/-3% 0,420Ω wire 0,80mm=20AWG OD-31 / 15mm	0,390	0,420	15	0,80	20	0,054
000-1895	Air Core Coil 0,390mH +/-3% 0,170Ω wire 1,40mm=15AWG OD-46 / 30mm	0,390	0,170	25	1,40	15	0,211
000-1908	Air Core Coil 0,390mH +/-3% 0,600Ω wire 0,70mm=21AWG OD-22 / 25mm	0,390	0,600	8	0,70	21	0,046
000-1988	Air Core Coil 0,390mH +/-3% 0,320Ω wire 1,00mm=18AWG OD-29 / 25mm	0,390	0,320	8	1,00	18	0,103
000-0050	Air Core Coil 0,400mH +/-3% 0,140Ω wire 1,60mm=14AWG OD-50 / 25mm	0,400	0,140	8	1,60	14	0,300
000-0829	Air Core Coil 0,400mH +/-3% 0,11Ω wire 1,80mm=13AWG OD-56 / 30mm	0,400	0,110	25	1,80	13	0,382
000-1171	Air Core Coil 0,400mH +/-3% 0,598Ω wire 0,63mm=22AWG OD-32 / 8mm	0,400	0,598	15	0,63	22	0,031

Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-1184	Air Core Coil 0,400mH +/-3% 0,960Ω wire 0,50mm=24AWG OD-23 / 15mm	0,400	0,960	15	0,50	24	0,020
000-1186	Air Core Coil 0,400mH +/-3% 0,180Ω wire 1,40mm=15AWG OD-46 / 30mm	0,400	0,180	25	1,40	15	0,218
000-1243	Air Core Coil 0,400mH +/-3% 0,167Ω wire 1,40mm=15AWG OD-56 / 15mm	0,400	0,167	25	1,40	15	0,201
000-1320	Air Core Coil 0,400mH +/-3% 0,890Ω wire 0,50mm=24AWG OD-24 / 8mm	0,400	0,890	9	0,50	24	0,019
000-1328	Air Core Coil 0,400mH +/-3% 0,890Ω wire 0,50mm=24AWG OD-27 / 8mm	0,400	0,890	15	0,50	24	0,019
000-1364	Air Core Coil 0,400mH +/-3% 0,640Ω wire 0,70mm=21AWG OD-32 / 30mm	0,400	0,640	25	0,70	21	0,049
000-1474	Air Core Coil 0,400mH +/-3% 0,530Ω wire 0,70mm=21AWG OD-29 / 15mm	0,400	0,530	15	0,70	21	0,041
000-1489	Air Core Coil 0,400mH +/-3% 0,640Ω wire 0,63mm=22AWG OD-26 / 15mm	0,400	0,640	15	0,63	22	0,033
000-1512	Air Core Coil 0,400mH +/-3% 0,245Ω wire 1,20mm=17AWG OD-41 / 30mm	0,400	0,245	25	1,20	17	0,156
000-1515	Air Core Coil 0,400mH +/-3% 0,212Ω wire 1,20mm=17AWG OD-45 / 15mm	0,400	0,212	15	1,20	17	0,141
000-1548	Air Core Coil 0,400mH +/-3% 0,183Ω wire 1,40mm=15AWG OD-43 / 25mm	0,400	0,183	8	1,40	15	0,217
000-1552	Air Core Coil 0,400mH +/-3% 2,230Ω wire 0,30mm=29AWG OD-16 / 8mm	0,400	2,230	9	0,30	29	0,006
000-1553	Air Core Coil 0,400mH +/-3% 2,50Ω wire 0,30mm=29AWG OD-18 / 15mm	0,400	2,500	15	0,30	29	0,007
000-1556	Air Core Coil 0,400mH +/-3% 1,700Ω wire 0,40mm=26AWG OD-14 / 25mm	0,400	1,700	8	0,40	26	0,015
000-1654	Air Core Coil 0,400mH +/-3% 0,300Ω wire 1,00mm=18AWG OD-35 / 22mm	0,400	0,300	19	1,00	18	0,098
000-1840	Air Core Coil 0,400mH +/-3% 0,430Ω wire 0,80mm=20AWG OD-32 / 15mm	0,400	0,430	15	0,80	20	0,055
000-1841	Air Core Coil 0,400mH +/-3% 0,330Ω wire 1,00mm=18AWG OD-37 / 30mm	0,400	0,330	25	1,00	18	0,104
000-1950	Air Core Coil 0,400mH +/-3% 0,290Ω wire 1,00mm=18AWG OD-43 / 15mm	0,400	0,290	25	1,00	18	0,094
000-1966	Air Core Coil 0,400mH +/-3% 0,294Ω wire 1,00mm=18AWG OD-38 / 15mm	0,400	0,294	15	1,00	18	0,093
000-0187	Air Core Coil 0,410mH +/-3% 0,18Ω wire 1,40mm=15AWG OD-46 / 30mm	0,410	0,180	25	1,40	15	0,220
000-0847	Air Core Coil 0,410mH +/-3% 0,12Ω wire 1,80mm=13AWG OD-56 / 30mm	0,410	0,120	25	1,80	13	0,383
000-1120	Air Core Coil 0,410mH +/-3% 0,435Ω wire 0,80mm=20AWG OD-32 / 15mm	0,410	0,435	15	0,80	20	0,057
000-1303	Air Core Coil 0,410mH +/-3% 0,300Ω wire 1,00mm=18AWG OD-38 / 15mm	0,410	0,300	15	1,00	18	0,094
000-1304	Air Core Coil 0,410mH +/-3% 0,300Ω wire 1,00mm=18AWG OD-37 / 20mm	0,410	0,300	20	1,00	18	0,090
000-1447	Air Core Coil 0,410mH +/-3% 0,580Ω wire 0,70mm=21AWG OD-29 / 20mm	0,410	0,580	20	0,70	21	0,044
000-0188	Air Core Coil 0,420mH +/-3% 0,12Ω wire 1,80mm=13AWG OD-56 / 30mm	0,420	0,120	25	1,80	13	0,386
000-1157	Air Core Coil 0,420mH +/-3% 0,980Ω wire 0,50mm=24AWG OD-23 / 15mm	0,420	0,980	15	0,50	24	0,021
000-1188	Air Core Coil 0,420mH +/-3% 0,440Ω wire 0,80mm=20AWG OD-32 / 15mm	0,420	0,440	15	0,80	20	0,057
000-1189	Air Core Coil 0,420mH +/-3% 0,190Ω wire 1,40mm=15AWG OD-46 / 30mm	0,420	0,190	25	1,40	15	0,220
000-1190	Air Core Coil 0,420mH +/-3% 1,520Ω wire 0,40mm=26AWG OD-21 / 15mm	0,420	1,520	15	0,40	26	0,013
000-1404	Air Core Coil 0,420mH +/-3% 0,540Ω wire 0,70mm=21AWG OD-29 / 15mm	0,420	0,540	15	0,70	21	0,042
000-1451	Air Core Coil 0,420mH +/-3% 0,650Ω wire 0,63mm=22AWG OD-26 / 15mm	0,420	0,650	15	0,63	22	0,034
000-1574	Air Core Coil 0,420mH +/-3% 0,22Ω wire 1,20mm=17AWG OD-58 / 10mm	0,420	0,220	20	1,20	17	0,150
000-1577	Air Core Coil 0,420mH +/-3% 0,300Ω wire 1,00mm=18AWG OD-37 / 20mm	0,420	0,300	20	1,00	18	0,095
000-1976	Air Core Coil 0,420mH +/-3% 0,250Ω wire 1,20mm=17AWG OD-41 / 30mm	0,420	0,250	25	1,20	17	0,157
000-0911	Air Core Coil 0,424mH +/-1% 0,303Ω wire 1,00mm=18AWG OD-44 / 15mm	0,424	0,303	25	1,00	18	0,095
000-0199	Air Core Coil 0,430mH +/-3% 0,190Ω wire 1,40mm=15AWG OD-46 / 30mm	0,430	0,190	25	1,40	15	0,223
000-0204	Air Core Coil 0,430mH +/-3% 0,385Ω wire 1,00mm=18AWG OD-26 / 40mm	0,430	0,385	10	1,00	18	0,120
000-0820	Air Core Coil 0,430mH +/-3% 0,310Ω wire 1,00mm=18AWG OD-45 / 15mm	0,430	0,300	25	1,00	18	0,097
000-0899	Air Core Coil 0,430mH +/-3% 0,670Ω wire 0,63mm=22AWG OD-34 / 15mm	0,430	0,670	25	0,63	22	0,034
000-1121	Air Core Coil 0,430mH +/-3% 0,445Ω wire 0,80mm=20AWG OD-32 / 15mm	0,430	0,445	15	0,80	20	0,058
000-1842	Air Core Coil 0,430mH +/-3% 0,910Ω wire 0,50mm=24AWG OD-27 / 8mm	0,430	0,910	15	0,50	24	0,020
000-1968	Air Core Coil 0,430mH +/-3% 0,545Ω wire 0,70mm=21AWG OD-29 / 15mm	0,430	0,545	15	0,70	21	0,042
000-0198	Air Core Coil 0,440mH +/-3% 0,190Ω wire 1,40mm=15AWG OD-46 / 30mm	0,440	0,190	25	1,40	15	0,225
000-1191	Air Core Coil 0,440mH +/-3% 0,310Ω wire 1,00mm=18AWG OD-45 / 15mm	0,440	0,310	25	1,00	18	0,098
000-1192	Air Core Coil 0,440mH +/-3% 0,680Ω wire 0,63mm=22AWG OD-34 / 15mm	0,440	0,680	25	0,63	22	0,035
000-1390	Air Core Coil 0,440mH +/-3% 0,260Ω wire 1,20mm=17AWG OD-41 / 30mm	0,440	0,260	25	1,20	17	0,159
000-1391	Air Core Coil 0,440mH +/-3% 1,320Ω wire 0,40mm=26AWG OD-26 / 10mm	0,440	1,320	20	0,40	26	0,012
000-1460	Air Core Coil 0,440mH +/-3% 0,455Ω wire 0,80mm=20AWG OD-32 / 15mm	0,440	0,455	15	0,80	20	0,059
000-1974	Air Core Coil 0,440mH +/-3% 0,560Ω wire 0,70mm=21AWG OD-29 / 15mm	0,440	0,560	15	0,70	21	0,043
000-0053	Air Core Coil 0,450mH +/-3% 0,160Ω wire 1,60mm=14AWG OD-51 / 30mm	0,450	0,160	25	1,60	14	0,315
000-1193	Air Core Coil 0,450mH +/-3% 0,980Ω wire 0,50mm=24AWG OD-29 / 10mm	0,450	0,980	20	0,50	24	0,021
000-1194	Air Core Coil 0,450mH +/-3% 1,560Ω wire 0,40mm=26AWG OD-21 / 15mm	0,450	1,560	15	0,40	26	0,013
000-1195	Air Core Coil 0,450mH +/-3% 0,460Ω wire 0,80mm=20AWG OD-32 / 15mm	0,450	0,460	15	0,80	20	0,061
000-1196	Air Core Coil 0,450mH +/-3% 0,310Ω wire 1,00mm=18AWG OD-39 / 15mm	0,450	0,310	15	1,00	18	0,098
000-1365	Air Core Coil 0,450mH +/-3% 0,660Ω wire 0,70mm=21AWG OD-32 / 30mm	0,450	0,660	25	0,70	21	0,053
000-1400	Air Core Coil 0,450mH +/-3% 0,940Ω wire 0,50mm=24AWG OD-27 / 8mm	0,450	0,940	15	0,50	24	0,020
000-1655	Air Core Coil 0,450mH +/-3% 0,190Ω wire 1,40mm=15AWG OD-46 / 30mm	0,450	0,190	25	1,40	15	0,239
000-1927	Air Core Coil 0,450mH +/-3% 0,260Ω wire 1,20mm=17AWG OD-41 / 30mm	0,450	0,260	25	1,20	17	0,160
000-1197	Air Core Coil 0,460mH +/-3% 1,000Ω wire 0,50mm=24AWG OD-29 / 10mm	0,460	1,000	20	0,50	24	0,021
000-1213	Air Core Coil 0,460mH +/-3% 1,390Ω wire 0,40mm=26AWG OD-23 / 8mm	0,460	1,390	15	0,40	26	0,012
000-1331	Air Core Coil 0,460mH +/-3% 0,560Ω wire 0,70mm=21AWG OD-29 / 15mm	0,460	0,560	15	0,70	21	0,043
000-1877	Air Core Coil 0,460mH +/-3% 1,470Ω wire 0,40mm=26AWG OD-26 / 10mm	0,460	1,470	20	0,40	26	0,013
000-1977	Air Core Coil 0,460mH +/-3% 0,260Ω wire 1,20mm=17AWG OD-41 / 30mm	0,460	0,260	25	1,20	17	0,162
000-0010	Air Core Coil 0,470mH +/-3% 0,164Ω wire 1,60mm=14AWG OD-52 / 30mm	0,470	0,164	25	1,60	14	0,322
000-0110	Air Core Coil 0,470mH +/-3% 0,130Ω wire 1,80mm=13AWG OD-59 / 30mm	0,470	0,130	25	1,80	13	0,409
000-0887	Air Core Coil 0,470mH +/-3% 0,250Ω wire 1,20mm=17AWG OD-50 / 15mm	0,470	0,250	25	1,20	17	0,159
000-0967	Air Core Coil 0,470mH +/-3% 1,70Ω wire 0,40mm=26AWG OD-20 / 20mm	0,470	1,700	10	0,40	26	0,014
000-1030	Air Core Coil 0,470mH +/-3% 0,570Ω wire 0,70mm=21AWG OD-29 / 15mm	0,470	0,570	15	0,70	21	0,045
000-1031	Air Core Coil 0,470mH +/-3% 0,320Ω wire 1,00mm=18AWG OD-45 / 15mm	0,470	0,320	25	1,00	18	0,103
000-1198	Air Core Coil 0,470mH +/-3% 0,260Ω wire 1,20mm=17AWG OD-41 / 30mm	0,470	0,260	25	1,20	17	0,164
000-1242	Air Core Coil 0,470mH +/-3% 0,190Ω wire 1,40mm=15AWG OD-59 / 15mm	0,470	0,190	25	1,40	15	0,218
000-1281	Air Core Coil 0,470mH +/-3% 0,320Ω wire 1,00mm=18AWG OD-40 / 15mm	0,470	0,320	15	1,00	18	0,102
000-1294	Air Core Coil 0,470mH +/-3% 0,690Ω wire 0,63mm=22AWG OD-27 / 15mm	0,470	0,690	15	0,63	22	0,036
000-1297	Air Core Coil 0,470mH +/-3% 0,730Ω wire 0,63mm=22AWG OD-34 / 15mm	0,470	0,730	25	0,63	22	0,036
000-1518	Air Core Coil 0,470mH +/-3% 0,200Ω wire 1,40mm=15AWG OD-46 / 30mm	0,470	0,200	25	1,40	15	0,232
000-1539	Air Core Coil 0,470mH +/-3% 0,330Ω wire 1,00mm=18AWG OD-37 / 20mm	0,470	0,330	20	1,00	18	0,093
000-1636	Air Core Coil 0,470mH +/-3% 1,350Ω wire 0,40mm=26AWG OD-20 / 8mm	0,470	1,350	9	0,40	26	0,012
000-1747	Air Core Coil 0,470mH +/-3% 0,355Ω wire 1,00mm=18AWG OD-37 / 30mm	0,470	0,355	25	1,00	18	0,112
000-1758	Air Core Coil 0,470mH +/-3% 0,351Ω wire 1,00mm=18AWG OD-33 / 27mm	0,470	0,351	15	1,00	18	0,111
000-1760	Air Core Coil 0,470mH +/-3% 0,259Ω wire 1,20mm=17AWG OD-38 / 12mm	0,470	0,259	15	1,20	17	0,167
000-1843	Air Core Coil 0,470mH +/-3% 0,470Ω wire 0,80mm=20AWG OD-32 / 15mm	0,470	0,470	15	0,80	20	0,062
000-1845	Air Core Coil 0,470mH +/-3% 0,950Ω wire 0,50mm=24AWG OD-27 / 8mm	0,470	0,950	15	0,50	24	0,021
000-1989	Air Core Coil 0,470mH +/-3% 0,360Ω wire 1,00mm=18AWG OD-31 / 25mm	0,470	0,360	8	1,00	18	0,111
000-0209	Air Core Coil 0,480mH +/-3% 0,200Ω wire 1,40mm=15AWG OD-46 / 30mm	0,480	0,200	25	1,40	15	0,232
000-1054	Air Core Coil 0,480mH +/-3% 0,260Ω wire 1,20mm=17AWG OD-41 / 30mm	0,480	0,260	25	1,20	17	0,168
000-1201	Air Core Coil 0,480mH +/-3% 0,325Ω wire 1,00mm=18AWG OD-45 / 15mm	0,480	0,325	25	1,00	18	0,104
000-1573	Air Core Coil 0,480mH +/-3% 0,24Ω wire 1,20mm=17AWG OD-61 / 10mm	0,480	0,240	20	1,20	17	0,162
000-1755	Air Core Coil 0,480mH +/-3% 0,700Ω wire 0,70mm=21AWG OD-25 / 27mm	0,480	0,700	15	0,70	21	0,053
000-1762	Air Core Coil 0,480mH +/-3% 0,690Ω wire 0,70mm=21AWG OD-32 / 30mm	0,480	0,690	25	0,70	21	0,054
000-0175	Air Core Coil 0,490mH +/-3% 0,13Ω wire 1,80mm=13AWG OD-59 / 30mm	0,490	0,130	25	1,80	13	0,433
000-0194	Air Core Coil 0,490mH +/-3% 0,201Ω wire 1,40mm=15AWG OD-46 / 30mm	0,490	0,201	25	1,40	15	0,236
000-0228	Air Core Coil 0,490mH +/-3% 0,26Ω wire 1,20mm=17AWG OD-41 / 30mm	0,490	0,260	25	1,20	17	0,175
000-1055	Air Core Coil 0,490mH +/-3% 2,430Ω wire 0,30mm=29AWG OD-16 / 8mm	0,490	2,430	9	0,30	29	0,007
000-1122	Air Core Coil 0,490mH +/-3% 0,477Ω wire 0,80mm=20AWG OD-33 / 15mm	0,490	0,477	15	0,80	20	0,063

Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-1202	Air Core Coil 0,490mH +/-3% 1,630Ω wire 0,40mm=26AWG OD-21 / 15mm	0,490	1,630	15	0,40	26	0,014
000-1203	Air Core Coil 0,490mH +/-3% 0,325Ω wire 1,00mm=18AWG OD-40 / 15mm	0,490	0,325	15	1,00	18	0,104
000-1689	Air Core Coil 0,490mH +/-3% 0,580Ω wire 0,70mm=21AWG OD-30 / 15mm	0,490	0,580	15	0,70	21	0,046
000-0835	Air Core Coil 0,500mH +/-3% 0,70Ω wire 0,70mm=21AWG OD-23 / 25mm	0,500	0,700	8	0,70	21	0,053
000-0855	Air Core Coil 0,500mH +/-3% 0,71Ω wire 0,63mm=22AWG OD-27 / 15mm	0,500	0,710	15	0,63	22	0,038
000-0883	Air Core Coil 0,500mH +/-3% 1,080Ω wire 0,50mm=24AWG OD-23 / 15mm	0,500	1,080	15	0,50	24	0,022
000-0950	Air Core Coil 0,500mH +/-3% 0,260Ω wire 1,20mm=17AWG OD-40 / 25mm	0,500	0,260	15	1,20	17	0,170
000-0981	Air Core Coil 0,500mH +/-3% 0,160Ω wire 1,60mm=14AWG OD-53 / 30mm	0,500	0,160	25	1,60	14	0,331
000-1034	Air Core Coil 0,500mH +/-3% 0,490Ω wire 0,80mm=20AWG OD-33 / 15mm	0,500	0,490	15	0,80	20	0,063
000-1205	Air Core Coil 0,500mH +/-3% 0,280Ω wire 1,20mm=17AWG OD-41 / 30mm	0,500	0,280	25	1,20	17	0,176
000-1267	Air Core Coil 0,500mH +/-3% 0,203Ω wire 1,40mm=15AWG OD-48 / 30mm	0,500	0,203	25	1,40	15	0,238
000-1327	Air Core Coil 0,500mH +/-3% 1,000Ω wire 0,50mm=24AWG OD-28 / 8mm	0,500	1,000	15	0,50	24	0,022
000-1366	Air Core Coil 0,500mH +/-3% 0,700Ω wire 0,70mm=21AWG OD-32 / 30mm	0,500	0,700	25	0,70	21	0,055
000-1389	Air Core Coil 0,500mH +/-3% 1,530Ω wire 0,40mm=26AWG OD-26 / 10mm	0,500	1,530	20	0,40	26	0,014
000-1401	Air Core Coil 0,500mH +/-3% 0,330Ω wire 1,00mm=18AWG OD-40 / 15mm	0,500	0,330	15	1,00	18	0,107
000-1402	Air Core Coil 0,500mH +/-3% 0,340Ω wire 1,00mm=18AWG OD-39 / 20mm	0,500	0,340	20	1,00	18	0,107
000-1403	Air Core Coil 0,500mH +/-3% 0,380Ω wire 1,00mm=18AWG OD-39 / 30mm	0,500	0,380	25	1,00	18	0,118
000-1405	Air Core Coil 0,500mH +/-3% 0,580Ω wire 0,70mm=21AWG OD-30 / 15mm	0,500	0,580	15	0,70	21	0,047
000-1505	Air Core Coil 0,500mH +/-3% 0,248Ω wire 1,20mm=17AWG OD-48 / 15mm	0,500	0,248	15	1,20	17	0,158
000-1555	Air Core Coil 0,500mH +/-3% 1,500Ω wire 0,40mm=26AWG OD-24 / 8mm	0,500	1,500	15	0,40	26	0,013
000-1596	Air Core Coil 0,500mH +/-3% 0,670Ω wire 0,63mm=22AWG OD-33 / 8mm	0,500	0,670	15	0,63	22	0,035
000-1881	Air Core Coil 0,500mH +/-3% 0,640Ω wire 0,70mm=21AWG OD-30 / 20mm	0,500	0,640	20	0,70	21	0,050
000-0174	Air Core Coil 0,510mH +/-3% 0,132Ω wire 1,80mm=13AWG OD-59 / 30mm	0,510	0,132	25	1,80	13	0,441
000-0195	Air Core Coil 0,510mH +/-3% 0,204Ω wire 1,40mm=15AWG OD-48 / 30mm	0,510	0,204	25	1,40	15	0,250
000-1123	Air Core Coil 0,510mH +/-3% 0,495Ω wire 0,80mm=20AWG OD-33 / 15mm	0,510	0,495	15	0,80	20	0,064
000-1319	Air Core Coil 0,510mH +/-3% 1,010Ω wire 0,50mm=24AWG OD-25 / 8mm	0,510	1,010	9	0,50	24	0,021
000-1431	Air Core Coil 0,510mH +/-3% 0,710Ω wire 0,70mm=21AWG OD-32 / 30mm	0,510	0,710	25	0,70	21	0,056
000-0977	Air Core Coil 0,518mH +/-3% 2,52Ω wire 0,30mm=29AWG OD-19 / 15mm	0,518	2,520	15	0,30	29	0,009
000-0924	Air Core Coil 0,520mH +/-3% 0,261Ω wire 1,20mm=17AWG OD-52 / 15mm	0,520	0,261	25	1,20	17	0,162
000-0925	Air Core Coil 0,520mH +/-3% 0,26Ω wire 1,20mm=17AWG OD-41 / 25mm	0,520	0,261	15	1,20	17	0,175
000-1479	Air Core Coil 0,520mH +/-3% 0,210Ω wire 1,40mm=15AWG OD-48 / 30mm	0,520	0,210	25	1,40	15	0,253
000-1545	Air Core Coil 0,520mH +/-3% 0,340Ω wire 1,00mm=18AWG OD-46 / 15mm	0,520	0,340	25	1,00	18	0,107
000-1665	Air Core Coil 0,520mH +/-3% 0,590Ω wire 0,70mm=21AWG OD-30 / 15mm	0,520	0,590	15	0,70	21	0,047
000-0099	Air Core Coil 0,530mH +/-3% 0,135Ω wire 1,80mm=13AWG OD-59 / 30mm	0,530	0,135	25	1,80	13	0,459
000-0210	Air Core Coil 0,530mH +/-3% 0,210Ω wire 1,40mm=15AWG OD-48 / 30mm	0,530	0,210	25	1,40	15	0,255
000-0995	Air Core Coil 0,530mH +/-3% 0,295Ω wire 1,20mm=17AWG OD-43 / 30mm	0,530	0,295	25	1,20	17	0,177
000-1124	Air Core Coil 0,530mH +/-3% 0,500Ω wire 0,80mm=20AWG OD-34 / 15mm	0,530	0,500	15	0,80	20	0,066
000-0178	Air Core Coil 0,540mH +/-3% 0,21Ω wire 1,40mm=15AWG OD-49 / 30mm	0,540	0,210	25	1,40	15	0,257
000-0180	Air Core Coil 0,540mH +/-3% 0,14Ω wire 1,80mm=13AWG OD-59 / 30mm	0,540	0,140	25	1,80	13	0,465
000-0929	Air Core Coil 0,540mH +/-3% 0,385Ω wire 1,00mm=18AWG OD-33 / 25mm	0,540	0,385	8	1,00	18	0,120
000-0961	Air Core Coil 0,550mH +/-3% 0,360Ω wire 1,00mm=18AWG OD-39 / 20mm	0,550	0,360	20	1,00	18	0,111
000-1036	Air Core Coil 0,550mH +/-3% 0,220Ω wire 1,40mm=15AWG OD-49 / 30mm	0,550	0,220	25	1,40	15	0,253
000-1145	Air Core Coil 0,550mH +/-3% 0,750Ω wire 0,63mm=22AWG OD-27 / 15mm	0,550	0,750	15	0,63	22	0,039
000-1209	Air Core Coil 0,550mH +/-3% 0,600Ω wire 0,70mm=21AWG OD-30 / 15mm	0,550	0,600	15	0,70	21	0,049
000-1435	Air Core Coil 0,550mH +/-3% 1,520Ω wire 0,40mm=26AWG OD-24 / 8mm	0,550	1,520	15	0,40	26	0,013
000-1509	Air Core Coil 0,550mH +/-3% 0,300Ω wire 1,20mm=17AWG OD-43 / 30mm	0,550	0,300	25	1,20	17	0,182
000-1846	Air Core Coil 0,550mH +/-3% 0,500Ω wire 0,80mm=20AWG OD-34 / 15mm	0,550	0,500	15	0,80	20	0,068
000-0011	Air Core Coil 0,560mH +/-3% 0,180Ω wire 1,60mm=14AWG OD-54 / 30mm	0,560	0,180	25	1,60	14	0,356
000-0111	Air Core Coil 0,560mH +/-3% 0,140Ω wire 1,80mm=13AWG OD-59 / 30mm	0,560	0,140	25	1,80	13	0,470
000-0888	Air Core Coil 0,560mH +/-3% 0,272Ω wire 1,20mm=17AWG OD-55 / 15mm	0,560	0,272	25	1,20	17	0,172
000-1026	Air Core Coil 0,560mH +/-3% 0,760Ω wire 0,63mm=22AWG OD-27 / 15mm	0,560	0,760	15	0,63	22	0,039
000-1035	Air Core Coil 0,560mH +/-3% 0,360Ω wire 1,00mm=18AWG OD-46 / 15mm	0,560	0,360	25	1,00	18	0,111
000-1040	Air Core Coil 0,560mH +/-3% 0,610Ω wire 0,70mm=21AWG OD-30 / 15mm	0,560	0,610	15	0,70	21	0,050
000-1161	Air Core Coil 0,560mH +/-3% 1,530Ω wire 0,40mm=26AWG OD-24 / 8mm	0,560	1,530	15	0,40	26	0,013
000-1210	Air Core Coil 0,560mH +/-3% 0,300Ω wire 1,20mm=17AWG OD-43 / 30mm	0,560	0,300	25	1,20	17	0,182
000-1373	Air Core Coil 0,560mH +/-3% 0,400Ω wire 1,00mm=18AWG OD-39 / 30mm	0,560	0,400	25	1,00	18	0,124
000-1407	Air Core Coil 0,560mH +/-3% 0,45Ω wire 1,00mm=18AWG OD-30 / 40mm	0,560	0,450	10	1,00	18	0,139
000-1572	Air Core Coil 0,560mH +/-3% 0,27Ω wire 1,20mm=17AWG OD-46 / 20mm	0,560	0,270	20	1,20	17	0,177
000-1678	Air Core Coil 0,560mH +/-3% 0,345Ω wire 1,00mm=18AWG OD-40 / 15mm	0,560	0,345	15	1,00	18	0,116
000-1847	Air Core Coil 0,560mH +/-3% 1,100Ω wire 0,50mm=24AWG OD-28 / 8mm	0,560	1,100	15	0,50	24	0,023
000-1848	Air Core Coil 0,560mH +/-3% 0,510Ω wire 0,80mm=20AWG OD-34 / 15mm	0,560	0,510	15	0,80	20	0,068
000-1896	Air Core Coil 0,560mH +/-3% 0,220Ω wire 1,40mm=15AWG OD-49 / 30mm	0,560	0,220	25	1,40	15	0,258
000-1990	Air Core Coil 0,560mH +/-3% 0,390Ω wire 1,00mm=18AWG OD-33 / 25mm	0,560	0,390	8	1,00	18	0,125
000-0155	Air Core Coil 0,580mH +/-3% 0,51Ω wire 0,80mm=20AWG OD-33 / 15mm	0,580	0,510	15	0,80	20	0,069
000-1039	Air Core Coil 0,580mH +/-3% 2,820Ω wire 0,30mm=29AWG OD-17 / 8mm	0,580	2,820	9	0,30	29	0,007
000-1302	Air Core Coil 0,580mH +/-3% 0,310Ω wire 1,20mm=17AWG OD-43 / 30mm	0,580	0,310	25	1,20	17	0,187
000-1700	Air Core Coil 0,580mH +/-3% 3,120Ω wire 0,30mm=29AWG OD-19 / 15mm	0,580	3,120	15	0,30	29	0,009
000-1439	Air Core Coil 0,590mH +/-3% 0,815Ω wire 0,63mm=22AWG OD-28 / 15mm	0,590	0,815	15	0,63	22	0,040
000-0052	Air Core Coil 0,600mH +/-3% 0,184Ω wire 1,60mm=14AWG OD-54 / 30mm	0,600	0,184	25	1,60	14	0,370
000-0151	Air Core Coil 0,600mH +/-3% 0,150Ω wire 1,80mm=13AWG OD-62 / 30mm	0,600	0,150	25	1,80	13	0,480
000-0213	Air Core Coil 0,600mH +/-3% 3,18Ω wire 0,30mm=29AWG OD-19 / 15mm	0,600	3,180	15	0,30	29	0,009
000-0912	Air Core Coil 0,600mH +/-3% 0,279Ω wire 1,20mm=17AWG OD-56 / 15mm	0,600	0,279	25	1,20	17	0,173
000-1367	Air Core Coil 0,600mH +/-3% 0,770Ω wire 0,70mm=21AWG OD-32 / 30mm	0,600	0,770	25	0,70	21	0,061
000-1406	Air Core Coil 0,600mH +/-3% 0,630Ω wire 0,70mm=21AWG OD-30 / 15mm	0,600	0,630	15	0,70	21	0,054
000-1444	Air Core Coil 0,600mH +/-3% 0,230Ω wire 1,40mm=15AWG OD-49 / 30mm	0,600	0,230	25	1,40	15	0,268
000-1511	Air Core Coil 0,600mH +/-3% 0,310Ω wire 1,20mm=17AWG OD-43 / 30mm	0,600	0,310	25	1,20	17	0,191
000-1571	Air Core Coil 0,600mH +/-3% 0,28Ω wire 1,20mm=17AWG OD-48 / 20mm	0,600	0,280	20	1,20	17	0,184
000-1735	Air Core Coil 0,600mH +/-3% 1,600Ω wire 0,40mm=26AWG OD-24 / 8mm	0,600	1,600	15	0,40	26	0,014
000-1761	Air Core Coil 0,600mH +/-3% 0,294Ω wire 1,20mm=17AWG OD-41 / 27mm	0,600	0,294	15	1,20	17	0,193
000-1849	Air Core Coil 0,600mH +/-3% 1,120Ω wire 0,50mm=24AWG OD-29 / 8mm	0,600	1,120	15	0,50	24	0,024
000-1850	Air Core Coil 0,600mH +/-3% 0,530Ω wire 0,80mm=20AWG OD-35 / 15mm	0,600	0,530	15	0,80	20	0,071
000-1851	Air Core Coil 0,600mH +/-3% 0,410Ω wire 1,00mm=18AWG OD-39 / 30mm	0,600	0,410	25	1,00	18	0,129
000-1951	Air Core Coil 0,600mH +/-3% 0,370Ω wire 1,00mm=18AWG OD-47 / 15mm	0,600	0,370	25	1,00	18	0,117
000-1967	Air Core Coil 0,600mH +/-3% 0,370Ω wire 1,00mm=18AWG OD-44 / 15mm	0,600	0,370	15	1,00	18	0,116
000-1991	Air Core Coil 0,600mH +/-3% 0,410Ω wire 1,00mm=18AWG OD-33 / 25mm	0,600	0,410	8	1,00	18	0,129
000-0987	Air Core Coil 0,610mH +/-3% 0,22Ω wire 1,40mm=15AWG OD-49 / 30mm	0,610	0,220	25	1,40	15	0,278
000-1353	Air Core Coil 0,610mH +/-3% 0,820Ω wire 0,63mm=22AWG OD-28 / 15mm	0,610	0,820	15	0,63	22	0,043
000-0012	Air Core Coil 0,620mH +/-3% 0,189Ω wire 1,60mm=14AWG OD-54 / 30mm	0,620	0,189	25	1,60	14	0,375
000-0112	Air Core Coil 0,620mH +/-3% 0,150Ω wire 1,80mm=13AWG OD-62 / 30mm	0,620	0,150	25	1,80	13	0,483
000-0927	Air Core Coil 0,620mH +/-3% 0,380Ω wire 1,00mm=18AWG OD-47 / 15mm	0,620	0,380	25	1,00	18	0,120
000-0988	Air Core Coil 0,620mH +/-3% 0,22Ω wire 1,40mm=15AWG OD-49 / 30mm	0,620	0,220	25	1,40	15	0,279
000-1265	Air Core Coil 0,620mH +/-3% 1,140Ω wire 0,50mm=24AWG OD-29 / 8mm	0,620	1,140	15	0,50	24	0,024
000-1558	Air Core Coil 0,620mH +/-3% 0,550Ω wire 0,80mm=20AWG OD-35 / 15mm	0,620	0,550	15	0,80	20	0,072
000-1668	Air Core Coil 0,620mH +/-3% 0,650Ω wire 0,70mm=21AWG OD-30 / 15mm	0,620	0,650	15	0,70	21	0,055
000-0165	Air Core Coil 0,630mH +/-3% 0,23Ω wire 1,40mm=15AWG OD-49 / 30mm	0,630	0,230	25	1,40	15	0,280



Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-0214	Air Core Coil 0,630mH +/-3% 3,190Ω wire 0,30mm=29AWG OD-19 / 15mm	0,630	3,190	15	0,30	29	0,010
000-1398	Air Core Coil 0,637mH +/-1% 0,890Ω wire 0,63mm=22AWG OD-29 / 15mm	0,637	0,890	15	0,63	22	0,042
000-0215	Air Core Coil 0,640mH +/-3% 0,380Ω wire 1,00mm=18AWG OD-47 / 15mm	0,640	0,380	25	1,00	18	0,124
000-0913	Air Core Coil 0,640mH +/-3% 0,286Ω wire 1,20mm=17AWG OD-56 / 15mm	0,640	0,286	25	1,20	17	0,178
000-1731	Air Core Coil 0,640mH +/-3% 0,240Ω wire 1,40mm=15AWG OD-49 / 30mm	0,640	0,240	25	1,40	15	0,281
000-1796	Air Core Coil 0,640mH +/-3% 1,680Ω wire 0,40mm=26AWG OD-25 / 8mm	0,640	1,680	15	0,40	26	0,015
000-0142	Air Core Coil 0,650mH +/-3% 0,153Ω wire 1,80mm=13AWG OD-62 / 30mm	0,650	0,153	25	1,80	13	0,503
000-0863	Air Core Coil 0,650mH +/-3% 0,430Ω wire 1,00mm=18AWG OD-34 / 25mm	0,650	0,430	8	1,00	18	0,133
000-0914	Air Core Coil 0,650mH +/-3% 0,800Ω wire 0,70mm=21AWG OD-25 / 25mm	0,650	0,800	8	0,70	21	0,063
000-1085	Air Core Coil 0,650mH +/-3% 0,430Ω wire 1,00mm=18AWG OD-39 / 30mm	0,650	0,430	25	1,00	18	0,135
000-1416	Air Core Coil 0,650mH +/-3% 0,240Ω wire 1,40mm=15AWG OD-49 / 30mm	0,650	0,240	25	1,40	15	0,282
000-1737	Air Core Coil 0,650mH +/-3% 1,160Ω wire 0,50mm=24AWG OD-29 / 8mm	0,650	1,160	15	0,50	24	0,025
000-1772	Air Core Coil 0,650mH +/-3% 1,680Ω wire 0,40mm=26AWG OD-25 / 8mm	0,650	1,680	15	0,40	26	0,015
000-1791	Air Core Coil 0,650mH +/-3% 0,320Ω wire 1,20mm=17AWG OD-43 / 30mm	0,650	0,320	25	1,20	17	0,198
000-1929	Air Core Coil 0,650mH +/-3% 0,560Ω wire 0,80mm=20AWG OD-35 / 15mm	0,650	0,560	15	0,80	20	0,074
000-1952	Air Core Coil 0,650mH +/-3% 0,380Ω wire 1,00mm=18AWG OD-47 / 15mm	0,650	0,380	25	1,00	18	0,124
000-0916	Air Core Coil 0,665mH +/-1% 0,245Ω wire 1,40mm=15AWG OD-49 / 30mm	0,665	0,245	25	1,40	15	0,283
000-0179	Air Core Coil 0,670mH +/-3% 0,55Ω wire 0,80mm=20AWG OD-35 / 15mm	0,670	0,550	15	0,80	20	0,074
000-0982	Air Core Coil 0,670mH +/-3% 0,24Ω wire 1,40mm=15AWG OD-49 / 30mm	0,670	0,240	25	1,40	15	0,285
000-0013	Air Core Coil 0,680mH +/-3% 0,200Ω wire 1,60mm=14AWG OD-54 / 30mm	0,680	0,200	25	1,60	14	0,393
000-0113	Air Core Coil 0,680mH +/-3% 0,155Ω wire 1,80mm=13AWG OD-62 / 30mm	0,680	0,155	25	1,80	13	0,520
000-1044	Air Core Coil 0,680mH +/-3% 0,700Ω wire 0,70mm=21AWG OD-32 / 15mm	0,680	0,700	15	0,70	21	0,056
000-1282	Air Core Coil 0,680mH +/-3% 0,400Ω wire 1,00mm=18AWG OD-45 / 15mm	0,680	0,400	15	1,00	18	0,130
000-1287	Air Core Coil 0,680mH +/-3% 0,410Ω wire 1,00mm=18AWG OD-48 / 15mm	0,680	0,410	25	1,00	18	0,125
000-1305	Air Core Coil 0,680mH +/-3% 0,330Ω wire 1,20mm=17AWG OD-43 / 30mm	0,680	0,330	25	1,20	17	0,203
000-1537	Air Core Coil 0,680mH +/-3% 0,440Ω wire 1,00mm=18AWG OD-39 / 30mm	0,680	0,440	25	1,00	18	0,139
000-1542	Air Core Coil 0,680mH +/-3% 3,530Ω wire 0,30mm=29AWG OD-19 / 15mm	0,680	3,530	15	0,30	29	0,010
000-1570	Air Core Coil 0,680mH +/-3% 0,30Ω wire 1,20mm=17AWG OD-48 / 20mm	0,680	0,300	20	1,20	17	0,197
000-1766	Air Core Coil 0,680mH +/-3% 0,870Ω wire 0,63mm=22AWG OD-28 / 15mm	0,680	0,870	15	0,63	22	0,042
000-1852	Air Core Coil 0,680mH +/-3% 0,560Ω wire 0,80mm=20AWG OD-35 / 15mm	0,680	0,560	15	0,80	20	0,075
000-1853	Air Core Coil 0,680mH +/-3% 1,220Ω wire 0,50mm=24AWG OD-31 / 10mm	0,680	1,220	20	0,50	24	0,026
000-1854	Air Core Coil 0,680mH +/-3% 0,240Ω wire 1,40mm=15AWG OD-49 / 30mm	0,680	0,240	25	1,40	15	0,288
000-1907	Air Core Coil 0,680mH +/-3% 0,820Ω wire 0,70mm=21AWG OD-25 / 25mm	0,680	0,820	8	0,70	21	0,064
000-1997	Air Core Coil 0,680mH +/-3% 0,440Ω wire 1,00mm=18AWG OD-34 / 25mm	0,680	0,440	8	1,00	18	0,138
000-0221	Air Core Coil 0,690mH +/-3% 0,88Ω wire 0,63mm=22AWG OD-29 / 15mm	0,690	0,880	15	0,63	22	0,043
000-0821	Air Core Coil 0,690mH +/-3% 0,390Ω wire 1,00mm=18AWG OD-48 / 15mm	0,690	0,390	25	1,00	18	0,128
000-0807	Air Core Coil 0,700mH +/-3% 1,31Ω wire 0,50mm=24AWG OD-21 / 15mm	0,700	1,310	8	0,50	24	0,028
000-0808	Air Core Coil 0,700mH +/-3% 1,74Ω wire 0,50mm=24AWG OD-18 / 40mm	0,700	1,740	10	0,50	24	0,036
000-0989	Air Core Coil 0,700mH +/-3% 1,75Ω wire 0,40mm=26AWG OD-25 / 8mm	0,700	1,750	15	0,40	26	0,015
000-1046	Air Core Coil 0,700mH +/-3% 1,250Ω wire 0,50mm=24AWG OD-30 / 8mm	0,700	1,250	15	0,50	24	0,025
000-1144	Air Core Coil 0,700mH +/-3% 0,400Ω wire 1,00mm=18AWG OD-48 / 15mm	0,700	0,400	25	1,00	18	0,127
000-1334	Air Core Coil 0,700mH +/-3% 0,710Ω wire 0,70mm=21AWG OD-32 / 15mm	0,700	0,710	15	0,70	21	0,057
000-1352	Air Core Coil 0,700mH +/-3% 0,900Ω wire 0,63mm=22AWG OD-29 / 15mm	0,700	0,900	15	0,63	22	0,044
000-1410	Air Core Coil 0,700mH +/-3% 0,850Ω wire 0,70mm=21AWG OD-33 / 30mm	0,700	0,850	25	0,70	21	0,066
000-1510	Air Core Coil 0,700mH +/-3% 0,340Ω wire 1,20mm=17AWG OD-45 / 30mm	0,700	0,340	25	1,20	17	0,210
000-1554	Air Core Coil 0,700mH +/-3% 3,870Ω wire 0,30mm=29AWG OD-20 / 15mm	0,700	3,870	15	0,30	29	0,010
000-1569	Air Core Coil 0,700mH +/-3% 0,30Ω wire 1,20mm=17AWG OD-48 / 20mm	0,700	0,300	20	1,20	17	0,200
000-1615	Air Core Coil 0,700mH +/-3% 0,245Ω wire 1,40mm=15AWG OD-50 / 30mm	0,700	0,245	25	1,40	15	0,292
000-1855	Air Core Coil 0,700mH +/-3% 0,570Ω wire 0,80mm=20AWG OD-35 / 15mm	0,700	0,570	15	0,80	20	0,077
000-0877	Air Core Coil 0,710mH +/-3% 0,40Ω wire 1,00mm=18AWG OD-48 / 15mm	0,710	0,400	25	1,00	18	0,128
000-0878	Air Core Coil 0,710mH +/-3% 1,750Ω wire 0,40mm=26AWG OD-25 / 8mm	0,710	1,750	15	0,40	26	0,015
000-0866	Air Core Coil 0,720mH +/-3% 0,40Ω wire 1,00mm=18AWG OD-49 / 15mm	0,720	0,400	25	1,00	18	0,130
000-0940	Air Core Coil 0,720mH +/-3% 0,25Ω wire 1,40mm=15AWG OD-50 / 30mm	0,720	0,250	25	1,40	15	0,303
000-1038	Air Core Coil 0,720mH +/-3% 3,000Ω wire 0,30mm=29AWG OD-17 / 8mm	0,720	3,000	9	0,30	29	0,008
000-1286	Air Core Coil 0,740mH +/-3% 0,420Ω wire 1,00mm=18AWG OD-48 / 15mm	0,740	0,420	25	1,00	18	0,131
000-1296	Air Core Coil 0,740mH +/-3% 0,940Ω wire 0,63mm=22AWG OD-35 / 15mm	0,740	0,940	25	0,63	22	0,048
000-0061	Air Core Coil 0,750mH +/-3% 0,205Ω wire 1,60mm=14AWG OD-58 / 30mm	0,750	0,205	25	1,60	14	0,415
000-1075	Air Core Coil 0,750mH +/-3% 0,420Ω wire 1,00mm=18AWG OD-48 / 15mm	0,750	0,420	25	1,00	18	0,131
000-1079	Air Core Coil 0,750mH +/-3% 0,470Ω wire 1,00mm=18AWG OD-40 / 30mm	0,750	0,470	25	1,00	18	0,145
000-1105	Air Core Coil 0,750mH +/-3% 1,280Ω wire 0,50mm=24AWG OD-30 / 8mm	0,750	1,250	15	0,50	24	0,026
000-1160	Air Core Coil 0,750mH +/-3% 1,810Ω wire 0,40mm=26AWG OD-25 / 8mm	0,750	1,810	15	0,40	26	0,015
000-1224	Air Core Coil 0,750mH +/-3% 0,350Ω wire 1,20mm=17AWG OD-45 / 30mm	0,750	0,350	25	1,20	17	0,215
000-1356	Air Core Coil 0,750mH +/-3% 0,740Ω wire 0,70mm=21AWG OD-32 / 15mm	0,750	0,740	15	0,70	21	0,058
000-1856	Air Core Coil 0,750mH +/-3% 0,590Ω wire 0,80mm=20AWG OD-36 / 15mm	0,750	0,590	15	0,80	20	0,081
000-1857	Air Core Coil 0,750mH +/-3% 0,260Ω wire 1,40mm=15AWG OD-51 / 30mm	0,750	0,260	25	1,40	15	0,305
000-0848	Air Core Coil 0,760mH +/-3% 0,17Ω wire 1,80mm=13AWG OD-65 / 30mm	0,760	0,170	25	1,80	13	0,547
000-1396	Air Core Coil 0,760mH +/-3% 3,860Ω wire 0,30mm=29AWG OD-20 / 15mm	0,760	3,860	15	0,30	29	0,010
000-1568	Air Core Coil 0,760mH +/-3% 0,31Ω wire 1,20mm=17AWG OD-50 / 20mm	0,760	0,310	20	1,20	17	0,211
000-1736	Air Core Coil 0,760mH +/-3% 1,830Ω wire 0,40mm=26AWG OD-25 / 8mm	0,760	1,830	15	0,40	26	0,016
000-0056	Air Core Coil 0,770mH +/-3% 0,21Ω wire 1,60mm=14AWG OD-58 / 30mm	0,770	0,210	25	1,60	14	0,420
000-0955	Air Core Coil 0,770mH +/-3% 0,264Ω wire 1,40mm=15AWG OD-51 / 30mm	0,770	0,264	25	1,40	15	0,310
000-0958	Air Core Coil 0,770mH +/-3% 0,620Ω wire 0,80mm=20AWG OD-36 / 15mm	0,770	0,620	15	0,80	20	0,082
000-0205	Air Core Coil 0,780mH +/-3% 0,533Ω wire 1,00mm=18AWG OD-30 / 40mm	0,780	0,533	10	1,00	18	0,165
000-0902	Air Core Coil 0,780mH +/-3% 0,425Ω wire 1,00mm=18AWG OD-50 / 15mm	0,780	0,425	25	1,00	18	0,134
000-0910	Air Core Coil 0,780mH +/-3% 0,750Ω wire 0,70mm=21AWG OD-33 / 15mm	0,780	0,750	15	0,70	21	0,060
000-0953	Air Core Coil 0,780mH +/-3% 0,27Ω wire 1,40mm=15AWG OD-51 / 30mm	0,780	0,267	25	1,40	15	0,315
000-1734	Air Core Coil 0,780mH +/-1% 1,86Ω wire 0,40mm=26AWG OD-25 / 8mm	0,780	1,860	15	0,40	26	0,016
000-1696	Air Core Coil 0,790mH +/-3% 0,750Ω wire 0,70mm=21AWG OD-33 / 15mm	0,790	0,750	15	0,70	21	0,061
000-0948	Air Core Coil 0,794mH +/-1% 1,860Ω wire 0,40mm=26AWG OD-25 / 8mm	0,794	1,860	15	0,40	26	0,016
000-0044	Air Core Coil 0,800mH +/-3% 0,209Ω wire 1,60mm=14AWG OD-58 / 30mm	0,800	0,209	25	1,60	14	0,426
000-0098	Air Core Coil 0,800mH +/-3% 0,170Ω wire 1,80mm=13AWG OD-65 / 30mm	0,800	0,170	25	1,80	13	0,564
000-0844	Air Core Coil 0,800mH +/-3% 0,87Ω wire 0,70mm=21AWG OD-25 / 25mm	0,800	0,870	8	0,70	21	0,069
000-1012	Air Core Coil 0,800mH +/-3% 0,360Ω wire 1,20mm=17AWG OD-45 / 30mm	0,800	0,360	25	1,20	17	0,225
000-1169	Air Core Coil 0,800mH +/-3% 0,750Ω wire 0,70mm=21AWG OD-33 / 15mm	0,800	0,750	15	0,70	21	0,061
000-1244	Air Core Coil 0,800mH +/-3% 0,270Ω wire 1,40mm=15AWG OD-52 / 30mm	0,800	0,270	25	1,40	15	0,319
000-1285	Air Core Coil 0,800mH +/-3% 0,430Ω wire 1,00mm=18AWG OD-50 / 15mm	0,800	0,430	25	1,00	18	0,137
000-1368	Air Core Coil 0,800mH +/-3% 0,900Ω wire 0,70mm=21AWG OD-33 / 30mm	0,800	0,900	25	0,70	21	0,068
000-1394	Air Core Coil 0,800mH +/-3% 0,620Ω wire 0,80mm=20AWG OD-36 / 15mm	0,800	0,620	15	0,80	20	0,083
000-1567	Air Core Coil 0,800mH +/-3% 0,32Ω wire 1,20mm=17AWG OD-50 / 20mm	0,800	0,320	20	1,20	17	0,217
000-1691	Air Core Coil 0,800mH +/-3% 1,400Ω wire 0,50mm=24AWG OD-25 / 15mm	0,800	1,400	15	0,50	24	0,030
000-1744	Air Core Coil 0,800mH +/-3% 1,890Ω wire 0,40mm=26AWG OD-25 / 8mm	0,800	1,890	15	0,40	26	0,017
000-1992	Air Core Coil 0,800mH +/-3% 0,470Ω wire 1,00mm=18AWG OD-35 / 25mm	0,800	0,470	8	1,00	18	0,152
000-0014	Air Core Coil 0,820mH +/-3% 0,215Ω wire 1,60mm=14AWG OD-58 / 30mm	0,820	0,215	25	1,60	14	0,441
000-0114	Air Core Coil 0,820mH +/-3% 0,180Ω wire 1,80mm=13AWG OD-65 / 30mm	0,820	0,180	25	1,80	13	0,571
000-0156	Air Core Coil 0,820mH +/-3% 0,97Ω wire 0,63mm=22AWG OD-36 / 15mm	0,820	0,970	25	0,63	22	0,049



Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-0203	Air Core Coil 0,820mH +/-3% 0,56Ω wire 1,00mm=18AWG OD-32 / 40mm	0,820	0,560	10	1,00	18	0,173
000-0994	Air Core Coil 0,820mH +/-3% 0,330Ω wire 1,20mm=17AWG OD-58 / 15mm	0,820	0,330	25	1,20	17	0,211
000-1288	Air Core Coil 0,820mH +/-3% 0,480Ω wire 1,00mm=18AWG OD-40 / 30mm	0,820	0,480	25	1,00	18	0,151
000-1676	Air Core Coil 0,820mH +/-3% 0,439Ω wire 1,00mm=18AWG OD-50 / 15mm	0,820	0,439	25	1,00	18	0,138
000-1787	Air Core Coil 0,820mH +/-3% 3,900Ω wire 0,30mm=29AWG OD-20 / 15mm	0,820	3,900	15	0,30	29	0,010
000-1858	Air Core Coil 0,820mH +/-3% 1,350Ω wire 0,50mm=24AWG OD-31 / 8mm	0,820	1,350	15	0,50	24	0,027
000-1859	Air Core Coil 0,820mH +/-3% 0,630Ω wire 0,80mm=20AWG OD-36 / 15mm	0,820	0,630	15	0,80	20	0,083
000-1860	Air Core Coil 0,820mH +/-3% 0,760Ω wire 0,70mm=21AWG OD-33 / 15mm	0,820	0,760	15	0,70	21	0,064
000-1882	Air Core Coil 0,820mH +/-3% 0,365Ω wire 1,20mm=17AWG OD-45 / 30mm	0,820	0,365	25	1,20	17	0,230
000-1897	Air Core Coil 0,820mH +/-3% 0,270Ω wire 1,40mm=15AWG OD-52 / 130mm	0,820	0,270	25	1,40	15	0,319
000-1973	Air Core Coil 0,820mH +/-3% 0,440Ω wire 1,00mm=18AWG OD-46 / 15mm	0,820	0,440	15	1,00	18	0,141
000-1993	Air Core Coil 0,820mH +/-3% 0,480Ω wire 1,00mm=18AWG OD-36 / 25mm	0,820	0,480	8	1,00	18	0,155
000-1565	Air Core Coil 0,830mH +/-3% 0,270Ω wire 1,40mm=15AWG OD-52 / 30mm	0,830	0,270	25	1,40	15	0,320
000-0972	Air Core Coil 0,840mH +/-3% 0,45Ω wire 1,00mm=18AWG OD-46 / 15mm	0,840	0,450	15	1,00	18	0,144
000-0015	Air Core Coil 0,850mH +/-3% 0,220Ω wire 1,60mm=14AWG OD-58 / 30mm	0,850	0,220	25	1,60	14	0,446
000-0115	Air Core Coil 0,850mH +/-3% 0,180Ω wire 1,80mm=13AWG OD-65 / 30mm	0,850	0,180	25	1,80	13	0,590
000-0930	Air Core Coil 0,850mH +/-3% 0,448Ω wire 1,00mm=18AWG OD-43 / 20mm	0,850	0,448	20	1,00	18	0,144
000-1064	Air Core Coil 0,850mH +/-3% 1,930Ω wire 0,40mm=26AWG OD-25 / 8mm	0,850	1,930	15	0,40	26	0,017
000-1128	Air Core Coil 0,850mH +/-3% 0,640Ω wire 0,80mm=20AWG OD-37 / 15mm	0,850	0,640	15	0,80	20	0,085
000-1284	Air Core Coil 0,850mH +/-3% 0,440Ω wire 1,00mm=18AWG OD-50 / 15mm	0,850	0,440	25	1,00	18	0,144
000-1430	Air Core Coil 0,850mH +/-3% 0,450Ω wire 1,00mm=18AWG OD-48 / 15mm	0,850	0,450	15	1,00	18	0,144
000-1445	Air Core Coil 0,850mH +/-3% 0,280Ω wire 1,40mm=15AWG OD-52 / 30mm	0,850	0,280	25	1,40	15	0,323
000-1784	Air Core Coil 0,850mH +/-3% 0,370Ω wire 1,20mm=17AWG OD-45 / 30mm	0,850	0,370	25	1,20	17	0,233
000-1861	Air Core Coil 0,850mH +/-3% 0,500Ω wire 1,00mm=18AWG OD-40 / 30mm	0,850	0,500	25	1,00	18	0,153
000-1669	Air Core Coil 0,860mH +/-3% 0,800Ω wire 0,70mm=21AWG OD-33 / 15mm	0,860	0,800	15	0,70	21	0,063
000-0170	Air Core Coil 0,870mH +/-3% 0,22Ω wire 1,60mm=14AWG OD-58 / 30mm	0,870	0,220	25	1,60	14	0,450
000-1158	Air Core Coil 0,870mH +/-3% 1,950Ω wire 0,40mm=26AWG OD-26 / 8mm	0,870	1,950	15	0,40	26	0,017
000-1295	Air Core Coil 0,870mH +/-3% 1,010Ω wire 0,63mm=22AWG OD-36 / 15mm	0,870	1,010	25	0,63	22	0,051
000-1438	Air Core Coil 0,870mH +/-3% 3,460Ω wire 0,30mm=29AWG OD-18 / 8mm	0,870	3,460	9	0,30	29	0,009
000-1443	Air Core Coil 0,870mH +/-3% 0,800Ω wire 0,70mm=21AWG OD-33 / 15mm	0,870	0,800	15	0,70	21	0,064
000-1918	Air Core Coil 0,870mH +/-3% 0,380Ω wire 1,20mm=17AWG OD-45 / 30mm	0,870	0,380	25	1,20	17	0,236
000-0818	Air Core Coil 0,875mH +/-3% 0,460Ω wire 1,00mm=18AWG OD-48 / 15mm	0,875	0,460	15	1,00	18	0,146
000-0845	Air Core Coil 0,880mH +/-3% 0,38Ω wire 1,20mm=17AWG OD-45 / 30mm	0,880	0,380	25	1,20	17	0,238
000-1429	Air Core Coil 0,880mH +/-3% 0,470Ω wire 1,00mm=18AWG OD-48 / 15mm	0,880	0,470	15	1,00	18	0,146
000-1437	Air Core Coil 0,880mH +/-3% 0,940Ω wire 0,70mm=21AWG OD-34 / 30mm	0,880	0,940	25	0,70	21	0,075
000-1052	Air Core Coil 0,890mH +/-3% 0,670Ω wire 0,80mm=20AWG OD-38 / 15mm	0,890	0,670	15	0,80	20	0,088
000-1408	Air Core Coil 0,890mH +/-3% 0,800Ω wire 0,70mm=21AWG OD-33 / 15mm	0,890	0,800	15	0,70	21	0,064
000-0016	Air Core Coil 0,900mH +/-3% 0,228Ω wire 1,60mm=14AWG OD-58 / 30mm	0,900	0,228	25	1,60	14	0,462
000-0116	Air Core Coil 0,900mH +/-3% 0,185Ω wire 1,80mm=13AWG OD-65 / 30mm	0,900	0,185	25	1,80	13	0,620
000-0239	Air Core Coil 0,900mH +/-3% 2,23Ω wire 0,40mm=26AWG OD-25 / 10mm	0,900	2,230	18	0,40	26	0,017
000-0824	Air Core Coil 0,900mH +/-3% 1,49Ω wire 0,50mm=24AWG OD-26 / 15mm	0,900	1,490	15	0,50	24	0,031
000-0825	Air Core Coil 0,900mH +/-3% 3,74Ω wire 0,30mm=29AWG OD-19 / 15mm	0,900	3,740	15	0,30	29	0,011
000-1001	Air Core Coil 0,900mH +/-3% 0,950Ω wire 0,70mm=21AWG OD-35 / 30mm	0,900	0,950	25	0,70	21	0,076
000-1413	Air Core Coil 0,900mH +/-3% 0,390Ω wire 1,20mm=17AWG OD-45 / 30mm	0,900	0,390	25	1,20	17	0,240
000-1448	Air Core Coil 0,900mH +/-3% 0,810Ω wire 0,70mm=21AWG OD-34 / 15mm	0,900	0,810	15	0,70	21	0,065
000-1526	Air Core Coil 0,900mH +/-3% 0,670Ω wire 0,80mm=20AWG OD-38 / 15mm	0,900	0,670	15	0,80	20	0,090
000-1566	Air Core Coil 0,900mH +/-3% 0,35Ω wire 1,20mm=17AWG OD-52 / 20mm	0,900	0,350	20	1,20	17	0,234
000-1647	Air Core Coil 0,900mH +/-3% 0,530Ω wire 1,00mm=18AWG OD-42 / 30mm	0,900	0,530	25	1,00	18	0,159
000-1657	Air Core Coil 0,900mH +/-3% 0,290Ω wire 1,40mm=15AWG OD-54 / 30mm	0,900	0,290	25	1,40	15	0,337
000-1878	Air Core Coil 0,900mH +/-3% 2,090Ω wire 0,40mm=26AWG OD-26 / 8mm	0,900	2,090	15	0,40	26	0,018
000-1953	Air Core Coil 0,900mH +/-3% 0,460Ω wire 1,00mm=18AWG OD-52 / 15mm	0,900	0,460	25	1,00	18	0,147
000-1969	Air Core Coil 0,900mH +/-3% 0,470Ω wire 1,00mm=18AWG OD-48 / 15mm	0,900	0,470	15	1,00	18	0,148
000-1862	Air Core Coil 0,910mH +/-3% 0,290Ω wire 1,40mm=15AWG OD-54 / 30mm	0,910	0,290	25	1,40	15	0,339
000-0837	Air Core Coil 0,920mH +/-3% 0,68Ω wire 0,80mm=20AWG OD-38 / 15mm	0,920	0,680	15	0,80	20	0,090
000-0846	Air Core Coil 0,920mH +/-3% 0,39Ω wire 1,20mm=17AWG OD-48 / 30mm	0,920	0,390	25	1,20	17	0,242
000-1081	Air Core Coil 0,930mH +/-3% 0,300Ω wire 1,40mm=15AWG OD-54 / 30mm	0,930	0,300	25	1,40	15	0,344
000-1369	Air Core Coil 0,930mH +/-3% 0,970Ω wire 0,70mm=21AWG OD-35 / 30mm	0,930	0,970	25	0,70	21	0,077
000-1235	Air Core Coil 0,940mH +/-3% 0,500Ω wire 1,00mm=18AWG OD-57 / 21mm	0,940	0,500	42	1,00	18	0,157
000-0017	Air Core Coil 0,950mH +/-3% 0,236Ω wire 1,60mm=14AWG OD-61 / 30mm	0,950	0,236	25	1,60	14	0,478
000-0117	Air Core Coil 0,950mH +/-3% 0,190Ω wire 1,80mm=13AWG OD-69 / 30mm	0,950	0,190	25	1,80	13	0,640
000-0944	Air Core Coil 0,950mH +/-3% 0,390Ω wire 1,20mm=17AWG OD-48 / 30mm	0,950	0,390	25	1,20	17	0,246
000-0962	Air Core Coil 0,950mH +/-3% 1,030Ω wire 0,63mm=22AWG OD-30 / 15mm	0,950	1,030	15	0,63	22	0,052
000-1077	Air Core Coil 0,950mH +/-3% 0,300Ω wire 1,40mm=15AWG OD-54 / 30mm	0,950	0,300	25	1,40	15	0,347
000-1134	Air Core Coil 0,950mH +/-3% 0,680Ω wire 0,80mm=20AWG OD-38 / 15mm	0,950	0,680	15	0,80	20	0,092
000-1399	Air Core Coil 0,950mH +/-3% 0,830Ω wire 0,70mm=21AWG OD-34 / 15mm	0,950	0,830	15	0,70	21	0,067
000-1954	Air Core Coil 0,950mH +/-3% 0,480Ω wire 1,00mm=18AWG OD-52 / 15mm	0,950	0,480	25	1,00	18	0,155
000-1970	Air Core Coil 0,950mH +/-3% 0,480Ω wire 1,00mm=18AWG OD-48 / 15mm	0,950	0,480	15	1,00	18	0,153
000-1337	Air Core Coil 0,960mH +/-3% 0,370Ω wire 1,20mm=17AWG OD-60 / 15mm	0,960	0,370	25	1,20	17	0,235
000-1374	Air Core Coil 0,960mH +/-3% 0,540Ω wire 1,00mm=18AWG OD-42 / 30mm	0,960	0,540	25	1,00	18	0,166
000-1436	Air Core Coil 0,960mH +/-3% 0,990Ω wire 0,70mm=21AWG OD-35 / 30mm	0,960	0,990	25	0,70	21	0,078
000-0018	Air Core Coil 1,000mH +/-3% 0,245Ω wire 1,60mm=14AWG OD-61 / 30mm	1,000	0,245	25	1,60	14	0,504
000-0118	Air Core Coil 1,000mH +/-3% 0,198Ω wire 1,80mm=13AWG OD-69 / 30mm	1,000	0,198	25	1,80	13	0,658
000-0826	Air Core Coil 1,000mH +/-3% 3,98Ω wire 0,30mm=29AWG OD-19 / 15mm	1,000	3,980	15	0,30	29	0,011
000-1056	Air Core Coil 1,000mH +/-3% 0,710Ω wire 0,80mm=20AWG OD-38 / 15mm	1,000	0,710	15	0,80	20	0,096
000-1057	Air Core Coil 1,000mH +/-3% 0,550Ω wire 1,00mm=18AWG OD-42 / 30mm	1,000	0,550	25	1,00	18	0,172
000-1089	Air Core Coil 1,000mH +/-3% 1,570Ω wire 0,50mm=24AWG OD-26 / 15mm	1,000	1,570	15	0,50	24	0,034
000-1094	Air Core Coil 1,000mH +/-3% 0,395Ω wire 1,20mm=17AWG OD-48 / 30mm	1,000	0,395	25	1,20	17	0,256
000-1096	Air Core Coil 1,000mH +/-3% 0,285Ω wire 1,40mm=15AWG OD-71 / 21mm	1,000	0,285	42	1,40	15	0,348
000-1231	Air Core Coil 1,000mH +/-3% 0,720Ω wire 0,80mm=20AWG OD-43 / 15mm	1,000	0,720	25	0,80	20	0,092
000-1239	Air Core Coil 1,000mH +/-3% 0,480Ω wire 1,00mm=18AWG OD-52 / 15mm	1,000	0,480	25	1,00	18	0,158
000-1370	Air Core Coil 1,000mH +/-3% 1,000Ω wire 0,70mm=21AWG OD-35 / 30mm	1,000	1,000	25	0,70	21	0,080
000-1395	Air Core Coil 1,000mH +/-3% 2,240Ω wire 0,40mm=26AWG OD-29 / 10mm	1,000	2,240	20	0,40	26	0,019
000-1409	Air Core Coil 1,000mH +/-3% 0,850Ω wire 0,70mm=21AWG OD-34 / 15mm	1,000	0,850	15	0,70	21	0,069
000-1440	Air Core Coil 1,000mH +/-3% 1,100Ω wire 0,63mm=22AWG OD-30 / 15mm	1,000	1,100	15	0,63	22	0,055
000-1563	Air Core Coil 1,000mH +/-3% 0,36Ω wire 1,20mm=17AWG OD-52 / 20mm	1,000	0,360	20	1,20	17	0,248
000-1786	Air Core Coil 1,000mH +/-3% 4,40Ω wire 0,30mm=29AWG OD-14 / 20mm	1,000	4,400	8	0,30	29	0,012
000-1898	Air Core Coil 1,000mH +/-3% 0,300Ω wire 1,40mm=15AWG OD-54 / 30mm	1,000	0,300	25	1,40	15	0,365
000-1972	Air Core Coil 1,000mH +/-3% 0,490Ω wire 1,00mm=18AWG OD-49 / 15mm	1,000	0,490	15	1,00	18	0,157
000-1994	Air Core Coil 1,000mH +/-3% 0,540Ω wire 1,00mm=18AWG OD-36 / 25mm	1,000	0,540	8	1,00	18	0,172
000-1047	Air Core Coil 1,040mH +/-3% 0,290Ω wire 1,40mm=15AWG OD-71 / 21mm	1,040	0,290	42	1,40	15	0,355
000-1135	Air Core Coil 1,050mH +/-3% 0,730Ω wire 0,80mm=20AWG OD-39 / 15mm	1,050	0,730	15	0,80	20	0,097
000-1782	Air Core Coil 1,050mH +/-3% 0,397Ω wire 1,20mm=17AWG OD-49 / 30mm	1,050	0,397	25	1,20	17	0,263
000-0058	Air Core Coil 1,060mH +/-3% 0,25Ω wire 1,60mm=14AWG OD-63 / 30mm	1,060	0,250	25	1,60	14	0,520
000-1701	Air Core Coil 1,060mH +/-3% 4,380Ω wire 0,30mm=29AWG OD-20 / 15mm	1,060	4,380	15	0,30	29	0,011
000-1776	Air Core Coil 1,060mH +/-3% 1,690Ω wire 0,50mm=24AWG OD-26 / 15mm	1,060	1,690	15	0,50	24	0,035

Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-0055	Air Core Coil 1,070mH +/-3% 0,251Ω wire 1,60mm=14AWG OD-63 / 30mm	1,070	0,251	25	1,60	14	0,520
000-0019	Air Core Coil 1,100mH +/-3% 0,258Ω wire 1,60mm=14AWG OD-63 / 30mm	1,100	0,258	25	1,60	14	0,523
000-0119	Air Core Coil 1,100mH +/-3% 0,208Ω wire 1,80mm=13AWG OD-69 / 30mm	1,100	0,208	25	1,80	13	0,680
000-0827	Air Core Coil 1,100mH +/-3% 4,15Ω wire 0,30mm=29AWG OD-20 / 15mm	1,100	4,150	15	0,30	29	0,011
000-1078	Air Core Coil 1,100mH +/-3% 0,570Ω wire 1,00mm=18AWG OD-43 / 30mm	1,100	0,570	25	1,00	18	0,176
000-1477	Air Core Coil 1,100mH +/-3% 0,920Ω wire 0,70mm=21AWG OD-35 / 15mm	1,100	0,920	15	0,70	21	0,072
000-1478	Air Core Coil 1,100mH +/-3% 0,760Ω wire 0,80mm=20AWG OD-39 / 15mm	1,100	0,760	15	0,80	20	0,097
000-1562	Air Core Coil 1,100mH +/-3% 0,39Ω wire 1,20mm=17AWG OD-55 / 20mm	1,100	0,390	20	1,20	17	0,264
000-1795	Air Core Coil 1,100mH +/-3% 1,55Ω wire 0,50mm=24AWG OD-30 / 8mm	1,100	1,550	9	0,50	24	0,033
000-1886	Air Core Coil 1,100mH +/-3% 1,700Ω wire 0,50mm=24AWG OD-26 / 15mm	1,100	1,700	15	0,50	24	0,035
000-1887	Air Core Coil 1,100mH +/-3% 1,150Ω wire 0,63mm=22AWG OD-30 / 15mm	1,100	1,150	15	0,63	22	0,056
000-1924	Air Core Coil 1,100mH +/-3% 0,420Ω wire 1,20mm=17AWG OD-49 / 30mm	1,100	0,420	25	1,20	17	0,268
000-1931	Air Core Coil 1,100mH +/-3% 0,310Ω wire 1,40mm=15AWG OD-72 / 14mm	1,100	0,310	42	1,40	15	0,360
000-1014	Air Core Coil 1,130mH +/-3% 4,400Ω wire 0,30mm=29AWG OD-20 / 15mm	1,130	4,400	15	0,30	29	0,011
000-1983	Air Core Coil 1,130mH +/-3% 0,430Ω wire 1,20mm=17AWG OD-50 / 30mm	1,130	0,430	25	1,20	17	0,272
000-1984	Air Core Coil 1,130mH +/-3% 0,320Ω wire 1,40mm=15AWG OD-56 / 30mm	1,130	0,320	25	1,40	15	0,380
000-1067	Air Core Coil 1,150mH +/-3% 2,390Ω wire 0,40mm=26AWG OD-29 / 10mm	1,150	2,390	20	0,40	26	0,021
000-1136	Air Core Coil 1,150mH +/-3% 0,760Ω wire 0,80mm=20AWG OD-40 / 15mm	1,150	0,760	15	0,80	20	0,102
000-1174	Air Core Coil 1,150mH +/-3% 0,445Ω wire 1,20mm=17AWG OD-50 / 30mm	1,150	0,445	25	1,20	17	0,276
000-1256	Air Core Coil 1,150mH +/-3% 0,322Ω wire 1,40mm=15AWG OD-56 / 30mm	1,150	0,322	25	1,40	15	0,385
000-1625	Air Core Coil 1,150mH +/-3% 0,590Ω wire 1,00mm=18AWG OD-43 / 30mm	1,150	0,590	25	1,00	18	0,183
000-1797	Air Core Coil 1,150mH +/-3% 0,32Ω wire 1,40mm=15AWG OD-60 / 25mm	1,150	0,320	25	1,40	15	0,389
000-0237	Air Core Coil 1,170mH +/-3% 1,70Ω wire 0,50mm=24AWG OD-30 / 8mm	1,170	1,700	9	0,50	24	0,035
000-0020	Air Core Coil 1,200mH +/-3% 0,270Ω wire 1,60mm=14AWG OD-63 / 30mm	1,200	0,270	25	1,60	14	0,552
000-0120	Air Core Coil 1,200mH +/-3% 0,220Ω wire 1,80mm=13AWG OD-71 / 18mm	1,200	0,220	25	1,80	13	0,720
000-0853	Air Core Coil 1,200mH +/-3% 1,18Ω wire 0,63mm=22AWG OD-32 / 15mm	1,200	1,180	15	0,63	22	0,058
000-0896	Air Core Coil 1,200mH +/-3% 0,340Ω wire 1,40mm=15AWG OD-51 / 33mm	1,200	0,340	17	1,40	15	0,424
000-0984	Air Core Coil 1,200mH +/-3% 0,28Ω wire 1,60mm=14AWG OD-66 / 25mm	1,200	0,280	8	1,60	14	0,568
000-1133	Air Core Coil 1,200mH +/-3% 1,760Ω wire 0,50mm=24AWG OD-27 / 15mm	1,200	1,760	15	0,50	24	0,037
000-1280	Air Core Coil 1,200mH +/-3% 0,555Ω wire 1,00mm=18AWG OD-53 / 15mm	1,200	0,555	25	1,00	18	0,176
000-1301	Air Core Coil 1,200mH +/-3% 0,460Ω wire 1,20mm=17AWG OD-50 / 30mm	1,200	0,460	25	1,20	17	0,283
000-1336	Air Core Coil 1,200mH +/-3% 0,330Ω wire 1,40mm=15AWG OD-73 / 21mm	1,200	0,330	42	1,40	15	0,386
000-1467	Air Core Coil 1,200mH +/-3% 0,550Ω wire 1,00mm=18AWG OD-48 / 20mm	1,200	0,550	20	1,00	18	0,173
000-1527	Air Core Coil 1,200mH +/-3% 0,41Ω wire 1,20mm=17AWG OD-57 / 20mm	1,200	0,410	20	1,20	17	0,278
000-1767	Air Core Coil 1,200mH +/-3% 4,660Ω wire 0,30mm=29AWG OD-20 / 15mm	1,200	4,660	15	0,30	29	0,013
000-1863	Air Core Coil 1,200mH +/-3% 0,950Ω wire 0,70mm=21AWG OD-36 / 15mm	1,200	0,950	15	0,70	21	0,077
000-1864	Air Core Coil 1,200mH +/-3% 0,800Ω wire 0,80mm=20AWG OD-41 / 15mm	1,200	0,800	15	0,80	20	0,106
000-1899	Air Core Coil 1,200mH +/-3% 0,330Ω wire 1,40mm=15AWG OD-57 / 30mm	1,200	0,330	25	1,40	15	0,396
000-1901	Air Core Coil 1,200mH +/-3% 0,600Ω wire 1,00mm=18AWG OD-44 / 30mm	1,200	0,600	25	1,00	18	0,184
000-1995	Air Core Coil 1,200mH +/-3% 0,590Ω wire 1,00mm=18AWG OD-36 / 25mm	1,200	0,590	8	1,00	18	0,196
000-0149	Air Core Coil 1,250mH +/-3% 0,42Ω wire 1,20mm=17AWG OD-51 / 30mm	1,250	0,420	25	1,20	17	0,290
000-0974	Air Core Coil 1,250mH +/-3% 1,21Ω wire 0,63mm=22AWG OD-32 / 15mm	1,250	1,210	15	0,63	22	0,062
000-1137	Air Core Coil 1,250mH +/-3% 0,800Ω wire 0,80mm=20AWG OD-41 / 15mm	1,250	0,800	15	0,80	20	0,106
000-1626	Air Core Coil 1,250mH +/-3% 0,610Ω wire 1,00mm=18AWG OD-44 / 30mm	1,250	0,610	25	1,00	18	0,190
000-1656	Air Core Coil 1,250mH +/-3% 0,340Ω wire 1,40mm=15AWG OD-59 / 30mm	1,250	0,340	25	1,40	15	0,407
000-1799	Air Core Coil 1,260mH +/-3% 1,00Ω wire 0,70mm=21AWG OD-36 / 15mm	1,260	1,010	15	0,70	21	0,079
000-1108	Air Core Coil 1,280mH +/-3% 2,670Ω wire 0,40mm=26AWG OD-23 / 15mm	1,280	2,670	15	0,40	26	0,023
000-1376	Air Core Coil 1,280mH +/-3% 0,470Ω wire 1,20mm=17AWG OD-50 / 30mm	1,280	0,470	25	1,20	17	0,300
000-0021	Air Core Coil 1,300mH +/-3% 0,283Ω wire 1,60mm=14AWG OD-63 / 30mm	1,300	0,283	25	1,60	14	0,575
000-0121	Air Core Coil 1,300mH +/-3% 0,230Ω wire 1,80mm=13AWG OD-71 / 30mm	1,300	0,230	25	1,80	13	0,766
000-0886	Air Core Coil 1,300mH +/-3% 0,340Ω wire 1,40mm=15AWG OD-65 / 20mm	1,300	0,340	25	1,40	15	0,405
000-1048	Air Core Coil 1,300mH +/-3% 0,610Ω wire 1,00mm=18AWG OD-44 / 30mm	1,300	0,610	25	1,00	18	0,197
000-1058	Air Core Coil 1,300mH +/-3% 1,780Ω wire 0,50mm=24AWG OD-34 / 8mm	1,300	1,780	15	0,50	24	0,037
000-1083	Air Core Coil 1,300mH +/-3% 0,458Ω wire 1,20mm=17AWG OD-56 / 20mm	1,300	0,458	25	1,20	17	0,282
000-1138	Air Core Coil 1,300mH +/-3% 0,820Ω wire 0,80mm=20AWG OD-42 / 15mm	1,300	0,820	15	0,80	20	0,111
000-1293	Air Core Coil 1,300mH +/-3% 1,010Ω wire 0,70mm=21AWG OD-36 / 15mm	1,300	1,010	15	0,70	21	0,081
000-1371	Air Core Coil 1,300mH +/-3% 1,170Ω wire 0,70mm=21AWG OD-36 / 30mm	1,300	1,170	25	0,70	21	0,091
000-1434	Air Core Coil 1,300mH +/-3% 0,43Ω wire 1,20mm=17AWG OD-57 / 20mm	1,300	0,430	20	1,20	17	0,290
000-1540	Air Core Coil 1,300mH +/-3% 0,356Ω wire 1,40mm=15AWG OD-59 / 30mm	1,300	0,356	25	1,40	15	0,417
000-1710	Air Core Coil 1,300mH +/-3% 4,90Ω wire 0,30mm=29AWG OD-20 / 15mm	1,300	4,900	15	0,30	29	0,013
000-1945	Air Core Coil 1,300mH +/-3% 0,470Ω wire 1,20mm=17AWG OD-50 / 30mm	1,300	0,470	25	1,20	17	0,300
000-1658	Air Core Coil 1,330mH +/-3% 0,358Ω wire 1,40mm=15AWG OD-59 / 30mm	1,330	0,358	25	1,40	15	0,425
000-1660	Air Core Coil 1,330mH +/-3% 0,335Ω wire 1,40mm=15AWG OD-67 / 22mm	1,330	0,335	25	1,40	15	0,404
000-1029	Air Core Coil 1,340mH +/-3% 5,100Ω wire 0,30mm=29AWG OD-20 / 15mm	1,340	5,100	15	0,30	29	0,013
000-1455	Air Core Coil 1,340mH +/-3% 1,900Ω wire 0,50mm=24AWG OD-27 / 15mm	1,340	1,900	15	0,50	24	0,039
000-0838	Air Core Coil 1,350mH +/-3% 1,92Ω wire 0,50mm=24AWG OD-34 / 15mm	1,350	1,920	25	0,50	24	0,040
000-1142	Air Core Coil 1,350mH +/-3% 0,350Ω wire 1,40mm=15AWG OD-75 / 21mm	1,350	0,350	42	1,40	15	0,405
000-1150	Air Core Coil 1,350mH +/-3% 0,850Ω wire 0,80mm=20AWG OD-42 / 15mm	1,350	0,850	15	0,80	20	0,111
000-1375	Air Core Coil 1,350mH +/-3% 0,630Ω wire 1,00mm=18AWG OD-44 / 30mm	1,350	0,630	25	1,00	18	0,202
000-1457	Air Core Coil 1,350mH +/-3% 0,490Ω wire 1,20mm=17AWG OD-50 / 30mm	1,350	0,490	25	1,20	17	0,307
000-0022	Air Core Coil 1,400mH +/-3% 0,294Ω wire 1,60mm=14AWG OD-66 / 30mm	1,400	0,294	25	1,60	14	0,608
000-0122	Air Core Coil 1,400mH +/-3% 0,238Ω wire 1,80mm=13AWG OD-75 / 30mm	1,400	0,238	25	1,80	13	0,793
000-1006	Air Core Coil 1,400mH +/-3% 0,500Ω wire 1,20mm=17AWG OD-50 / 30mm	1,400	0,500	25	1,20	17	0,309
000-1183	Air Core Coil 1,400mH +/-3% 0,44Ω wire 1,20mm=17AWG OD-59 / 20mm	1,400	0,440	20	1,20	17	0,305
000-1330	Air Core Coil 1,400mH +/-3% 1,100Ω wire 0,70mm=21AWG OD-37 / 15mm	1,400	1,100	15	0,70	21	0,084
000-1461	Air Core Coil 1,400mH +/-3% 1,310Ω wire 0,63mm=22AWG OD-33 / 15mm	1,400	1,310	15	0,63	22	0,065
000-1470	Air Core Coil 1,400mH +/-3% 0,370Ω wire 1,40mm=15AWG OD-59 / 30mm	1,400	0,370	25	1,40	15	0,437
000-1524	Air Core Coil 1,400mH +/-3% 0,860Ω wire 0,80mm=20AWG OD-42 / 15mm	1,400	0,860	15	0,80	20	0,112
000-1702	Air Core Coil 1,400mH +/-3% 5,200Ω wire 0,30mm=29AWG OD-20 / 15mm	1,400	5,200	15	0,30	29	0,013
000-1775	Air Core Coil 1,400mH +/-3% 1,920Ω wire 0,50mm=24AWG OD-27 / 15mm	1,400	1,920	15	0,50	24	0,040
000-1955	Air Core Coil 1,400mH +/-3% 0,650Ω wire 1,00mm=18AWG OD-44 / 30mm	1,400	0,650	25	1,00	18	0,207
000-0169	Air Core Coil 1,420mH +/-3% 0,30Ω wire 1,60mm=14AWG OD-66 / 30mm	1,420	0,300	25	1,60	14	0,610
000-1441	Air Core Coil 1,430mH +/-3% 1,080Ω wire 0,70mm=21AWG OD-38 / 15mm	1,430	1,080	15	0,70	21	0,086
000-1140	Air Core Coil 1,450mH +/-3% 0,470Ω wire 1,20mm=17AWG OD-66 / 21mm	1,450	0,470	42	1,20	17	0,300
000-1151	Air Core Coil 1,450mH +/-3% 0,870Ω wire 0,80mm=20AWG OD-42 / 15mm	1,450	0,870	15	0,80	20	0,116
000-1249	Air Core Coil 1,450mH +/-3% 0,510Ω wire 1,20mm=17AWG OD-51 / 30mm	1,450	0,510	25	1,20	17	0,313
000-1341	Air Core Coil 1,450mH +/-3% 0,370Ω wire 1,40mm=15AWG OD-75 / 21mm	1,450	0,370	42	1,40	15	0,416
000-1649	Air Core Coil 1,450mH +/-3% 0,670Ω wire 1,00mm=18AWG OD-44 / 30mm	1,450	0,650	25	1,00	18	0,210
000-0023	Air Core Coil 1,500mH +/-3% 0,305Ω wire 1,60mm=14AWG OD-66 / 30mm	1,500	0,305	25	1,60	14	0,628
000-0123	Air Core Coil 1,500mH +/-3% 0,245Ω wire 1,80mm=13AWG OD-75 / 30mm	1,500	0,245	25	1,80	13	0,810
000-1060	Air Core Coil 1,500mH +/-3% 1,000Ω wire 0,80mm=20AWG OD-39 / 30mm	1,500	1,000	25	0,80	20	0,130
000-1087	Air Core Coil 1,500mH +/-3% 0,670Ω wire 1,00mm=18AWG OD-45 / 30mm	1,500	0,670	25	1,00	18	0,212
000-1095	Air Core Coil 1,500mH +/-3% 0,370Ω wire 1,40mm=15AWG OD-75 / 21mm	1,500	0,370	42	1,40	15	0,438
000-1103	Air Core Coil 1,500mH +/-3% 0,900Ω wire 0,80mm=20AWG OD-43 / 15mm	1,500	0,900	15	0,80	20	0,119
000-1182	Air Core Coil 1,500mH +/-3% 0,47Ω wire 1,20mm=17AWG OD-59 / 20mm	1,500	0,470	20	1,20	17	0,318

Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-1212	Air Core Coil 1,500mH +/-3% 5,280Ω wire 0,30mm=29AWG OD-21 / 15mm	1,500	5,280	15	0,30	29	0,014
000-1283	Air Core Coil 1,500mH +/-3% 0,640Ω wire 1,00mm=18AWG OD-57 / 15mm	1,500	0,640	25	1,00	18	0,199
000-1300	Air Core Coil 1,500mH +/-3% 0,520Ω wire 1,20mm=17AWG OD-52 / 30mm	1,500	0,520	25	1,20	17	0,320
000-1469	Air Core Coil 1,500mH +/-3% 0,380Ω wire 1,40mm=15AWG OD-59 / 30mm	1,500	0,380	25	1,40	15	0,451
000-1865	Air Core Coil 1,500mH +/-3% 1,100Ω wire 0,70mm=21AWG OD-38 / 15mm	1,500	1,100	15	0,70	21	0,088
000-1866	Air Core Coil 1,500mH +/-3% 1,980Ω wire 0,50mm=24AWG OD-28 / 15mm	1,500	1,980	15	0,50	24	0,041
000-1867	Air Core Coil 1,500mH +/-3% 2,830Ω wire 0,40mm=26AWG OD-28 / 8mm	1,500	2,830	15	0,40	26	0,023
000-1888	Air Core Coil 1,500mH +/-3% 1,350Ω wire 0,63mm=22AWG OD-33 / 15mm	1,500	1,350	15	0,63	22	0,069
000-1999	Air Core Coil 1,500mH +/-3% 0,650Ω wire 1,00mm=18AWG OD-40 / 25mm	1,500	0,650	8	1,00	18	0,216
000-0942	Air Core Coil 1,520mH +/-3% 0,390Ω wire 1,40mm=15AWG OD-59 / 30mm	1,520	0,390	25	1,40	15	0,458
000-1670	Air Core Coil 1,520mH +/-3% 1,100Ω wire 0,70mm=21AWG OD-38 / 15mm	1,520	1,100	15	0,70	21	0,089
000-1739	Air Core Coil 1,540mH +/-3% 2,850Ω wire 0,40mm=26AWG OD-29 / 8mm	1,540	2,850	15	0,40	26	0,024
000-0976	Air Core Coil 1,570mH +/-3% 0,70Ω wire 1,00mm=18AWG OD-30 / 32mm	1,570	0,700	17	1,00	18	0,228
000-0024	Air Core Coil 1,600mH +/-3% 0,320Ω wire 1,60mm=14AWG OD-66 / 30mm	1,600	0,320	25	1,60	14	0,650
000-0124	Air Core Coil 1,600mH +/-3% 0,255Ω wire 1,80mm=13AWG OD-75 / 30mm	1,600	0,255	25	1,80	13	0,840
000-0146	Air Core Coil 1,600mH +/-3% 1,390Ω wire 0,63mm=22AWG OD-34 / 15mm	1,600	1,390	15	0,63	22	0,070
000-1156	Air Core Coil 1,600mH +/-3% 0,400Ω wire 1,40mm=15AWG OD-59 / 30mm	1,600	0,400	25	1,40	15	0,468
000-1180	Air Core Coil 1,600mH +/-3% 0,49Ω wire 1,20mm=17AWG OD-59 / 20mm	1,600	0,490	20	1,20	17	0,330
000-1253	Air Core Coil 1,600mH +/-3% 0,950Ω wire 0,80mm=20AWG OD-43 / 15mm	1,600	0,950	15	0,80	20	0,122
000-1306	Air Core Coil 1,600mH +/-3% 1,150Ω wire 0,70mm=21AWG OD-38 / 15mm	1,600	1,150	15	0,70	21	0,091
000-1425	Air Core Coil 1,600mH +/-3% 0,530Ω wire 1,20mm=17AWG OD-54 / 30mm	1,600	0,530	25	1,20	17	0,328
000-1703	Air Core Coil 1,600mH +/-3% 5,290Ω wire 0,30mm=29AWG OD-21 / 15mm	1,600	5,290	15	0,30	29	0,014
000-1943	Air Core Coil 1,600mH +/-3% 0,650Ω wire 1,00mm=18AWG OD-52 / 20mm	1,600	0,650	25	1,00	18	0,211
000-0842	Air Core Coil 1,620mH +/-3% 2,05Ω wire 0,50mm=24AWG OD-29 / 15mm	1,620	2,050	15	0,50	24	0,043
000-0957	Air Core Coil 1,640mH +/-3% 0,530Ω wire 1,20mm=17AWG OD-53 / 30mm	1,640	0,530	25	1,20	17	0,335
000-1005	Air Core Coil 1,640mH +/-3% 3,000Ω wire 0,40mm=26AWG OD-29 / 8mm	1,640	3,000	15	0,40	26	0,025
000-1176	Air Core Coil 1,640mH +/-3% 0,49Ω wire 1,20mm=17AWG OD-61 / 20mm	1,640	0,490	20	1,20	17	0,334
000-1788	Air Core Coil 1,650mH +/-3% 0,410Ω wire 1,40mm=15AWG OD-61 / 30mm	1,650	0,410	25	1,40	15	0,476
000-0025	Air Core Coil 1,700mH +/-3% 0,332Ω wire 1,60mm=14AWG OD-69 / 30mm	1,700	0,332	25	1,60	14	0,670
000-0125	Air Core Coil 1,700mH +/-3% 0,265Ω wire 1,80mm=13AWG OD-79 / 30mm	1,700	0,265	25	1,80	13	0,875
000-0223	Air Core Coil 1,700mH +/-3% 1,45Ω wire 0,63mm=22AWG OD-35 / 15mm	1,700	1,450	15	0,63	22	0,074
000-1175	Air Core Coil 1,700mH +/-3% 0,50Ω wire 1,20mm=17AWG OD-61 / 20mm	1,700	0,500	20	1,20	17	0,342
000-1252	Air Core Coil 1,700mH +/-3% 0,990Ω wire 0,80mm=20AWG OD-44 / 15mm	1,700	0,990	15	0,80	20	0,125
000-1309	Air Core Coil 1,700mH +/-3% 1,200Ω wire 0,70mm=21AWG OD-38 / 15mm	1,700	1,200	15	0,70	21	0,094
000-1339	Air Core Coil 1,700mH +/-3% 0,400Ω wire 1,40mm=15AWG OD-76 / 21mm	1,700	0,400	42	1,40	15	0,490
000-1465	Air Core Coil 1,700mH +/-3% 2,180Ω wire 0,50mm=24AWG OD-29 / 15mm	1,700	2,180	15	0,50	24	0,045
000-1487	Air Core Coil 1,700mH +/-3% 0,42Ω wire 1,40mm=15AWG OD-61 / 30mm	1,700	0,420	25	1,40	15	0,485
000-1516	Air Core Coil 1,700mH +/-3% 0,720Ω wire 1,00mm=18AWG OD-46 / 30mm	1,700	0,720	25	1,00	18	0,225
000-1789	Air Core Coil 1,700mH +/-3% 0,544Ω wire 1,20mm=17AWG OD-54 / 30mm	1,700	0,544	25	1,20	17	0,343
000-1521	Air Core Coil 1,720mH +/-3% 0,660Ω wire 1,00mm=18AWG OD-59 / 15mm	1,720	0,660	25	1,00	18	0,215
000-0157	Air Core Coil 1,750mH +/-3% 0,690Ω wire 1,00mm=18AWG OD-59 / 15mm	1,750	0,690	25	1,00	18	0,215
000-0235	Air Core Coil 1,750mH +/-3% 0,70Ω wire 1,00mm=18AWG OD-52 / 20mm	1,750	0,700	25	1,00	18	0,225
000-0819	Air Core Coil 1,750mH +/-3% 0,970Ω wire 0,80mm=20AWG OD-49 / 15mm	1,750	0,970	25	0,80	20	0,129
000-1424	Air Core Coil 1,750mH +/-3% 0,550Ω wire 1,20mm=17AWG OD-55 / 30mm	1,750	0,550	25	1,20	17	0,348
000-0026	Air Core Coil 1,800mH +/-3% 0,345Ω wire 1,60mm=14AWG OD-69 / 30mm	1,800	0,345	25	1,60	14	0,695
000-0126	Air Core Coil 1,800mH +/-3% 0,275Ω wire 1,80mm=13AWG OD-79 / 30mm	1,800	0,275	25	1,80	13	0,900
000-0218	Air Core Coil 1,800mH +/-3% 1,03Ω wire 0,80mm=20AWG OD-45 / 15mm	1,800	1,030	15	0,80	20	0,134
000-0891	Air Core Coil 1,800mH +/-3% 0,460Ω wire 1,40mm=15AWG OD-49 / 50mm	1,800	0,460	13	1,40	15	0,554
000-0935	Air Core Coil 1,800mH +/-3% 0,444Ω wire 1,40mm=15AWG OD-56 / 42mm	1,800	0,444	24	1,40	15	0,550
000-1111	Air Core Coil 1,800mH +/-3% 0,51Ω wire 1,20mm=17AWG OD-61 / 20mm	1,800	0,510	20	1,20	17	0,353
000-1131	Air Core Coil 1,800mH +/-3% 0,740Ω wire 1,00mm=18AWG OD-46 / 30mm	1,800	0,740	25	1,00	18	0,235
000-1132	Air Core Coil 1,800mH +/-3% 0,570Ω wire 1,20mm=17AWG OD-55 / 30mm	1,800	0,570	25	1,20	17	0,353
000-1250	Air Core Coil 1,800mH +/-3% 3,130Ω wire 0,40mm=26AWG OD-30 / 8mm	1,800	3,130	15	0,40	26	0,026
000-1290	Air Core Coil 1,800mH +/-3% 0,700Ω wire 1,00mm=18AWG OD-60 / 15mm	1,800	0,700	25	1,00	18	0,218
000-1411	Air Core Coil 1,800mH +/-3% 1,380Ω wire 0,70mm=21AWG OD-38 / 30mm	1,800	1,380	25	0,70	21	0,110
000-1466	Air Core Coil 1,800mH +/-3% 1,250Ω wire 0,70mm=21AWG OD-40 / 15mm	1,800	1,250	15	0,70	21	0,097
000-1480	Air Core Coil 1,800mH +/-3% 1,100Ω wire 0,80mm=20AWG OD-40 / 30mm	1,800	1,100	25	0,80	20	0,145
000-1484	Air Core Coil 1,800mH +/-3% 0,420Ω wire 1,40mm=15AWG OD-61 / 30mm	1,800	0,420	25	1,40	15	0,499
000-1868	Air Core Coil 1,800mH +/-3% 2,200Ω wire 0,50mm=24AWG OD-29 / 15mm	1,800	2,200	15	0,50	24	0,046
000-1893	Air Core Coil 1,800mH +/-3% 0,970Ω wire 0,80mm=20AWG OD-49 / 15mm	1,800	0,970	25	0,80	20	0,130
000-1942	Air Core Coil 1,800mH +/-3% 0,700Ω wire 1,00mm=18AWG OD-52 / 20mm	1,800	0,700	25	1,00	18	0,226
000-0159	Air Core Coil 1,820mH +/-3% 3,087Ω wire 0,40mm=26AWG OD-31 / 8mm	1,820	3,087	15	0,40	26	0,026
000-0141	Air Core Coil 1,850mH +/-3% 0,280Ω wire 1,80mm=13AWG OD-79 / 30mm	1,850	0,280	25	1,80	13	0,915
000-0160	Air Core Coil 1,850mH +/-3% 0,45Ω wire 1,40mm=15AWG OD-57 / 42mm	1,850	0,450	24	1,40	15	0,543
000-1774	Air Core Coil 1,860mH +/-3% 2,200Ω wire 0,50mm=24AWG OD-29 / 15mm	1,860	2,200	15	0,50	24	0,048
000-1377	Air Core Coil 1,870mH +/-3% 0,760Ω wire 1,00mm=18AWG OD-47 / 30mm	1,870	0,760	25	1,00	18	0,243
000-0127	Air Core Coil 1,900mH +/-3% 0,318Ω wire 1,80mm=13AWG OD-66 / 60mm	1,900	0,318	35	1,80	13	1,039
000-0864	Air Core Coil 1,900mH +/-3% 1,11Ω wire 0,80mm=20AWG OD-40 / 30mm	1,900	1,110	25	0,80	20	0,146
000-1159	Air Core Coil 1,900mH +/-3% 1,040Ω wire 0,80mm=20AWG OD-49 / 15mm	1,900	1,040	25	0,80	20	0,134
000-1215	Air Core Coil 1,900mH +/-3% 0,54Ω wire 1,20mm=17AWG OD-63 / 20mm	1,900	0,540	20	1,20	17	0,366
000-1311	Air Core Coil 1,900mH +/-3% 1,260Ω wire 0,70mm=21AWG OD-40 / 15mm	1,900	1,260	15	0,70	21	0,100
000-1733	Air Core Coil 1,900mH +/-3% 3,21Ω wire 0,40mm=26AWG OD-30 / 8mm	1,900	3,210	15	0,40	26	0,026
000-0162	Air Core Coil 1,940mH +/-3% 1,30Ω wire 0,70mm=21AWG OD-40 / 15mm	1,940	1,300	15	0,70	21	0,101
000-0027	Air Core Coil 2,000mH +/-3% 0,363Ω wire 1,60mm=14AWG OD-72 / 30mm	2,000	0,363	25	1,60	14	0,743
000-0128	Air Core Coil 2,000mH +/-3% 0,328Ω wire 1,80mm=13AWG OD-66 / 60mm	2,000	0,328	35	1,80	13	1,055
000-0852	Air Core Coil 2,000mH +/-3% 1,61Ω wire 0,63mm=22AWG OD-36 / 15mm	2,000	1,610	15	0,63	22	0,080
000-1062	Air Core Coil 2,000mH +/-3% 1,180Ω wire 0,80mm=20AWG OD-40 / 30mm	2,000	1,180	25	0,80	20	0,154
000-1063	Air Core Coil 2,000mH +/-3% 0,800Ω wire 1,00mm=18AWG OD-48 / 30mm	2,000	0,800	25	1,00	18	0,252
000-1097	Air Core Coil 2,000mH +/-3% 0,460Ω wire 1,40mm=15AWG OD-78 / 31mm	2,000	0,460	54	1,40	15	0,543
000-1166	Air Core Coil 2,000mH +/-3% 0,500Ω wire 1,40mm=15AWG OD-56 / 60mm	2,000	0,500	35	1,40	15	0,613
000-1216	Air Core Coil 2,000mH +/-3% 0,55Ω wire 1,20mm=17AWG OD-63 / 20mm	2,000	0,550	20	1,20	17	0,378
000-1245	Air Core Coil 2,000mH +/-3% 0,444Ω wire 1,40mm=15AWG OD-64 / 30mm	2,000	0,444	25	1,40	15	0,534
000-1254	Air Core Coil 2,000mH +/-3% 0,440Ω wire 1,40mm=15AWG OD-79 / 21mm	2,000	0,440	42	1,40	15	0,505
000-1260	Air Core Coil 2,000mH +/-3% 6,080Ω wire 0,30mm=29AWG OD-21 / 15mm	2,000	6,080	15	0,30	29	0,015
000-1482	Air Core Coil 2,000mH +/-3% 1,330Ω wire 0,70mm=21AWG OD-41 / 15mm	2,000	1,330	15	0,70	21	0,104
000-1711	Air Core Coil 2,000mH +/-3% 3,21Ω wire 0,40mm=26AWG OD-31 / 8mm	2,000	3,210	15	0,40	26	0,027
000-1778	Air Core Coil 2,000mH +/-3% 2,410Ω wire 0,50mm=24AWG OD-30 / 15mm	2,000	2,410	15	0,50	24	0,049
000-1946	Air Core Coil 2,000mH +/-3% 0,590Ω wire 1,20mm=17AWG OD-55 / 30mm	2,000	0,590	25	1,20	17	0,377
000-0129	Air Core Coil 2,100mH +/-3% 0,335Ω wire 1,80mm=13AWG OD-66 / 60mm	2,100	0,335	35	1,80	13	1,100
000-0875	Air Core Coil 2,100mH +/-3% 2,510Ω wire 0,50mm=24AWG OD-31 / 15mm	2,100	2,510	15	0,50	24	0,051
000-1217	Air Core Coil 2,100mH +/-3% 0,56Ω wire 1,20mm=17AWG OD-63 / 20mm	2,100	0,560	20	1,20	17	0,388
000-1255	Air Core Coil 2,100mH +/-3% 1,200Ω wire 0,80mm=20AWG OD-41 / 30mm	2,100	1,200	25	0,80	20	0,154
000-1338	Air Core Coil 2,100mH +/-3% 0,460Ω wire 1,40mm=15AWG OD-48 / 21mm	2,100	0,460	42	1,40	15	0,519
000-1697	Air Core Coil 2,100mH +/-3% 1,360Ω wire 0,70mm=21AWG OD-37 / 30mm	2,100	1,360	25	0,70	21	0,116
000-1844	Air Core Coil 2,100mH +/-3% 0,600Ω wire 1,20mm=17AWG OD-55 / 30mm	2,100	0,600	25	1,20	17	0,390

Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-1459	Air Core Coil 2,170mH +/-3% 3,500Ω wire 0,40mm=26AWG OD-31 / 8mm	2,170	3,500	15	0,40	26	0,029
000-0028	Air Core Coil 2,200mH +/-3% 0,385Ω wire 1,60mm=14AWG OD-72 / 30mm	2,200	0,385	25	1,60	14	0,791
000-0130	Air Core Coil 2,200mH +/-3% 0,345Ω wire 1,80mm=13AWG OD-66 / 60mm	2,200	0,345	35	1,80	13	1,146
000-0202	Air Core Coil 2,200mH +/-3% 1,20Ω wire 0,80mm=20AWG OD-46 / 15mm	2,200	1,200	15	0,80	20	0,142
000-0985	Air Core Coil 2,200mH +/-3% 0,39Ω wire 1,60mm=14AWG OD-78 / 25mm	2,200	0,390	8	1,60	14	0,810
000-1033	Air Core Coil 2,200mH +/-3% 2,510Ω wire 0,50mm=24AWG OD-31 / 15mm	2,200	2,510	15	0,50	24	0,052
000-1065	Air Core Coil 2,200mH +/-3% 0,840Ω wire 1,00mm=18AWG OD-49 / 30mm	2,200	0,840	25	1,00	18	0,263
000-1218	Air Core Coil 2,200mH +/-3% 0,59Ω wire 1,20mm=17AWG OD-65 / 20mm	2,200	0,590	20	1,20	17	0,401
000-1246	Air Core Coil 2,200mH +/-3% 0,473Ω wire 1,40mm=15AWG OD-64 / 30mm	2,200	0,473	25	1,40	15	0,568
000-1299	Air Core Coil 2,200mH +/-3% 0,630Ω wire 1,20mm=17AWG OD-56 / 30mm	2,200	0,630	25	1,20	17	0,404
000-1314	Air Core Coil 2,200mH +/-3% 0,490Ω wire 1,40mm=15AWG OD-80 / 31mm	2,200	0,490	54	1,40	15	0,566
000-1316	Air Core Coil 2,200mH +/-3% 1,550Ω wire 0,70mm=21AWG OD-39 / 30mm	2,200	1,550	25	0,70	21	0,121
000-1355	Air Core Coil 2,200mH +/-3% 1,380Ω wire 0,70mm=21AWG OD-41 / 15mm	2,200	1,380	15	0,70	21	0,111
000-1495	Air Core Coil 2,200mH +/-3% 0,520Ω wire 1,40mm=15AWG OD-59 / 60mm	2,200	0,520	35	1,40	15	0,651
000-1564	Air Core Coil 2,200mH +/-3% 1,230Ω wire 0,80mm=20AWG OD-41 / 30mm	2,200	1,230	25	0,80	20	0,163
000-1582	Air Core Coil 2,200mH +/-3% 6,00Ω wire 0,30mm=29AWG OD-21 / 15mm	2,200	6,000	15	0,30	29	0,016
000-1637	Air Core Coil 2,200mH +/-3% 0,700Ω wire 1,20mm=17AWG OD-45 / 62mm	2,200	0,700	24	1,20	17	0,477
000-1638	Air Core Coil 2,200mH +/-3% 0,485Ω wire 1,40mm=15AWG OD-65 / 33mm	2,200	0,485	32	1,40	15	0,569
000-1869	Air Core Coil 2,200mH +/-3% 3,500Ω wire 0,40mm=26AWG OD-31 / 8mm	2,200	3,500	15	0,40	26	0,029
000-1941	Air Core Coil 2,200mH +/-3% 0,800Ω wire 1,00mm=18AWG OD-57 / 20mm	2,200	0,800	25	1,00	18	0,255
000-1730	Air Core Coil 2,250mH +/-3% 0,635Ω wire 1,20mm=17AWG OD-56 / 30mm	2,250	0,635	25	1,20	17	0,402
000-1471	Air Core Coil 2,280mH +/-3% 2,650Ω wire 0,50mm=24AWG OD-31 / 15mm	2,280	2,650	15	0,50	24	0,053
000-0131	Air Core Coil 2,300mH +/-3% 0,355Ω wire 1,80mm=13AWG OD-70 / 60mm	2,300	0,355	35	1,80	13	1,160
000-0936	Air Core Coil 2,300mH +/-3% 0,845Ω wire 1,00mm=18AWG OD-49 / 30mm	2,300	0,845	25	1,00	18	0,269
000-1220	Air Core Coil 2,300mH +/-3% 0,60Ω wire 1,20mm=17AWG OD-65 / 20mm	2,300	0,600	20	1,20	17	0,411
000-1821	Air Core Coil 2,300mH +/-3% 0,48Ω wire 1,40mm=15AWG OD-65 / 30mm	2,300	0,480	25	1,40	15	0,587
000-0931	Air Core Coil 2,330mH +/-3% 2,650Ω wire 0,50mm=24AWG OD-37 / 15mm	2,330	2,650	25	0,50	24	0,054
000-1623	Air Core Coil 2,370mH +/-3% 0,850Ω wire 1,00mm=18AWG OD-49 / 30mm	2,370	0,850	25	1,00	18	0,275
000-0029	Air Core Coil 2,400mH +/-3% 0,405Ω wire 1,60mm=14AWG OD-75 / 30mm	2,400	0,405	25	1,60	14	0,830
000-0132	Air Core Coil 2,400mH +/-3% 0,360Ω wire 1,80mm=13AWG OD-70 / 60mm	2,400	0,360	35	1,80	13	1,195
000-0226	Air Core Coil 2,400mH +/-3% 2,65Ω wire 0,50mm=24AWG OD-37 / 15mm	2,400	2,650	25	0,50	24	0,054
000-0906	Air Core Coil 2,400mH +/-3% 1,300Ω wire 0,80mm=20AWG OD-43 / 30mm	2,400	1,300	25	0,80	20	0,167
000-1219	Air Core Coil 2,400mH +/-3% 0,61Ω wire 1,20mm=17AWG OD-65 / 20mm	2,400	0,610	20	1,20	17	0,421
000-1473	Air Core Coil 2,400mH +/-3% 0,660Ω wire 1,20mm=17AWG OD-56 / 30mm	2,400	0,660	25	1,20	17	0,415
000-1783	Air Core Coil 2,400mH +/-3% 0,512Ω wire 1,40mm=15AWG OD-80 / 31mm	2,400	0,512	54	1,40	15	0,578
000-0030	Air Core Coil 2,500mH +/-3% 0,410Ω wire 1,60mm=14AWG OD-75 / 30mm	2,500	0,410	25	1,60	14	0,856
000-0133	Air Core Coil 2,500mH +/-3% 0,368Ω wire 1,80mm=13AWG OD-70 / 60mm	2,500	0,368	35	1,80	13	1,200
000-0183	Air Core Coil 2,500mH +/-3% 6,44Ω wire 0,30mm=29AWG OD-22 / 15mm	2,500	6,440	15	0,30	29	0,018
000-0201	Air Core Coil 2,500mH +/-3% 1,28Ω wire 0,80mm=20AWG OD-48 / 15mm	2,500	1,280	15	0,80	20	0,156
000-1088	Air Core Coil 2,500mH +/-3% 0,880Ω wire 1,00mm=18AWG OD-49 / 30mm	2,500	0,880	25	1,00	18	0,284
000-1098	Air Core Coil 2,500mH +/-3% 0,520Ω wire 1,40mm=15AWG OD-81 / 31mm	2,500	0,520	54	1,40	15	0,614
000-1118	Air Core Coil 2,500mH +/-3% 2,710Ω wire 0,50mm=24AWG OD-37 / 15mm	2,500	2,710	25	0,50	24	0,056
000-1119	Air Core Coil 2,500mH +/-3% 1,840Ω wire 0,63mm=22AWG OD-38 / 15mm	2,500	1,840	15	0,63	22	0,090
000-1618	Air Core Coil 2,500mH +/-3% 3,91Ω wire 0,40mm=26AWG OD-27 / 15mm	2,500	3,910	15	0,40	26	0,033
000-1673	Air Core Coil 2,500mH +/-3% 0,670Ω wire 1,20mm=17AWG OD-56 / 30mm	2,500	0,670	25	1,20	17	0,432
000-1695	Air Core Coil 2,500mH +/-3% 1,300Ω wire 0,80mm=20AWG OD-42 / 30mm	2,500	1,300	25	0,80	20	0,170
000-1940	Air Core Coil 2,500mH +/-3% 0,850Ω wire 1,00mm=18AWG OD-58 / 20mm	2,500	0,850	25	1,00	18	0,266
000-0946	Air Core Coil 2,530mH +/-3% 0,490Ω wire 1,40mm=15AWG OD-77 / 20mm	2,530	0,490	20	1,40	15	0,599
000-1126	Air Core Coil 2,550mH +/-3% 1,840Ω wire 0,63mm=22AWG OD-38 / 15mm	2,550	1,840	15	0,63	22	0,091
000-1298	Air Core Coil 2,550mH +/-3% 0,680Ω wire 1,20mm=17AWG OD-58 / 30mm	2,550	0,680	25	1,20	17	0,436
000-1503	Air Core Coil 2,550mH +/-3% 0,890Ω wire 1,00mm=18AWG OD-50 / 30mm	2,550	0,890	25	1,00	18	0,285
000-0031	Air Core Coil 2,600mH +/-3% 0,422Ω wire 1,60mm=14AWG OD-75 / 30mm	2,600	0,422	25	1,60	14	0,870
000-0134	Air Core Coil 2,600mH +/-3% 0,374Ω wire 1,80mm=13AWG OD-70 / 60mm	2,600	0,374	35	1,80	13	1,230
000-1491	Air Core Coil 2,600mH +/-3% 0,900Ω wire 1,00mm=18AWG OD-50 / 30mm	2,600	0,900	25	1,00	18	0,286
000-1889	Air Core Coil 2,600mH +/-3% 0,690Ω wire 1,20mm=17AWG OD-58 / 30mm	2,600	0,690	25	1,20	17	0,440
000-0032	Air Core Coil 2,700mH +/-3% 0,437Ω wire 1,60mm=14AWG OD-75 / 30mm	2,700	0,437	25	1,60	14	0,890
000-0135	Air Core Coil 2,700mH +/-3% 0,380Ω wire 1,80mm=13AWG OD-70 / 60mm	2,700	0,380	35	1,80	13	1,257
000-0186	Air Core Coil 2,700mH +/-3% 1,31Ω wire 0,80mm=20AWG OD-52 / 15mm	2,700	1,310	25	0,80	20	0,161
000-0715	Air Core Coil 2,700mH +/-3% 6,50Ω wire 0,30mm=29AWG OD-25 / 12mm	2,700	6,500	17	0,30	29	0,018
000-0823	Air Core Coil 2,700mH +/-3% 2,90Ω wire 0,50mm=24AWG OD-28 / 17mm	2,700	2,900	10	0,50	24	0,059
000-1041	Air Core Coil 2,700mH +/-3% 0,700Ω wire 1,20mm=17AWG OD-58 / 30mm	2,700	0,700	25	1,20	17	0,443
000-1247	Air Core Coil 2,700mH +/-3% 0,525Ω wire 1,40mm=15AWG OD-69 / 30mm	2,700	0,525	25	1,40	15	0,631
000-1307	Air Core Coil 2,700mH +/-3% 0,920Ω wire 1,00mm=18AWG OD-51 / 30mm	2,700	0,920	25	1,00	18	0,295
000-1342	Air Core Coil 2,700mH +/-3% 1,750Ω wire 0,70mm=21AWG OD-39 / 30mm	2,700	1,750	25	0,70	21	0,134
000-1378	Air Core Coil 2,700mH +/-3% 1,560Ω wire 0,70mm=21AWG OD-42 / 15mm	2,700	1,560	15	0,70	21	0,124
000-1732	Air Core Coil 2,700mH +/-3% 4,09Ω wire 0,40mm=26AWG OD-26 / 15mm	2,700	4,090	15	0,40	26	0,034
000-1802	Air Core Coil 2,700mH +/-3% 0,590Ω wire 1,40mm=15AWG OD-61 / 60mm	2,700	0,590	35	1,40	15	0,711
000-1870	Air Core Coil 2,700mH +/-3% 2,800Ω wire 0,50mm=24AWG OD-32 / 15mm	2,700	2,800	25	0,50	24	0,056
000-1939	Air Core Coil 2,700mH +/-3% 0,900Ω wire 1,00mm=18AWG OD-58 / 20mm	2,700	0,900	15	1,00	18	0,285
000-0063	Air Core Coil 2,750mH +/-3% 0,91Ω wire 1,00mm=18AWG OD-51 / 30mm	2,750	0,910	25	1,00	18	0,309
000-0217	Air Core Coil 2,750mH +/-3% 0,39Ω wire 1,80mm=13AWG OD-72 / 60mm	2,750	0,390	35	1,80	13	1,278
000-0049	Air Core Coil 2,800mH +/-3% 0,443Ω wire 1,60mm=14AWG OD-78 / 30mm	2,800	0,443	25	1,60	14	0,920
000-0200	Air Core Coil 2,800mH +/-3% 1,36Ω wire 0,80mm=20AWG OD-48 / 15mm	2,800	1,360	15	0,80	20	0,166
000-0938	Air Core Coil 2,800mH +/-3% 0,720Ω wire 1,20mm=17AWG OD-60 / 30mm	2,800	0,720	25	1,20	17	0,455
000-0971	Air Core Coil 2,800mH +/-3% 0,95Ω wire 1,00mm=18AWG OD-50 / 30mm	2,800	0,950	25	1,00	18	0,310
000-1595	Air Core Coil 2,800mH +/-3% 0,600Ω wire 1,40mm=15AWG OD-61 / 60mm	2,800	0,600	35	1,40	15	0,726
000-1978	Air Core Coil 2,800mH +/-3% 3,500Ω wire 0,50mm=24AWG OD-22 / 35mm	2,800	3,500	7	0,50	24	0,073
000-0062	Air Core Coil 2,900mH +/-3% 0,450Ω wire 1,60mm=14AWG OD-78 / 30mm	2,900	0,450	25	1,60	14	0,930
000-0224	Air Core Coil 2,900mH +/-3% 2,90Ω wire 0,50mm=24AWG OD-32 / 15mm	2,900	2,900	15	0,50	24	0,061
000-0865	Air Core Coil 2,900mH +/-3% 0,680Ω wire 1,20mm=17AWG OD-59 / 30mm	2,900	0,680	25	1,20	17	0,467
000-0900	Air Core Coil 2,900mH +/-3% 0,630Ω wire 1,40mm=15AWG OD-61 / 60mm	2,900	0,630	35	1,40	15	0,740
000-0990	Air Core Coil 2,900mH +/-3% 0,98Ω wire 1,00mm=18AWG OD-50 / 30mm	2,900	0,980	25	1,00	18	0,311
000-0996	Air Core Coil 2,900mH +/-3% 2,100Ω wire 0,63mm=22AWG OD-53 / 21mm	2,900	2,100	42	0,63	22	0,106
000-1221	Air Core Coil 2,900mH +/-3% 1,43Ω wire 0,80mm=20AWG OD-43 / 30mm	2,900	1,430	25	0,80	20	0,188
000-0033	Air Core Coil 3,000mH +/-3% 0,46Ω wire 1,60mm=14AWG OD-78 / 30mm	3,000	0,460	25	1,60	14	0,943
000-0136	Air Core Coil 3,000mH +/-3% 0,400Ω wire 1,80mm=13AWG OD-74 / 60mm	3,000	0,400	35	1,80	13	1,331
000-0947	Air Core Coil 3,000mH +/-3% 0,540Ω wire 1,40mm=15AWG OD-77 / 20mm	3,000	0,540	10	1,40	15	0,693
000-1068	Air Core Coil 3,000mH +/-3% 0,990Ω wire 1,00mm=18AWG OD-51 / 30mm	3,000	0,990	25	1,00	18	0,312
000-1107	Air Core Coil 3,000mH +/-3% 4,350Ω wire 0,40mm=26AWG OD-27 / 15mm	3,000	4,350	15	0,40	26	0,036
000-1259	Air Core Coil 3,000mH +/-3% 7,600Ω wire 0,30mm=29AWG OD-22 / 15mm	3,000	7,600	15	0,30	29	0,019
000-1392	Air Core Coil 3,000mH +/-3% 1,680Ω wire 0,70mm=21AWG OD-43 / 15mm	3,000	1,680	15	0,70	21	0,131
000-1560	Air Core Coil 3,000mH +/-3% 0,750Ω wire 1,20mm=17AWG OD-60 / 30mm	3,000	0,750	25	1,20	17	0,470
000-1779	Air Core Coil 3,000mH +/-3% 3,040Ω wire 0,50mm=24AWG OD-32 / 15mm	3,000	3,040	15	0,50	24	0,062
000-1891	Air Core Coil 3,000mH +/-3% 2,220Ω wire 0,63mm=22AWG OD-38 / 30mm	3,000	2,220	25	0,63	22	0,113
000-1894	Air Core Coil 3,000mH +/-3% 0,640Ω wire 1,40mm=15AWG OD-61 / 60mm	3,000	0,640	35	1,40	15	0,758

Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-1913	Air Core Coil 3,000mH +/-3% 1,380Ω wire 0,80mm=20AWG OD-44 / 30mm	3,000	1,380	25	0,80	20	0,196
000-0833	Air Core Coil 3,100mH +/-3% 0,46Ω wire 1,60mm=14AWG OD-82 / 30mm	3,100	0,460	25	1,60	14	0,958
000-1592	Air Core Coil 3,160mH +/-3% 1,46Ω wire 0,80mm=20AWG OD-45 / 21mm	3,160	1,460	15	0,80	20	0,192
000-0189	Air Core Coil 3,200mH +/-3% 1,04Ω wire 1,00mm=18AWG OD-52 / 30mm	3,200	1,040	25	1,00	18	0,325
000-0884	Air Core Coil 3,200mH +/-3% 3,100Ω wire 0,50mm=24AWG OD-33 / 15mm	3,200	3,100	15	0,50	24	0,061
000-1422	Air Core Coil 3,200mH +/-3% 0,780Ω wire 1,20mm=17AWG OD-60 / 30mm	3,200	0,780	25	1,20	17	0,488
000-1583	Air Core Coil 3,200mH +/-3% 7,31Ω wire 0,30mm=29AWG OD-22 / 15mm	3,200	7,310	15	0,30	29	0,020
000-1672	Air Core Coil 3,200mH +/-3% 0,650Ω wire 1,40mm=15AWG OD-61 / 60mm	3,200	0,650	35	1,40	15	0,796
000-1705	Air Core Coil 3,200mH +/-3% 1,46Ω wire 0,80mm=20AWG OD-45 / 21mm	3,200	1,460	15	0,80	20	0,193
000-0034	Air Core Coil 3,300mH +/-3% 0,482Ω wire 1,60mm=14AWG OD-81 / 30mm	3,300	0,482	25	1,60	14	1,000
000-0137	Air Core Coil 3,300mH +/-3% 0,420Ω wire 1,80mm=13AWG OD-75 / 60mm	3,300	0,420	35	1,80	13	1,385
000-0238	Air Core Coil 3,300mH +/-3% 4,40Ω wire 0,40mm=26AWG OD-34,5 / 8mm	3,300	4,400	15	0,40	26	0,038
000-1025	Air Core Coil 3,300mH +/-3% 0,800Ω wire 1,20mm=17AWG OD-63 / 30mm	3,300	0,800	25	1,20	17	0,496
000-1070	Air Core Coil 3,300mH +/-3% 1,040Ω wire 1,00mm=18AWG OD-54 / 30mm	3,300	1,040	25	1,00	18	0,326
000-1199	Air Core Coil 3,300mH +/-3% 0,615Ω wire 1,40mm=15AWG OD-72 / 30mm	3,300	0,615	25	1,40	15	0,648
000-1200	Air Core Coil 3,300mH +/-3% 1,760Ω wire 0,70mm=21AWG OD-45 / 15mm	3,300	1,760	15	0,70	21	0,138
000-1423	Air Core Coil 3,300mH +/-3% 1,480Ω wire 0,80mm=20AWG OD-46 / 21mm	3,300	1,480	15	0,80	20	0,197
000-1494	Air Core Coil 3,300mH +/-3% 0,660Ω wire 1,40mm=15AWG OD-61 / 60mm	3,300	0,660	35	1,40	15	0,817
000-1871	Air Core Coil 3,300mH +/-3% 3,090Ω wire 0,50mm=24AWG OD-33 / 15mm	3,300	3,090	15	0,50	24	0,063
000-1872	Air Core Coil 3,300mH +/-3% 4,600Ω wire 0,40mm=26AWG OD-28 / 15mm	3,300	4,600	15	0,40	26	0,037
000-1050	Air Core Coil 3,350mH +/-3% 1,950Ω wire 0,70mm=21AWG OD-40 / 30mm	3,350	1,950	25	0,70	21	0,153
000-0035	Air Core Coil 3,400mH +/-3% 0,488Ω wire 1,60mm=14AWG OD-81 / 30mm	3,400	0,488	25	1,60	14	1,033
000-0154	Air Core Coil 3,450mH +/-3% 0,49Ω wire 1,60mm=14AWG OD-82 / 30mm	3,450	0,490	25	1,60	14	1,037
000-0960	Air Core Coil 3,450mH +/-3% 3,170Ω wire 0,50mm=24AWG OD-33 / 15mm	3,450	3,170	15	0,50	24	0,066
000-0998	Air Core Coil 3,450mH +/-3% 4,750Ω wire 0,40mm=26AWG OD-28 / 15mm	3,450	4,750	15	0,40	26	0,038
000-0153	Air Core Coil 3,500mH +/-3% 0,55Ω wire 1,60mm=14AWG OD-82 / 30mm	3,500	0,552	25	1,60	14	1,038
000-1312	Air Core Coil 3,500mH +/-3% 1,760Ω wire 0,70mm=21AWG OD-46 / 15mm	3,500	1,760	15	0,70	21	0,141
000-1493	Air Core Coil 3,500mH +/-3% 0,690Ω wire 1,40mm=15AWG OD-64 / 60mm	3,500	0,690	35	1,40	15	0,818
000-1709	Air Core Coil 3,500mH +/-3% 1,57Ω wire 0,80mm=20AWG OD-45 / 30mm	3,500	1,570	25	0,80	20	0,206
000-1975	Air Core Coil 3,500mH +/-3% 1,100Ω wire 1,00mm=18AWG OD-54 / 30mm	3,500	1,100	25	1,00	18	0,339
000-1996	Air Core Coil 3,580mH +/-3% 0,820Ω wire 1,20mm=17AWG OD-63 / 30mm	3,580	0,820	25	1,20	17	0,520
000-0046	Air Core Coil 3,600mH +/-3% 0,583Ω wire 1,60mm=14AWG OD-70 / 60mm	3,600	0,583	35	1,60	14	1,157
000-0167	Air Core Coil 3,600mH +/-3% 1,08Ω wire 1,00mm=18AWG OD-54 / 30mm	3,600	1,080	25	1,00	18	0,351
000-0700	Air Core Coil 3,600mH +/-3% 2,20Ω wire 0,63mm=22AWG OD-42 / 15mm	3,600	2,200	15	0,63	22	0,117
000-1584	Air Core Coil 3,600mH +/-3% 7,83Ω wire 0,30mm=29AWG OD-23 / 15mm	3,600	7,830	15	0,30	29	0,021
000-0185	Air Core Coil 3,700mH +/-3% 5,05Ω wire 0,40mm=26AWG OD-28 / 15mm	3,700	5,050	15	0,40	26	0,041
000-1704	Air Core Coil 3,700mH +/-3% 3,250Ω wire 0,50mm=24AWG OD-33 / 15mm	3,700	3,250	15	0,50	24	0,069
000-1222	Air Core Coil 3,800mH +/-3% 1,200Ω wire 1,00mm=18AWG OD-54 / 30mm	3,800	1,200	25	1,00	18	0,370
000-1800	Air Core Coil 3,800mH +/-3% 0,63Ω wire 1,40mm=15AWG OD-74 / 30mm	3,800	0,630	25	1,40	15	0,783
000-0036	Air Core Coil 3,900mH +/-3% 0,593Ω wire 1,60mm=14AWG OD-70 / 60mm	3,900	0,593	35	1,60	14	1,164
000-1127	Air Core Coil 3,900mH +/-3% 2,320Ω wire 0,63mm=22AWG OD-43 / 15mm	3,900	2,320	15	0,63	22	0,120
000-1139	Air Core Coil 3,900mH +/-3% 3,450Ω wire 0,50mm=24AWG OD-35 / 15mm	3,900	3,450	15	0,50	24	0,069
000-1241	Air Core Coil 3,900mH +/-3% 0,660Ω wire 1,40mm=15AWG OD-74 / 30mm	3,900	0,660	25	1,40	15	0,790
000-1326	Air Core Coil 3,900mH +/-3% 2,100Ω wire 0,70mm=21AWG OD-41 / 30mm	3,900	2,100	25	0,70	21	0,165
000-1713	Air Core Coil 3,900mH +/-3% 0,825Ω wire 1,20mm=17AWG OD-64 / 30mm	3,900	0,825	25	1,20	17	0,556
000-1873	Air Core Coil 3,900mH +/-3% 5,070Ω wire 0,40mm=26AWG OD-29 / 15mm	3,900	5,070	15	0,40	26	0,041
000-1930	Air Core Coil 3,900mH +/-3% 1,200Ω wire 1,00mm=18AWG OD-54 / 30mm	3,900	1,200	25	1,00	18	0,370
000-1944	Air Core Coil 3,900mH +/-3% 0,700Ω wire 1,40mm=15AWG OD-64 / 60mm	3,900	0,700	35	1,40	15	0,871
000-1458	Air Core Coil 3,940mH +/-3% 5,070Ω wire 0,40mm=26AWG OD-29 / 15mm	3,940	5,070	15	0,40	26	0,042
000-0047	Air Core Coil 4,000mH +/-3% 0,60Ω wire 1,60mm=14AWG OD-70 / 60mm	4,000	0,603	35	1,60	14	1,230
000-0172	Air Core Coil 4,000mH +/-3% 0,48Ω wire 1,80mm=13AWG OD-78 / 60mm	4,000	0,480	35	1,80	13	1,583
000-0181	Air Core Coil 4,000mH +/-3% 0,83Ω wire 1,20mm=17AWG OD-65 / 30mm	4,000	0,830	25	1,20	17	0,572
000-0885	Air Core Coil 4,000mH +/-3% 3,610Ω wire 0,50mm=24AWG OD-35 / 15mm	4,000	3,610	15	0,50	24	0,072
000-1099	Air Core Coil 4,000mH +/-3% 0,720Ω wire 1,40mm=15AWG OD-66 / 60mm	4,000	0,720	35	1,40	15	0,891
000-1185	Air Core Coil 4,000mH +/-3% 2,030Ω wire 0,70mm=21AWG OD-47 / 15mm	4,000	2,030	15	0,70	21	0,152
000-1605	Air Core Coil 4,000mH +/-3% 3,950Ω wire 0,50mm=24AWG OD-29 / 27mm	4,000	3,950	15	0,50	24	0,081
000-1793	Air Core Coil 4,000mH +/-3% 2,190Ω wire 0,80mm=20AWG OD-35 / 50mm	4,000	1,980	13	0,80	20	0,271
000-1920	Air Core Coil 4,000mH +/-3% 2,200Ω wire 0,70mm=21AWG OD-43 / 50mm	4,000	2,200	25	0,70	21	0,163
000-1936	Air Core Coil 4,000mH +/-3% 2,040Ω wire 0,80mm=20AWG OD-34 / 50mm	4,000	2,040	8	0,80	20	0,268
000-1956	Air Core Coil 4,000mH +/-3% 1,21Ω wire 1,00mm=18AWG OD-55 / 30mm	4,000	1,210	25	1,00	18	0,375
000-1981	Air Core Coil 4,000mH +/-3% 1,700Ω wire 0,80mm=20AWG OD-45 / 30mm	4,000	1,700	25	0,80	20	0,220
000-1639	Air Core Coil 4,100mH +/-3% 0,660Ω wire 1,40mm=15AWG OD-73 / 33mm	4,100	0,660	32	1,40	15	0,800
000-1798	Air Core Coil 4,100mH +/-3% 8,60Ω wire 0,30mm=29AWG OD-24 / 15mm	4,100	8,600	15	0,30	29	0,023
000-1393	Air Core Coil 4,200mH +/-3% 2,190Ω wire 0,70mm=21AWG OD-41 / 30mm	4,200	2,190	25	0,70	21	0,172
000-1664	Air Core Coil 4,300mH +/-3% 1,800Ω wire 0,80mm=20AWG OD-47 / 30mm	4,300	1,800	25	0,80	20	0,231
000-0059	Air Core Coil 4,400mH +/-3% 0,60Ω wire 1,80mm=13AWG OD-82 / 60mm	4,400	0,534	35	1,80	13	1,650
000-1671	Air Core Coil 4,400mH +/-3% 2,230Ω wire 0,70mm=21AWG OD-43 / 30mm	4,400	2,230	25	0,70	21	0,176
000-1043	Air Core Coil 4,430mH +/-3% 1,240Ω wire 1,00mm=18AWG OD-55 / 30mm	4,430	1,240	25	1,00	18	0,382
000-0143	Air Core Coil 4,400mH +/-3% 0,780Ω wire 1,40mm=15AWG OD-59 / 62mm	4,500	0,780	24	1,40	15	0,970
000-0857	Air Core Coil 4,500mH +/-3% 1,85Ω wire 0,80mm=20AWG OD-46 / 30mm	4,500	1,850	25	0,80	20	0,246
000-0923	Air Core Coil 4,500mH +/-3% 0,930Ω wire 1,20mm=17AWG OD-68 / 30mm	4,500	0,930	25	1,20	17	0,604
000-0932	Air Core Coil 4,500mH +/-3% 3,850Ω wire 0,50mm=24AWG OD-35 / 15mm	4,500	3,850	15	0,50	24	0,076
000-1468	Air Core Coil 4,500mH +/-3% 0,800Ω wire 1,40mm=15AWG OD-58 / 62mm	4,500	0,800	24	1,40	15	0,980
000-1585	Air Core Coil 4,500mH +/-3% 8,84Ω wire 0,30mm=29AWG OD-24 / 15mm	4,500	8,840	15	0,30	29	0,024
000-1957	Air Core Coil 4,500mH +/-3% 1,250Ω wire 1,00mm=18AWG OD-57 / 30mm	4,500	1,250	25	1,00	18	0,396
000-0037	Air Core Coil 4,700mH +/-3% 0,650Ω wire 1,60mm=14AWG OD-73 / 60mm	4,700	0,650	35	1,60	14	1,334
000-0880	Air Core Coil 4,700mH +/-3% 1,900Ω wire 0,80mm=20AWG OD-46 / 30mm	4,700	1,900	25	0,80	20	0,250
000-1187	Air Core Coil 4,700mH +/-3% 0,760Ω wire 1,40mm=15AWG OD-76 / 30mm	4,700	0,760	25	1,40	15	0,870
000-1240	Air Core Coil 4,700mH +/-3% 1,300Ω wire 1,00mm=18AWG OD-57 / 30mm	4,700	1,300	25	1,00	18	0,402
000-1519	Air Core Coil 4,700mH +/-3% 0,820Ω wire 1,40mm=15AWG OD-60 / 62mm	4,700	0,820	24	1,40	15	1,000
000-1520	Air Core Coil 4,700mH +/-3% 2,330Ω wire 0,70mm=21AWG OD-43 / 30mm	4,700	2,330	25	0,70	21	0,182
000-1587	Air Core Coil 4,700mH +/-3% 0,800Ω wire 1,40mm=15AWG OD-66 / 60mm	4,700	0,800	35	1,40	15	0,976
000-1607	Air Core Coil 4,700mH +/-3% 4,300Ω wire 0,50mm=24AWG OD-30 / 27mm	4,700	4,300	15	0,50	24	0,088
000-1714	Air Core Coil 4,700mH +/-3% 0,970Ω wire 1,20mm=17AWG OD-68 / 30mm	4,700	0,970	25	1,20	17	0,622
000-1780	Air Core Coil 4,700mH +/-3% 3,910Ω wire 0,50mm=24AWG OD-36 / 15mm	4,700	3,910	15	0,50	24	0,080
000-1935	Air Core Coil 4,700mH +/-3% 2,190Ω wire 0,80mm=20AWG OD-36 / 50mm	4,700	2,190	13	0,80	20	0,282
000-0234	Air Core Coil 4,800mH +/-3% 0,53Ω wire 1,80mm=13AWG OD-82 / 60mm	4,800	0,530	35	1,80	13	1,722
000-1486	Air Core Coil 4,800mH +/-3% 0,830Ω wire 1,40mm=15AWG OD-60 / 62mm	4,800	0,830	24	1,40	15	1,026
000-0138	Air Core Coil 5,000mH +/-3% 0,534Ω wire 1,80mm=13AWG OD-82 / 60mm	5,000	0,534	35	1,80	13	1,775
000-0147	Air Core Coil 5,000mH +/-3% 3,06Ω wire 0,63mm=22AWG OD-40 / 30mm	5,000	3,060	25	0,63	22	0,148
000-1258	Air Core Coil 5,000mH +/-3% 10,100Ω wire 0,30mm=29AWG OD-25 / 15mm	5,000	10,100	15	0,30	29	0,026
000-1501	Air Core Coil 5,000mH +/-3% 0,990Ω wire 1,20mm=17AWG OD-69 / 30mm	5,000	0,990	25	1,20	17	0,640
000-1604	Air Core Coil 5,000mH +/-3% 4,450Ω wire 0,50mm=24AWG OD-30 / 27mm	5,000	4,450	15	0,50	24	0,102
000-1614	Air Core Coil 5,000mH +/-3% 0,830Ω wire 1,40mm=15AWG OD-66 / 60mm	5,000	0,830	35	1,40	15	1,009
000-1892	Air Core Coil 5,000mH +/-3% 1,300Ω wire 1,00mm=18AWG OD-60 / 30mm	5,000	1,300	25	1,00	18	0,419

Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-1938	Air Core Coil 5,000mH +/-3% 2,450Ω wire 0,70mm=21AWG OD-43 / 30mm	5,000	2,450	25	0,70	21	0,190
000-1982	Air Core Coil 5,000mH +/-3% 1,950Ω wire 0,80mm=20AWG OD-48 / 30mm	5,000	1,950	25	0,80	20	0,259
000-0937	Air Core Coil 5,100mH +/-3% 1,010Ω wire 1,20mm=17AWG OD-70 / 30mm	5,100	1,010	25	1,20	17	0,655
000-1346	Air Core Coil 5,100mH +/-3% 8,800Ω wire 0,30mm=29AWG OD-30 / 8mm	5,100	8,800	15	0,30	29	0,025
000-1351	Air Core Coil 5,100mH +/-3% 10,200Ω wire 0,30mm=29AWG OD-25 / 15mm	5,100	10,200	15	0,30	29	0,026
000-0095	Air Core Coil 5,150mH +/-3% 0,65Ω wire 1,60mm=14AWG OD-74 / 60mm	5,150	0,650	35	1,60	14	1,410
000-0701	Air Core Coil 5,400mH +/-3% 0,870Ω wire 1,40mm=15AWG OD-69 / 60mm	5,400	0,870	35	1,40	15	1,075
000-0805	Air Core Coil 5,400mH +/-3% 1,33Ω wire 1,00mm=18AWG OD-78 / 15mm	5,400	1,330	25	1,00	18	0,438
000-0184	Air Core Coil 5,500mH +/-3% 1,37Ω wire 1,00mm=18AWG OD-78 / 15mm	5,500	1,370	25	1,00	18	0,437
000-0861	Air Core Coil 5,500mH +/-3% 0,69Ω wire 1,60mm=14AWG OD-76 / 60mm	5,500	0,690	35	1,60	14	1,462
000-0038	Air Core Coil 5,600mH +/-3% 0,700Ω wire 1,60mm=14AWG OD-76 / 60mm	5,600	0,700	35	1,60	14	1,466
000-1500	Air Core Coil 5,600mH +/-3% 1,170Ω wire 1,20mm=17AWG OD-60 / 60mm	5,600	1,170	35	1,20	17	0,777
000-1538	Air Core Coil 5,600mH +/-3% 1,400Ω wire 1,00mm=18AWG OD-30 / 30mm	5,600	1,400	25	1,00	18	0,456
000-1546	Air Core Coil 5,600mH +/-3% 0,870Ω wire 1,40mm=15AWG OD-69 / 60mm	5,600	0,870	35	1,40	15	1,075
000-1611	Air Core Coil 5,600mH +/-3% 4,740Ω wire 0,50mm=24AWG OD-31 / 27mm	5,600	4,740	15	0,50	24	0,100
000-1652	Air Core Coil 5,600mH +/-3% 2,100Ω wire 0,80mm=20AWG OD-48 / 30mm	5,600	2,100	25	0,80	20	0,277
000-1653	Air Core Coil 5,600mH +/-3% 2,650Ω wire 0,70mm=21AWG OD-44 / 30mm	5,600	2,650	25	0,70	21	0,205
000-1349	Air Core Coil 5,700mH +/-3% 10,800Ω wire 0,30mm=29AWG OD-25 / 15mm	5,700	10,800	15	0,30	29	0,028
000-0161	Air Core Coil 5,780mH +/-3% 0,90Ω wire 1,40mm=15AWG OD-69 / 60mm	5,780	0,900	35	1,40	15	1,091
000-0804	Air Core Coil 5,800mH +/-3% 3,29Ω wire 0,63mm=22AWG OD-41 / 30mm	5,800	3,290	25	0,63	22	0,165
000-0970	Air Core Coil 5,800mH +/-3% 1,68Ω wire 1,00mm=18AWG OD-54 / 60mm	5,800	1,680	35	1,00	18	0,529
000-0148	Air Core Coil 6,000mH +/-3% 3,29Ω wire 0,63mm=22AWG OD-41 / 30mm	6,000	3,290	25	0,63	22	0,165
000-0182	Air Core Coil 6,000mH +/-3% 4,85Ω wire 0,50mm=24AWG OD-32 / 27mm	6,000	4,850	15	0,50	24	0,101
000-0811	Air Core Coil 6,000mH +/-3% 0,68Ω wire 1,60mm=14AWG OD-95 / 30mm	6,000	0,680	25	1,60	14	1,419
000-0945	Air Core Coil 6,000mH +/-3% 2,720Ω wire 0,70mm=21AWG OD-45 / 30mm	6,000	2,720	25	0,70	21	0,210
000-0992	Air Core Coil 6,000mH +/-3% 0,730Ω wire 1,60mm=14AWG OD-76 / 60mm	6,000	0,730	35	1,60	14	1,550
000-1167	Air Core Coil 6,000mH +/-3% 0,910Ω wire 1,40mm=15AWG OD-71 / 60mm	6,000	0,910	35	1,40	15	1,202
000-1225	Air Core Coil 6,000mH +/-3% 1,220Ω wire 1,20mm=17AWG OD-60 / 60mm	6,000	1,220	35	1,20	17	0,812
000-1348	Air Core Coil 6,000mH +/-3% 11,100Ω wire 0,30mm=29AWG OD-26 / 15mm	6,000	11,100	15	0,30	29	0,029
000-1508	Air Core Coil 6,000mH +/-3% 1,660Ω wire 1,00mm=18AWG OD-54 / 60mm	6,000	1,660	35	1,00	18	0,533
000-1958	Air Core Coil 6,000mH +/-3% 1,450Ω wire 1,00mm=18AWG OD-61 / 30mm	6,000	1,450	25	1,00	18	0,462
000-0983	Air Core Coil 6,150mH +/-3% 0,75Ω wire 1,60mm=14AWG OD-78 / 60mm	6,150	0,750	35	1,60	14	1,560
000-0039	Air Core Coil 6,200mH +/-3% 0,750Ω wire 1,60mm=14AWG OD-78 / 60mm	6,200	0,750	35	1,60	14	1,566
000-0893	Air Core Coil 6,200mH +/-3% 0,930Ω wire 1,40mm=15AWG OD-71 / 60mm	6,200	0,930	35	1,40	15	1,205
000-1329	Air Core Coil 6,200mH +/-3% 2,740Ω wire 0,70mm=21AWG OD-45 / 30mm	6,200	2,740	25	0,70	21	0,213
000-1499	Air Core Coil 6,200mH +/-3% 1,250Ω wire 1,20mm=17AWG OD-62 / 60mm	6,200	1,250	35	1,20	17	0,820
000-1610	Air Core Coil 6,200mH +/-3% 5,050Ω wire 0,50mm=24AWG OD-32 / 27mm	6,200	5,050	15	0,50	24	0,102
000-0933	Air Core Coil 6,400mH +/-3% 5,120Ω wire 0,50mm=24AWG OD-32 / 27mm	6,400	5,120	15	0,50	24	0,105
000-1347	Air Core Coil 6,400mH +/-3% 11,600Ω wire 0,30mm=29AWG OD-26 / 15mm	6,400	11,600	15	0,30	29	0,030
000-1630	Air Core Coil 6,400mH +/-3% 0,950Ω wire 1,40mm=15AWG OD-71 / 60mm	6,400	0,950	35	1,40	15	1,215
000-1768	Air Core Coil 6,400mH +/-3% 1,540Ω wire 1,00mm=18AWG OD-61 / 30mm	6,400	1,540	25	1,00	18	0,480
000-0993	Air Core Coil 6,600mH +/-3% 0,780Ω wire 1,60mm=14AWG OD-79 / 60mm	6,600	0,780	35	1,60	14	1,640
000-1586	Air Core Coil 6,600mH +/-3% 10,970Ω wire 0,30mm=29AWG OD-26 / 15mm	6,600	10,970	15	0,30	29	0,030
000-1666	Air Core Coil 6,600mH +/-3% 1,580Ω wire 1,00mm=18AWG OD-62 / 30mm	6,600	1,580	25	1,00	18	0,488
000-0040	Air Core Coil 6,800mH +/-3% 0,790Ω wire 1,60mm=14AWG OD-79 / 60mm	6,800	0,790	35	1,60	14	1,650
000-1333	Air Core Coil 6,800mH +/-3% 2,850Ω wire 0,70mm=21AWG OD-45 / 30mm	6,800	2,850	25	0,70	21	0,224
000-1498	Air Core Coil 6,800mH +/-3% 1,300Ω wire 1,20mm=17AWG OD-62 / 60mm	6,800	1,300	35	1,20	17	0,870
000-1547	Air Core Coil 6,800mH +/-3% 0,960Ω wire 1,40mm=15AWG OD-71 / 60mm	6,800	0,960	35	1,40	15	1,218
000-1609	Air Core Coil 6,800mH +/-3% 5,280Ω wire 0,50mm=24AWG OD-33 / 27mm	6,800	5,280	15	0,50	24	0,105
000-1706	Air Core Coil 6,800mH +/-3% 2,300Ω wire 0,80mm=20AWG OD-52 / 30mm	6,800	2,300	25	0,80	20	0,312
000-1707	Air Core Coil 6,800mH +/-3% 1,590Ω wire 1,00mm=18AWG OD-63 / 30mm	6,800	1,590	25	1,00	18	0,496
000-0240	Air Core Coil 7,000mH +/-3% 2,30Ω wire 0,80mm=20AWG OD-55 / 21mm	7,000	2,300	15	0,80	20	0,303
000-0934	Air Core Coil 7,000mH +/-3% 3,080Ω wire 0,70mm=21AWG OD-46 / 30mm	7,000	3,080	25	0,70	21	0,226
000-1257	Air Core Coil 7,000mH +/-3% 11,800Ω wire 0,30mm=29AWG OD-26 / 15mm	7,000	11,800	15	0,30	29	0,031
000-1497	Air Core Coil 7,000mH +/-3% 1,330Ω wire 1,20mm=17AWG OD-64 / 60mm	7,000	1,330	35	1,20	17	0,885
000-1506	Air Core Coil 7,000mH +/-3% 0,980Ω wire 1,40mm=15AWG OD-74 / 60mm	7,000	0,980	35	1,40	15	1,238
000-1598	Air Core Coil 7,000mH +/-3% 5,28Ω wire 0,50mm=24AWG OD-33 / 27mm	7,000	5,280	15	0,50	24	0,107
000-1959	Air Core Coil 7,000mH +/-3% 1,600Ω wire 1,00mm=18AWG OD-63 / 30mm	7,000	1,600	25	1,00	18	0,504
000-1588	Air Core Coil 7,200mH +/-3% 11,44Ω wire 0,30mm=29AWG OD-25 / 15mm	7,200	11,440	15	0,30	29	0,031
000-0041	Air Core Coil 7,500mH +/-3% 0,830Ω wire 1,60mm=14AWG OD-79 / 60mm	7,500	0,830	35	1,60	14	1,749
000-1541	Air Core Coil 7,500mH +/-3% 12,500Ω wire 0,30mm=29AWG OD-26 / 15mm	7,500	12,500	15	0,30	29	0,032
000-0851	Air Core Coil 7,800mH +/-3% 3,81Ω wire 0,63mm=22AWG OD-43 / 30mm	7,800	3,810	25	0,63	22	0,190
000-0048	Air Core Coil 8,000mH +/-3% 0,870Ω wire 1,60mm=14AWG OD-82 / 60mm	8,000	0,870	35	1,60	14	1,826
000-0212	Air Core Coil 8,000mH +/-3% 0,70Ω wire 1,80mm=13AWG OD-92 / 60mm	8,000	0,700	35	1,80	13	2,323
000-1271	Air Core Coil 8,000mH +/-3% 2,540Ω wire 0,80mm=20AWG OD-54 / 30mm	8,000	2,540	25	0,80	20	0,324
000-1427	Air Core Coil 8,000mH +/-3% 1,240Ω wire 1,40mm=15AWG OD-61 / 75mm	8,000	1,240	20	1,40	15	1,456
000-1502	Air Core Coil 8,000mH +/-3% 1,420Ω wire 1,20mm=17AWG OD-64 / 60mm	8,000	1,420	35	1,20	17	0,942
000-1613	Air Core Coil 8,000mH +/-3% 1,080Ω wire 1,40mm=15AWG OD-74 / 60mm	8,000	1,080	35	1,40	15	1,300
000-1785	Air Core Coil 8,000mH +/-3% 5,810Ω wire 0,50mm=24AWG OD-33 / 27mm	8,000	5,810	15	0,50	24	0,116
000-1960	Air Core Coil 8,000mH +/-3% 1,750Ω wire 1,00mm=18AWG OD-66 / 30mm	8,000	1,750	25	1,00	18	0,549
000-0042	Air Core Coil 8,200mH +/-3% 0,870Ω wire 1,60mm=14AWG OD-82 / 60mm	8,200	0,870	35	1,60	14	1,852
000-0230	Air Core Coil 8,200mH +/-3% 1,43Ω wire 1,20mm=17AWG OD-66 / 60mm	8,200	1,430	35	1,20	17	0,965
000-1023	Air Core Coil 8,200mH +/-3% 3,350Ω wire 0,70mm=21AWG OD-48 / 30mm	8,200	3,350	25	0,70	21	0,248
000-1238	Air Core Coil 8,200mH +/-3% 1,780Ω wire 1,00mm=18AWG OD-66 / 30mm	8,200	1,780	25	1,00	18	0,568
000-1602	Air Core Coil 8,200mH +/-3% 1,100Ω wire 1,40mm=15AWG OD-74 / 60mm	8,200	1,100	35	1,40	15	1,328
000-1608	Air Core Coil 8,200mH +/-3% 5,830Ω wire 0,50mm=24AWG OD-33 / 27mm	8,200	5,830	15	0,50	24	0,119
000-0233	Air Core Coil 9,000mH +/-3% 3,33Ω wire 0,70mm=21AWG OD-48 / 30mm	9,000	3,330	25	0,70	21	0,264
000-0836	Air Core Coil 9,000mH +/-3% 5,11Ω wire 0,63mm=22AWG OD-44 / 60mm	9,000	5,110	25	0,63	22	0,240
000-0909	Air Core Coil 9,000mH +/-3% 1,180Ω wire 1,40mm=15AWG OD-74 / 60mm	9,000	1,180	35	1,40	15	1,435
000-1442	Air Core Coil 9,000mH +/-3% 1,530Ω wire 1,20mm=17AWG OD-66 / 60mm	9,000	1,530	35	1,20	17	0,995
000-1961	Air Core Coil 9,000mH +/-3% 1,850Ω wire 1,00mm=18AWG OD-69 / 30mm	9,000	1,850	25	1,00	18	0,599
000-0043	Air Core Coil 9,100mH +/-3% 0,920Ω wire 1,60mm=14AWG OD-82 / 60mm	9,100	0,920	35	1,60	14	1,951
000-0144	Air Core Coil 10,000mH +/-3% 0,76Ω wire 1,80mm=13AWG OD-95 / 60mm	10,000	0,760	35	1,80	13	2,630
000-0222	Air Core Coil 10,000mH +/-3% 1,00Ω wire 1,60mm=14AWG OD-83 / 62mm	10,000	1,000	24	1,60	14	2,096
000-1248	Air Core Coil 10,000mH +/-3% 3,700Ω wire 0,70mm=21AWG OD-49 / 30mm	10,000	3,700	25	0,70	21	0,280
000-1504	Air Core Coil 10,000mH +/-3% 13,000Ω wire 0,30mm=29AWG OD-28 / 15mm	10,000	13,000	15	0,30	29	0,038
000-1549	Air Core Coil 10,000mH +/-3% 2,880Ω wire 0,80mm=20AWG OD-55 / 30mm	10,000	2,880	25	0,80	20	0,363
000-1601	Air Core Coil 10,000mH +/-3% 1,200Ω wire 1,40mm=15AWG OD-76 / 60mm	10,000	1,200	35	1,40	15	1,489
000-1681	Air Core Coil 10,000mH +/-3% 1,660Ω wire 1,20mm=17AWG OD-67 / 60mm	10,000	1,660	35	1,20	17	1,095
000-1781	Air Core Coil 10,000mH +/-3% 4,230Ω wire 0,70mm=21AWG OD-48 / 30mm	10,000	4,230	25	0,70	21	0,331
000-1962	Air Core Coil 10,000mH +/-3% 1,950Ω wire 1,00mm=18AWG OD-70 / 30mm	10,000	1,950	25	1,00	18	0,624
000-0220	Air Core Coil 11,000mH +/-3% 0,90Ω wire 1,80mm=13AWG OD-91 / 66mm	11,000	0,900	25	1,80	13	2,884
000-1418	Air Core Coil 11,000mH +/-3% 1,720Ω wire 1,20mm=17AWG OD-68 / 60mm	11,000	1,720	35	1,20	17	1,098
000-1698	Air Core Coil 11,000mH +/-3% 4,450Ω wire 0,70mm=21AWG OD-48 / 60mm	11,000	4,450	25	0,70	21	0,345
000-1749	Air Core Coil 11,000mH +/-3% 5,550Ω wire 0,63mm=22AWG OD-46 / 60mm	11,000	5,550	25	0,63	22	0,275

Index:	Description:	mH:	RDC [Ω]:	Coil ID [mm]	Wire [mm]:	AWG:	Weight (kg):
000-0158	Air Core Coil 11,200mH +/-3% 2,198Ω wire 1,00mm=18AWG OD-68 / 30mm	11,200	2,198	25	1,00	18	0,660
000-0897	Air Core Coil 11,600mH +/-3% 2,860Ω wire 1,00mm=18AWG OD-53 / 100mm	11,600	2,860	33	1,00	18	0,882
000-0211	Air Core Coil 12,000mH +/-3% 1,320Ω wire 1,40mm=15AWG OD-79 / 60mm	12,000	1,320	35	1,40	15	1,648
000-0856	Air Core Coil 12,000mH +/-3% 3,290Ω wire 0,80mm=20AWG OD-57 / 30mm	12,000	3,290	25	0,80	20	0,422
000-0926	Air Core Coil 12,000mH +/-3% 5,800Ω wire 0,63mm=22AWG OD-46 / 60mm	12,000	5,800	35	0,63	22	0,285
000-0964	Air Core Coil 12,000mH +/-3% 4,710Ω wire 0,70mm=21AWG OD-49 / 60mm	12,000	4,710	35	0,70	21	0,360
000-1715	Air Core Coil 12,000mH +/-3% 1,910Ω wire 1,20mm=17AWG OD-69 / 60mm	12,000	1,910	35	1,20	17	1,100
000-1971	Air Core Coil 12,000mH +/-3% 2,230Ω wire 1,00mm=18AWG OD-72 / 30mm	12,000	2,230	25	1,00	18	0,700
000-1037	Air Core Coil 13,000mH +/-3% 9,260Ω wire 0,50mm=24AWG OD-42 / 60mm	13,000	9,260	35	0,50	24	0,183
000-1687	Air Core Coil 13,000mH +/-3% 4,970Ω wire 0,70mm=21AWG OD-50 / 60mm	13,000	4,970	35	0,70	21	0,374
000-0956	Air Core Coil 13,280mH +/-3% 3,170Ω wire 1,00mm=18AWG OD-55 / 100mm	13,280	3,170	33	1,00	18	0,992
000-1594	Air Core Coil 13,500mH +/-3% 7,800Ω wire 0,50mm=24AWG OD-41 / 30mm	13,500	7,800	25	0,50	24	0,159
000-0872	Air Core Coil 14,000mH +/-3% 2,450Ω wire 1,00mm=18AWG OD-73 / 30mm	14,000	2,450	25	1,00	18	0,747
000-1719	Air Core Coil 14,000mH +/-3% 2,080Ω wire 1,20mm=17AWG OD-70 / 60mm	14,000	2,080	35	1,20	17	1,176
000-1770	Air Core Coil 14,400mH +/-3% 7,840Ω wire 0,50mm=24AWG OD-40 / 30mm	14,400	7,840	25	0,50	24	0,164
000-1720	Air Core Coil 14,500mH +/-3% 2,150Ω wire 1,20mm=17AWG OD-71 / 60mm	14,500	2,150	35	1,20	17	1,204
000-0196	Air Core Coil 14,800mH +/-3% 1,250Ω wire 1,60mm=14AWG OD-90 / 62mm	14,800	1,250	24	1,60	14	2,550
000-0892	Air Core Coil 15,000mH +/-3% 13,300Ω wire 0,40mm=26AWG OD-36 / 30mm	15,000	13,300	25	0,40	26	0,099
000-0963	Air Core Coil 15,000mH +/-3% 1,250Ω wire 1,60mm=14AWG OD-91 / 62mm	15,000	1,250	24	1,60	14	2,560
000-1476	Air Core Coil 15,000mH +/-3% 15,720Ω wire 0,40mm=26AWG OD-40 / 60mm	15,000	15,720	35	0,40	26	0,130
000-1561	Air Core Coil 15,000mH +/-3% 5,270Ω wire 0,70mm=21AWG OD-51 / 60mm	15,000	5,270	35	0,70	21	0,412
000-1591	Air Core Coil 15,000mH +/-3% 2,440Ω wire 1,00mm=18AWG OD-73 / 30mm	15,000	2,440	25	1,00	18	0,814
000-1716	Air Core Coil 15,000mH +/-3% 2,180Ω wire 1,20mm=17AWG OD-72 / 60mm	15,000	2,180	35	1,20	17	1,224
000-0841	Air Core Coil 16,000mH +/-3% 5,520Ω wire 0,70mm=21AWG OD-51 / 60mm	16,000	5,520	35	0,70	21	0,433
000-0873	Air Core Coil 16,000mH +/-3% 2,660Ω wire 1,00mm=18AWG OD-75 / 30mm	16,000	2,660	25	1,00	18	0,837
000-1721	Air Core Coil 16,000mH +/-3% 2,220Ω wire 1,20mm=17AWG OD-73 / 60mm	16,000	2,220	35	1,20	17	1,259
000-0197	Air Core Coil 16,800mH +/-3% 2,660Ω wire 1,00mm=18AWG OD-75 / 30mm	16,800	2,660	25	1,00	18	0,867
000-0943	Air Core Coil 17,000mH +/-3% 5,780Ω wire 0,70mm=21AWG OD-52 / 60mm	17,000	5,780	35	0,70	21	0,443
000-1722	Air Core Coil 17,000mH +/-3% 2,310Ω wire 1,20mm=17AWG OD-75 / 60mm	17,000	2,310	35	1,20	17	1,301
000-0840	Air Core Coil 18,000mH +/-3% 2,810Ω wire 1,00mm=18AWG OD-77 / 30mm	18,000	2,810	25	1,00	18	0,898
000-1699	Air Core Coil 18,000mH +/-3% 5,780Ω wire 0,70mm=21AWG OD-52 / 60mm	18,000	5,780	35	0,70	21	0,455
000-1717	Air Core Coil 18,000mH +/-3% 2,400Ω wire 1,20mm=17AWG OD-75 / 60mm	18,000	2,400	35	1,20	17	1,341
000-1723	Air Core Coil 19,000mH +/-3% 2,470Ω wire 1,20mm=17AWG OD-77 / 60mm	19,000	2,470	35	1,20	17	1,385
000-0809	Air Core Coil 20,000mH +/-3% 3,040Ω wire 1,00mm=18AWG OD-80 / 30mm	20,000	3,040	25	1,00	18	0,969
000-1718	Air Core Coil 20,000mH +/-3% 2,550Ω wire 1,20mm=17AWG OD-77 / 60mm	20,000	2,550	35	1,20	17	1,426
000-1748	Air Core Coil 20,000mH +/-3% 5,100Ω wire 0,80mm=20AWG OD-57 / 60mm	20,000	5,100	35	0,80	20	0,632
000-1765	Air Core Coil 20,000mH +/-3% 6,380Ω wire 0,70mm=21AWG OD-52 / 60mm	20,000	6,380	35	0,70	21	0,480
000-1792	Air Core Coil 20,000mH +/-3% 1,850Ω wire 1,40mm=15AWG OD-89 / 60mm	20,000	1,850	35	1,40	15	2,240
000-0815	Air Core Coil 21,000mH +/-3% 8,060Ω wire 0,63mm=22AWG OD-51 / 60mm	21,000	8,060	35	0,63	22	0,388
000-1724	Air Core Coil 21,000mH +/-3% 2,620Ω wire 1,20mm=17AWG OD-79 / 60mm	21,000	2,620	35	1,20	17	1,475
000-0097	Air Core Coil 21,500mH +/-3% 5,250Ω wire 0,80mm=20AWG OD-59 / 60mm	21,500	5,250	35	0,80	20	0,700
000-0810	Air Core Coil 22,000mH +/-3% 3,170Ω wire 1,00mm=18AWG OD-83 / 30mm	22,000	3,170	25	1,00	18	1,024
000-0871	Air Core Coil 22,000mH +/-3% 6,650Ω wire 0,70mm=21AWG OD-53 / 60mm	22,000	6,650	35	0,70	21	0,505
000-0915	Air Core Coil 22,000mH +/-3% 8,100Ω wire 0,63mm=22AWG OD-51 / 60mm	22,000	8,100	35	0,63	22	0,401
000-0975	Air Core Coil 22,000mH +/-3% 10,600Ω wire 0,50mm=24AWG OD-40 / 32mm	22,000	10,600	17	0,50	24	0,210
000-1725	Air Core Coil 22,000mH +/-3% 2,680Ω wire 1,20mm=17AWG OD-79 / 60mm	22,000	2,680	35	1,20	17	1,512
000-1726	Air Core Coil 23,000mH +/-3% 2,730Ω wire 1,20mm=17AWG OD-79 / 60mm	23,000	2,730	35	1,20	17	1,547
000-1727	Air Core Coil 24,000mH +/-3% 2,790Ω wire 1,20mm=17AWG OD-79 / 60mm	24,000	2,790	35	1,20	17	1,589
000-0830	Air Core Coil 25,000mH +/-3% 19,710Ω wire 0,40mm=26AWG OD-28 / 47mm	25,000	19,710	10	0,40	26	0,159
000-1659	Air Core Coil 25,000mH +/-3% 3,700Ω wire 1,00mm=18AWG OD-70 / 60mm	25,000	3,700	35	1,00	18	1,149
000-1663	Air Core Coil 25,000mH +/-3% 7,000Ω wire 0,70mm=21AWG OD-55 / 60mm	25,000	7,000	35	0,70	21	0,545
000-0876	Air Core Coil 27,000mH +/-3% 13,830Ω wire 0,50mm=24AWG OD-47 / 30mm	27,000	13,830	25	0,50	24	0,225
000-1690	Air Core Coil 27,000mH +/-3% 7,300Ω wire 0,70mm=21AWG OD-55 / 60mm	27,000	7,300	35	0,70	21	0,566
000-0898	Air Core Coil 28,000mH +/-3% 5,970Ω wire 0,80mm=20AWG OD-60 / 60mm	28,000	5,970	35	0,80	20	0,761
000-0959	Air Core Coil 30,000mH +/-3% 8,000Ω wire 0,70mm=21AWG OD-56 / 60mm	30,000	8,000	35	0,70	21	0,597
000-0806	Air Core Coil 32,000mH +/-3% 3,900Ω wire 1,00mm=18AWG OD-93 / 30mm	32,000	3,900	25	1,00	18	1,295
000-0850	Air Core Coil 34,000mH +/-3% 6,820Ω wire 0,80mm=20AWG OD-64 / 60mm	34,000	6,820	35	0,80	20	0,859
000-0874	Air Core Coil 34,000mH +/-3% 4,180Ω wire 1,00mm=18AWG OD-92 / 30mm	34,000	4,180	25	1,00	18	1,260
000-0236	Air Core Coil 30,000mH +/-3% 8,720Ω wire 0,70mm=21AWG OD-46 / 75mm	35,000	8,720	20	0,70	21	0,679
000-1662	Air Core Coil 35,000mH +/-3% 9,960Ω wire 0,70mm=21AWG OD-46 / 75mm	35,000	9,960	20	0,70	21	0,712
000-0979	Air Core Coil 39,000mH +/-3% 24,760Ω wire 0,40mm=26AWG OD-32 / 47mm	39,000	24,760	10	0,40	26	0,206
000-0216	Air Core Coil 40,000mH +/-3% 7,500Ω wire 0,80mm=20AWG OD-59 / 66mm	40,000	7,500	25	0,80	20	0,996
000-0816	Air Core Coil 50,000mH +/-3% 8,720Ω wire 0,80mm=20AWG OD-61 / 66mm	50,000	8,720	25	0,80	20	1,110
000-0229	Air Core Coil 65,000mH +/-3% 22,220Ω wire 0,50mm=24AWG OD-52 / 60mm	65,000	22,220	35	0,50	24	0,444
000-0817	Air Core Coil 100,000mH +/-3% 12,610Ω wire 0,80mm=20AWG OD-72 / 66mm	100,000	12,610	25	0,80	20	1,628
000-0229	Air Core Coil 65,000mH +/-3% 22,220Ω wire 0,50mm=24AWG OD-52 / 60mm	65,000	22,220	35	0,50	24	0,444
000-0817	Air Core Coil 100,000mH +/-3% 12,610Ω wire 0,80mm=20AWG OD-72 / 66mm	100,000	12,610	25	0,80	20	1,628